

Technical Note

ROMM Electronic Components

No.09051EAT01

Serial-in / Parallel-out Driver Series Serial-Parallel 3-input Driver

BA823F

Description

BA823F are an 8-bit serial-to-parallel-output driver, applicable for thermal printer heads or LED character display drivers.

Features

- 1) Capable of driving a maximum of 200mA.
- 2) Non-driving current consumption can be reduced by controlling the strobe timing pulse.
- 3) Output data terminal can be used for a cascade configuration.
- 4) Digital ground and power ground are separated.
- 5) TTL and CMOS allow driving.

Applications

Driver for thermal print head Driver for LED character display

●Absolute maximum ratings (Ta=25°C)

Parar	meter	Symbol	Limits	Unit
Power supply	y voltage	Vcc	7.0 ^{*1}	V
Power dissipation	BA823F	Pd	500* ³	mW
Input voltage	;	VIN MAX	+0.3 to +6.0	V
Operating te	mperature	Topr	-20 to +75	°C
Storage tem	perature	Tstg	-55 to +125	°C

*1 Voltage of O₀~O₇ terminals is 34V (Max.)

*2 Reduced by 5.5 mW/°C over 25°C.

*3 Reduced by 5.0 mW/°C over 25°C.







●Electrical characteristics (Unless otherwise specified, Ta=25°C, Vcc=+5.0V)

Parameter	Symbol	Min.	Тур.	Max.	Unit	Conditions	Test Circuit
Power supply	Vcc	4.5	5.0	5.5	V	Vcc terminal	Fig.2
Current dissipation(no load)1	lo1	-	4	6	mA	@All outputs = "0"	Fig.2
Current dissipation(no load)2	IO2	-	8	11	mA	@All outputs = "0"	Fig.2
Input low level voltage	VIL	-	-	0.8	V	-	Fig.2
Input high level voltage	Vін	2	-	-	V	-	Fig.2
Input low level current	lı∟	-	-	0.4	mA	VIN=4.5V	Fig.2
Input high level current	Ιн	-	-	100	μA	VIN=2.0V	Fig.3
Maximum output voltage	VO OFF	-	-	21.8	V	Ō 0 to Ō 7, Io=10μA	Fig.3
Output saturation voltage	Vo on	-	0.8	1.3	V	@lo=100mA sink	Fig.3
Output current	IOL	-	-	207	mA	External voltage = 11.8V	Fig.3
"H" output voltage	Vdoh	2.4	-	-	V	RL=10kΩ	Fig.3
"L" output voltage	Vdol	-	-	0.8	V	-	Fig.3
Minimum set up time	t1	-	-	300	ns	VIH=2.0V, VIL=0.8V	-
Minimum shift clock width	T2	-	-	1	μs	VIH=2.0V, VIL=0.8V	-
Minimum timing pulse width	T3	-	-	1	μs	VIH=2.0V,VIL=0.8V	-
Maximum transfer time	fMax	500	-	-	kHz	VIH=2.0V,VIL=0.8V	-

●Usage conditions range



Fig.2 Power supply voltage and current usage conditions

Fig.2: Conditions to use supply voltage and output current (per circuit) Maximum conditions of use in the diagram to the left, show the absolute maximum supply voltage and IC output current. This product should not exceed the usage conditions range.

Block diagram



Pin descriptions

Pin No.	Pin Name	Symbol	Function
2	SHIFT PULSE	С	Shift pulse of shift register
15	DATA INPUT	D1	Data input of shift register is stored during the shift pulse rise time.
1	STROBE	S	When "1" is effective, the content of shift register is outputted.
12	OUTPUT	Ō٥	"0" is effective when the content of register is "1" on the 1st bit is outputted.
11	OUTPUT	Ō1	"0" is effective when the content of register is "1" on the 2nd bit is outputted.
10	OUTPUT	Ō 2	"0" is effective when the content of register is "1" on the 3rd bit is outputted.
9	OUTPUT	Ōз	"0" is effective when the content of register is "1" on the 4th bit is outputted.
8	OUTPUT	Ō 4	"0" is effective when the content of register is "1" on the 5th bit is outputted.
7	OUTPUT	Ō5	"0" is effective when the content of register is "1" on the 6tht bit is outputted.
6	OUTPUT	Ō 6	"0" is effective when the content of register is "1" on the 7tht bit is outputted.
5	OUTPUT	Ō7	"0" is effective when the content of register is "1" on the 8th bit is outputted.
3	DATA OUTPUT	Do	Data having passed through the output circuit of \bar{O}_7 becomes the input of the next stage
16	Vcc	Vcc	5.0V .is used normally (±10%)
13	GND	GND1	Especially, GND of the output circuit of $\bar{O}_0 \sim \bar{O}_3$
4	GND	GND2	Especially, GND of the output circuit of $\overline{O}_4 \sim \overline{O}_7$
14	GND	GND(Dig)	Especially, GND of the logic circuit

Description of operation

BA823 is configured internally as shown in the block diagram. Terminals of clock C, data D1, and strobe S are used as input. Data input is synchronized with the clock, read serially during the rise time and latched at the rise time edge of the shifted shift register. The content of the set shift register appears on the output terminal of $\overline{O}_0 \sim \overline{O}_7$ when the strobe is input, as shown in the time chart of Fig.5. Pulse width is the same as that of the strobe input pulse.

Data output terminal D0, is a terminal used for cascade connection of the IC, where the output of the final stage of the shift register has appeared, and is connected to the next data input terminal D1. In this case, when the clock and the strobe are used in conjunction, output terminal can be increased by 8 bits at a time.

Measurement circuits



Item	SW1	SW2
Icc	1	1
Іін	2	1~3

Fig.3 lcc	1st measureme	nt circuit



Item	SW1	SW2	SWз
Vo on	1	1~8	1
Iol	1	1~8	1
VO OFF	2	1~8	2

 $IO = 10\mu A$ when VO OFF is measured VA = 30V when IO ON is measured

Fig.4 VO ON, VO OFF, IOL measurement circuit

Input conditions





Timing chart



Application example



Example: Print head using the strobe function Disabling the high current while the heating element is switched off is advantageous. Use for thermal printer (when the timing is 1 phase) example

Interfaces





(c) Serial data output



Fig.8

•Thermal derating curve



At repetition frequency 1Hz or higher



Notes for use

1. Absolute maximum ratings

An excess in the absolute maximum ratings, such as supply voltage, temperature range of operating conditions, etc., can break down the devices, thus making impossible to identify breaking mode, such as a short circuit or an open circuit. If any over rated values will expect to exceed the absolute maximum ratings, consider adding circuit protection devices, such as fuses.

2. Connecting the power supply connector backward

Connecting of the power supply in reverse polarity can damage IC. Take precautions when connecting the power supply lines. An external direction diode can be added.

3. Power supply lines

Design PCB layout pattern to provide low impedance GND and supply lines. To obtain a low noise ground and supply line, separate the ground section and supply lines of the digital and analog blocks. Furthermore, for all power supply terminals to ICs, connect a capacitor between the power supply and the GND terminal. When applying electrolytic capacitors in the circuit, not that capacitance characteristic values are reduced at low temperatures.

4. GND voltage

The potential of GND pin must be minimum potential in all operating conditions.

5. Inter-pin shorts and mounting errors

Use caution when positioning the IC for mounting on printed circuit boards. The IC may be damaged if there is any connection error or if pins are shorted together.

6. Actions in strong electromagnetic field

Use caution when using the IC in the presence of a strong electromagnetic field as doing so may cause the IC to malfunction.

7. Testing on application boards

When testing the IC on an application board, connecting a capacitor to a pin with low impedance subjects the IC to stress. Always discharge capacitors after each process or step. Always turn the IC's power supply off before connecting it to or removing it from a jig or fixture during the inspection process. Ground the IC during assembly steps as an antistatic measure. Use similar precaution when transporting or storing the IC.

8. Regarding input pin of the IC

This monolithic IC contains P+ isolation and P substrate layers between adjacent elements in order to keep them isolated. P-N junctions are formed at the intersection of these P layers with the N layers of other elements, creating a parasitic diode or transistor. For example, the relation between each potential is as follows:

When GND > Pin A and GND > Pin B, the P-N junction operates as a parasitic diode.

When GND > Pin B, the P-N junction operates as a parasitic transistor.

Parasitic diodes can occur inevitable in the structure of the IC. The operation of parasitic diodes can result in mutual interference among circuits, operational faults, or physical damage. Accordingly, methods by which parasitic diodes operate, such as applying a voltage that is lower than the GND (P substrate) voltage to an input pin, should not be used.





9. Ground Wiring Pattern

When using both small signal and large current GND patterns, it is recommended to isolate the two ground patterns, placing a single ground point at the ground potential of application so that the pattern wiring resistance and voltage variations caused by large currents do not cause variations in the small signal ground voltage. Be careful not to change the GND wiring pattern of any external components, either.

Ordering part number



SOP16



	Notes
No copy consent	ying or reproduction of this document, in part or in whole, is permitted without the of ROHM Co.,Ltd.
The con	tent specified herein is subject to change for improvement without notice.
The con	ntent specified herein is for the purpose of introducing ROHM's products (hereinafte
"Produc	its"). If you wish to use any such Product, please be sure to refer to the specifications
which ca	an be obtained from ROHM upon request.
Example	es of application circuits, circuit constants and any other information contained hereir
illustrate	e the standard usage and operations of the Products. The peripheral conditions mus
be taker	n into account when designing circuits for mass production.
Great ca	are was taken in ensuring the accuracy of the information specified in this document
Howeve	r, should you incur any damage arising from any inaccuracy or misprint of such
informat	tion, ROHM shall bear no responsibility for such damage.
The tech	nnical information specified herein is intended only to show the typical functions of and
example	es of application circuits for the Products. ROHM does not grant you, explicitly o
implicitly	y, any license to use or exercise intellectual property or other rights held by ROHM and
other pa	arties. ROHM shall bear no responsibility whatsoever for any dispute arising from the
use of se	uch technical information.
The Pro	ducts specified in this document are intended to be used with general-use electronic
equipment	ent or devices (such as audio visual equipment, office-automation equipment, commu-
nication	devices, electronic appliances and amusement devices).
The Pro	ducts specified in this document are not designed to be radiation tolerant.
While R Product	OHM always makes efforts to enhance the quality and reliability of its Products, a may fail or malfunction for a variety of reasons.
Please b	be sure to implement in your equipment using the Products safety measures to guard
against	the possibility of physical injury, fire or any other damage caused in the event of the
failure o	f any Product, such as derating, redundancy, fire control and fail-safe designs. ROHN
shall be	ar no responsibility whatsoever for your use of any Product outside of the prescribed
scope o	r not in accordance with the instruction manual.
The Pro	ducts are not designed or manufactured to be used with any equipment, device or
system	which requires an extremely high level of reliability the failure or malfunction of which
may res	ult in a direct threat to human life or create a risk of human injury (such as a medica
instrume	ent, transportation equipment, aerospace machinery, nuclear-reactor controller
fuel-con	troller or other safety device). ROHM shall bear no responsibility in any way for use o
any of th	ne Products for the above special purposes. If a Product is intended to be used for any
such sp	ecial purpose, please contact a ROHM sales representative before purchasing.
If you in	tend to export or ship overseas any Product or technology specified herein that may
be contr	rolled under the Foreign Exchange and the Foreign Trade Law, you will be required to
obtain a	license or permit under the Law.



Thank you for your accessing to ROHM product informations. More detail product informations and catalogs are available, please contact us.

ROHM Customer Support System

http://www.rohm.com/contact/



ООО "ЛайфЭлектроникс"

ИНН 7805602321 КПП 780501001 Р/С 40702810122510004610 ФАКБ "АБСОЛЮТ БАНК" (ЗАО) в г.Санкт-Петербурге К/С 3010181090000000703 БИК 044030703

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный) Email: org@lifeelectronics.ru

www.lifeelectronics.ru