



# Grove - Dust Sensor User Manual

Release date: 2015/9/23

Version: 1.0

Wiki: [http://www.seeedstudio.com/wiki/Grove - Dust sensor](http://www.seeedstudio.com/wiki/Grove_-_Dust_sensor)

Bazaar: <http://www.seeedstudio.com/depot/Grove-Dust-Sensor-p-1050.html>

## Document Revision History

---

Revision	Date	Author	Description
1.0	Sep 23, 2015	Jiankai.li	Create file

## Contents

Document Revision History .....	2
1. Introduction .....	2
2. Features .....	3
3. Application Ideas .....	4
4. Cautions .....	5
5. Specification .....	6
6. Usage .....	7
7. Resources .....	10
8. Reference .....	11
9. Related Projects .....	12
9.1 Air Quality Box .....	12
9.2 Share Your Awesome Projects with Us .....	12

### *Disclaimer*

*For physical injuries and possessions loss caused by those reasons which are not related to product quality, such as operating without following manual guide, natural disasters or force majeure, we take no responsibility for that.*

*Under the supervision of Seeed Technology Inc., this manual has been compiled and published which covered the latest product description and specification. The content of this manual is subject to change without notice.*

### *Copyright*

*The design of this product (including software) and its accessories is under tutelage of laws. Any action to violate relevant right of our product will be penalized through law. Please consciously observe relevant local laws in the use of this product.*

## 1. Introduction

---

This Dust Sensor measures the Particulate Matter level in air by counting the Lo Pulse Occupancy time(LPO time) in given time unit. LPO time is in proportion to PM concentration. This sensor can provide you pretty reliable data for air purifier system because it's still responsive to particulates whose diameter is 1um. [Note: This sensor use counting method to test dust concentration but not weight method, and the unit is pcs/L or pcs/0.01cf.](#)



## 2. Features

---

- Highly responsive
- Reliable
- ROHS/PEACH compliant

**Note:** New version updates output Hi Voltage from Approx. over 4.0V change to Approx over 4.5V.

### 3. Application Ideas

---

- Dust emission monitor
- [Air Quality Monitoring](#)

## 4. Cautions

---

- Please keep it upright.
- 3 min preheat time is required when used at the first time.
- Arbitrary operation may cause unexpected damage.
- Pins VR1 and VR2 come preset. **Please DON'T change the default configuration.**



## 5. Specification

---

Items	Min	Norm	Max	Unit
VCC	4.75	-	5.25	V
Standby Current Supply	-	90	-	mA
Detectable range of concentration	-	0~28,000 / 0 ~ 8000	-	pcs/liter / pcs/0.01cf
Operating Temperature Range	0	-	45	° C
Output Method	Negative Logic, Digital output, Hi over 4.0V(Rev.2) Lo: under 0.7V			
Detecting the particle diameter	>1 um			
Dimensions	59(W) × 45(H) × 22(D) [mm]			
Humidity Range	95%rh or less			

## 6. Usage

---

Here is a demo to show you how to obtain PM concentration data from this Grove - Dust Sensor.

1. Plug the dust sensor into digital port D8 on the [Grove - Base Shield](#). It can only be D8, because the operation of this sensor involves sampling, a function only can be achieved by D8, the capture input pin of Atmage328P, on Arduino/Seeeduino.

Also you can connect Grove - Dust sensor to Arduino UNO without Base Shield :

Arduino UNO	Dust Sensor
5V	Red wire
GND	Black wire
Digit 8	Yellow wire

2. Copy and paste the demo code below to a new Arduino sketch.

```

/* Grove - Dust Sensor Demo v1.0
Interface to Shinyei Model PPD42NS Particle Sensor
Program by Christopher Nafis
Written April 2012

http://www.seeedstudio.com/depot/grove-dust-sensor-p-1050.html
http://www.sca-shinyei.com/pdf/PPD42NS.pdf

JST Pin 1 (Black Wire) => Arduino GND
JST Pin 3 (Red wire)    => Arduino 5VDC
JST Pin 4 (Yellow wire) => Arduino Digital Pin 8
*/


int pin = 8;
unsigned long duration;
unsigned long starttime;
unsigned long sampletime_ms = 30000;//sampe 30s ;
unsigned long lowpulseoccupancy = 0;
float ratio = 0;
float concentration = 0;

void setup() {
  Serial.begin(9600);
  pinMode(8, INPUT);
  starttime = millis();//get the current time;
}
  
```

```
void loop() {
  duration = pulseIn(pin, LOW);
  lowpulseoccupancy = lowpulseoccupancy+duration;

  if ((millis()-starttime) > sampletime_ms)//if the sampel time == 30s
  {
    ratio = lowpulseoccupancy/(sampletime_ms*10.0); // Integer percentage 0=>100
    concentration = 1.1*pow(ratio,3)-3.8*pow(ratio,2)+520*ratio+0.62; // using spec sheet curve
    Serial.print("concentration = ");
    Serial.print(concentration);
    Serial.println(" pcs/0.01cf");
    Serial.println("\n");
    lowpulseoccupancy = 0;
    starttime = millis();
  }
}
```

In this program, the seeeduino samples the total duration of "logic low" in 30s, and this duration illustrates the dust density of environment. Open serial monitor, we can read air quality's value detected by sensor from pc serial port.




The result above consists of three parts: lowpulseoccupancy, ratio and concentration.


"lowpulseoccupancy" represents the Lo Pulse Occupancy Time(LPO Time) detected in given 30s. Its unit is microsecond.

"ratio" reflects on which level LPO Time takes up the whole sample time.

"concentration" is a figure that has physical meaning. It's calculated from the characteristic graph below by using the LPO time.



Here is a figure we tested dust concentration in office :



We can see the concentration of dust is very low in the evening, but it's higher in the afternoon. Maybe you can set a threshold value while the concentration is beyond a value. Also, if you wanna set the sensor more sensitive you can add a fan on the sensor, and add a 10k resistor between the Pin5 and Ground. More information please visit the blog of A.J.

## 7. Resources

---

- [Grove\\_ - \\_Dust\\_sensor datasheet](#)
- [De-construction of the Shinyei PPD42NS dust sensor](#) *Made by Tracy Allen*

## 8. Reference

---

- [Building a low-cost networked PM2.5 monitor](#) -- *Made by A.J.*
- [Measuring the Pickle Jr. – a modified PPD42 with an attached fan.](#) -- *Made by A.J.*
- [Testing the Shinyei PPD42NS](#) -- *Made by darell tan*
- [Air Quality Monitoring](#) -- *Made by Chris Nafis*

## 9. Related Projects

---

If you want to make some awesome projects by Dust Sensor, here's some projects for reference.

### 9.1 Air Quality Box



This is an IoT demo make by Seeeduino and [Grove](#).

More and More concern are being paid to the environmental air quality nowadays because the tiny granule in the around air can badly endanger people' s health. We always get the information of environment from our government department. But it' s the average value of the whole city / section. It can' t reflect the situation near by you accurately.

**I want to make it.**

### 9.2 Share Your Awesome Projects with Us

Born with the spirit of making and sharing, that is what we believe makes a maker.

And only because of this , the open source community can be as prosperous as it is today.

It does not matter what you are and what you have made, hacker, maker, artist and engineers, as long as you start sharing your works with others,

you are being part of the open source community and you are making your contributions .

Now share you awesome projects on with us on [Recipe](#), and win a chance to become the Core User of Seeed.

- Core Users, are those who showing high interests and significant contributions in Seeed products.

- We cooperate with our Core Users in the development of our new product, this, in another word, the Core Users will have the chance to experience any new products of Seeed before its official launch, and in return we expect valuable feedback from them to help us improving the product performance and user experience. And for most of cases if our Core Users have any good ideas for making things, we'll offer hardware pieces, PCBA services as well as technical support.  
Besides, further commercial cooperation with the Core Users is highly possible.

Get more information about Core User please email to: [recipe@seeed.cc](mailto:recipe@seeed.cc)



Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: [org@lifeelectronics.ru](mailto:org@lifeelectronics.ru)

[www.lifeelectronics.ru](http://www.lifeelectronics.ru)