

16 Channel Buck Mode LED Driver

FEATURES

- 4.5V to 45V Input Supply Range
- Up to 50mA LED Current per Channel
- 100mA, 45V Internal Switches
- Improvements vs LT3595

Pinout Allows 1-Sided PCB Layout Higher Maximum Switch Duty Cycle LED Current Accuracy (7% vs 8%) ±4% LED Current Matching

- 16 Independent LED Channels
- 5000:1 True Color PWM[™] Dimming Range
- LEDs Disconnected in Shutdown
- Internal Schottky Diodes
- 2MHz Switching Frequency
- R_{SFT} Pin Sets Master LED Current
- Typical Efficiency: 92%
- Open LED Detection and Thermal Protection
- 56-Pin 5mm × 9mm × 0.75mm QFN Package

APPLICATIONS

- LED Video Billboards
- LCD Televisions
- Stadium and Advertising Displays

DESCRIPTION


The LT®3595A is a high performance LED Driver designed to drive sixteen independent channels of up to 10 LEDs at currents up to 50mA. Series connection of the LEDs provides identical LED currents resulting in uniform brightness. Power switches, Schottky diodes, and compensation components are all internal, providing a small converter footprint and lower component cost. The high 2MHz switching frequency permits the use of tiny, low profile inductors and capacitors. A fixed frequency, current mode architecture results in stable operation over a wide range of supply and output voltage.


A single external resistor sets the LED current for all sixteen channels, and dimming is then controlled for each channel by pulse width modulating the individual PWM pins. LED current accuracy is 7%, channel-to-channel current matching is $\pm 4\%$ and the PWM dimming range is 5000:1. The part is available in a 5mm \times 9mm \times 0.75mm 56-pin QFN package.

 \mathcal{O} , LT, LTC and LTM are registered trademarks of Linear Technology Corporation. True Color PWM is a trademark of Linear Technology Corporation. All other trademarks are the property of their respective owners.

TYPICAL APPLICATION

16-Channel LED Driver (Three LEDs per Channel), 20mA Current






3595af

ABSOLUTE MAXIMUM RATINGS

(Note 1)

Input Voltage (V _{IN})	45V
L1-16 Voltage	
Supply Voltage (V _{CC})	
R _{SET} , OPENLED, PWM1-16, SHDN Voltage	6V
Operating Junction Temperature Range	
(Note 2)40°C to	125°C
Storage Temperature Range65°C to	125°C

PIN CONFIGURATION



ORDER INFORMATION

LEAD FREE FINISH	TAPE AND REEL	PART MARKING	PACKAGE DESCRIPTION	TEMPERATURE RANGE
LT3595AEUHH#PBF	LT3595AEUHH#TRPBF	3595A	56-Lead (5mm × 9mm) Plastic QFN	-40°C to 125°C

Consult LTC Marketing for parts specified with wider operating temperature ranges. Consult LTC Marketing for information on non-standard lead based finish parts.

For more information on lead free part marking, go to: http://www.linear.com/leadfree/ For more information on tape and reel specifications, go to: http://www.linear.com/tapeandreel/



ELECTRICAL CHARACTERISTICS The • denotes the specifications which apply over the full operating temperature range, otherwise specifications are at $T_A = 25^{\circ}C$, $V_{IN} = 45V$, $V_{CC} = 3.3V$, $PWM = \overline{SHDN} = \overline{OPENLED} = 3.3V$, $R_{SET} = 75k\Omega$, GND = 0V, unless otherwise noted.


PARAMETER	CONDITIONS		MIN	TYP	MAX	UNITS
V _{IN} Operating Voltage			4.5			V
V _{CC} Operating Voltage			3		5.5	V
V _{CC} Input Under Voltage Lockout				2.6	2.9	V
I _{VIN} Quiescent Current ON, No Switching				0.25		mA
I _{VIN} Quiescent Current in Shutdown	SHDN = 0V			15	40	μА
I _{VCC} Quiescent Current ON, No Switching	V _{CC} = 3.3V			17		mA
I _{VCC} Quiescent Current in Shutdown	V _{CC} = 3.3V, SHDN = 0V			3	10	μА
I _{L1-16} Output Current Accuracy	$R_{SET} = 75k\Omega$		18.6	20	21.4	mA
I _{L1-16} Channel-to-Channel Matching	$R_{SET} = 75k\Omega$	•		±1	±4	%
Switching Frequency			1.6	2	2.4	MHz
Maximum Duty Cycle		•	80	85		%
Switch Current Limit		•	90	120	150	mA
Switch V _{CESAT}	I _{SW1-16} = 50mA			450		mV
Switch Leakage Current	V _{SW1-16} = 45V			0.1	6	μА
Schottky Forward Drop	I _{SCHOTTKY} = 50mA			0.8		V
Schottky Leakage Current	$V_{SW1-16} = 0.7V$, $\overline{SHDN} = 0V$			0.1	4	μА
SHDN, PWM1-16 Input Low Voltage					0.4	V
SHDN, PWM1-16 Input High Voltage			1.6			V
SHDN Pin Bias Current	<u>SHDN</u> = 3.3V			35		μА
PWM1-16 Pin Bias Current	PWM1-16 = 3.3V			0.1	1	μА
OPENLED Pin Voltage	$V_{CC} = 3.3V$, $I_{\overline{OPENLED}} = 200\mu A$			0.12		V
OPENLED Pin Input Leakage Current	OPENLED = 3.3V			0.1	1	μА


Note 1: Stresses beyond those listed under Absolute Maximum Ratings may cause permanent damage to the device. Exposure to any Absolute Maximum Rating condition for extended periods may affect device reliability and lifetime.


Note 2: The LT3595A is guaranteed to meet performance specifications from 0°C to 125°C junction temperature. Specifications over the -40°C to 125°C operating junction temperature range are assured by design, characterization and correlation with statistical process controls.





TYPICAL PERFORMANCE CHARACTERISTICS $T_A = 25$ °C, unless otherwise noted.



















V_{CC} Quiescent Current








3595af




TYPICAL PERFORMANCE CHARACTERISTICS $T_A = 25$ °C, unless otherwise noted.









Switch Saturation Voltage (V_{CESAT}) 700




Schottky Forward Voltage Drop



Transient Response



OPENLED Waveforms



V_{IN} = 45V 10 LEDS AT 20mA



PIN FUNCTIONS

L1-16 (Pins 1, 3, 7, 9, 10, 12, 16, 18, 29, 31, 35, 37, 38, 40, 44, 46): LED Pins. Connection point for the anode of the highest LED in each string.

SW1-16 (Pins 2, 4, 6, 8, 11, 13, 15, 17, 30, 32, 34, 36, 39, 41, 43, 45): Switch Pins. Minimize trace area at these pins to minimize EMI. Connect the inductors to these pins.

 V_{IN} (Pins 5, 33): 4.5V to 45V Input Supply Pin. Must be locally bypassed. Both V_{IN} pins must be tied together.

PWM1-16 (Pins 19-22, 25-28, 47-50, 53-56): Input Pin for LED Dimming Function. The rising edge of each channel must be synchronized.

OPENLED (Pin 23): Open Collector Output for Reporting Faults. If any channel experiences an open LED connection, the OPENLED pin is pulled low.

SHDN (**Pin 24**): Shutdown. Tie to 1.6V or greater to enable the device. Tie below 0.4V to turn off the device.

GND (Pins 14, 42): Ground. Connect these pins to ground.

R_{SET} (Pin 51): External Resistor to Set the Master LED Current. The LED current is equal to:


$$I_{LED} = \frac{1.21V}{R_{SET}} \bullet 1240$$

where R_{SET} is the value of the external resistor. Use a kelvin for ground metal.

 V_{CC} (Pin 52): 3.3V Input Supply. Must be locally bypassed.

Exposed Pad (Pin 57): Ground. The Exposed Pad must be soldered to PCB. Use wide metal from backtab to the grounds of the input capacitors on V_{CC} and V_{IN} .

BLOCK DIAGRAM



OPERATION

The LT3595A uses a constant-frequency, current mode control scheme to provide excellent line and load regulation. Operation is best understood by referring to the Block Diagram. The oscillator, V-I converter and internal regulator are shared by the sixteen converters. The control circuitry, power switches, PWM comparators and Dimming Feedback Control (DFC) blocks are identical for all converters.

The LT3595A enters shutdown mode when the SHDN pin is lower than 400mV. If the SHDN pin is above 1.6V, then the LT3595A turns on. At the start of each oscillator cycle, the power switch is turned on. Current ramps up through the output capacitor, the inductor, and the switch to ground. When the voltage across the output capacitor is larger than the LEDs' forward voltage, current flows through the LEDs.

When the switch is on, a voltage proportional to the switch current is added to a stabilizing ramp and the resulting sum is fed into the positive terminal of the PWM comparator. When this voltage exceeds the level at the negative input of the PWM comparator, the PWM logic turns off the power switch. The level at the negative input of the PWM comparator is set by the error amplifier output. This voltage is set by the LED current and the bandgap reference. In this manner, the error amplifier sets the correct peak current level in the inductor to keep the LED output current in regulation. The external R_{SET} resistor is used to program the LED current from 10mA to 50mA.

Input Voltage Range

The minimum input voltage required to generate a specific output voltage in an LT3595A application is limited by its

4.5V input voltage or by its maximum duty cycle. The duty cycle is the fraction of time that the internal switch is on divided by the total period. It is determined by the input voltage and the voltage across the LEDs:

$$DC = \frac{V_{LED} + V_{D}}{V_{VIN} - V_{CESAT} + V_{D}}$$

where V_{LED} is the voltage drop across the LEDs, V_D is the Schottky forward drop, and V_{CESAT} is the saturation voltage of the internal switch. This leads to a minimum input voltage of:

$$V_{IN(MIN)} = \frac{V_{LED} + V_{D}}{DC_{MAX}} + V_{CESAT} - V_{D}$$

where DC_{MAX} is the minimum rating of maximum duty cycle.

The maximum input voltage is limited by the absolute maximum rating of 45V.

Pulse-Skipping

At low duty cycles, the LT3595A may enter pulse-skipping mode. Low duty cycle occurs at higher input voltages and lower LED count. The LT3595A can drive currents without pulse-skipping provided the voltage across the LED string is greater than 15% of the input supply voltage. If the current decreases to the point that the LED voltage is less than 15% of the input supply, the device may begin skipping pulses. This will result in some low frequency ripple, although the LED current remains regulated on an average basis down to 10mA.

OPERATION

Discontinuous Current Mode

The LT3595A can drive a 10-LED string at 15mA LED current operating in continuous conduction mode using the recommended external components shown in the application circuit on page 1 of this data sheet. As current is further reduced, the regulator enters discontinuous conduction mode. The photo in Figure 1 details circuit operation driving ten LEDs at 10mA load. The inductor current reaches zero during the discharge phase and the SW pin exhibits ringing. The ringing is due to the LC tank circuit formed by the inductor in combination with the switch and diode capacitance. This ringing is not harmful; far less spectral energy is contained in the ringing than in the switch transitions.




Figure 1. Switching Waveforms

APPLICATIONS INFORMATION

Inductor Selection

A 100µH inductor is recommended for most LT3595A applications. Although small size and high efficiency are major concerns, the inductor should have low core losses at 2MHz and low DCR (copper wire resistance). Some inductors that meet these criteria are listed in Table 1. An efficiency comparison of different inductors is shown in Figure 2.




Figure 2. Efficiency Comparison of Different Inductors

Table 1. Inductor Manufacturers

VENDOR	PART SERIES	INDUCTANCE RANGE (µH) RELEVANT TO LT3595A	DIMENSIONS (mm)
Coilcraft www.coilcraft.com	D01605 LPS4012 1812FS MSS5131	100 to 680 100 to 680 100 to 680 100 to 390	$5.4 \times 4.2 \times 1.8 \\ 4 \times 4 \times 1.2 \\ 5.8 \times 4.9 \times 3.8 \\ 5.1 \times 5.1 \times 3.1$
Sumida www.sumida.com	CDC4D20	100 to 680	$4.8\times4.8\times2$
Toko www.tokoam.com	D53LC	100 to 680	$5.2 \times 5.4 \times 3$
TDK www.component. tdk.com	VLCF4020T	100 to 330	4 × 4 × 2
Coiltronics www.cooperet.com	SD3812 SD52	100 to 330 100 to 330	$4 \times 4 \times 1.2$ $5.6 \times 5.2 \times 2$
Murata www.murata.com	LQH32M LQH43M	100 to 560 100 to 680	$3.2 \times 2.5 \times 2$ $4.5 \times 3.2 \times 2$

Capacitor Selection

The small size of ceramic capacitors make them ideal for LT3595A applications. Only X5R and X7R types should be used because they retain their capacitance over wider voltage and temperature ranges than other types such as Y5V or Z5U. Typically, $10\mu F$ capacitors on V_{IN} and V_{CC} are sufficient. The output capacitor used across the LED



string depends on the number of LEDs and can vary from $0.47\mu F$ to $1\mu F$. Refer to Table 2 for proper output capacitor selection.

Table 2. Recommended Output Capacitor Values ($V_{LED} = 3.5V$)

# LEDs	C _{OUT} (μF)
3-10	0.47
1-2	1

Table 3. Recommended Ceramic Capacitor Manufacturers

Taiyo Yuden	408-573-4150 www.t-yuden.com
TDK	847-803-6100 www.component.tdk.com
Murata	770-436-1300 www.murata.com
Kemet	800-533-1992 www.kemet.com

Table 3 shows a list of several ceramic capacitor manufacturers. Consult the manufacturers for detailed information on their entire selection of ceramic parts.

Open LED Detection

The LT3595A detects an open LED on any channel and reports it to the OPENLED pin. The fault also reports during startup until the output voltage and LED current are in regulation. Therefore, it can also be used as a "power ok" signal.

Programming LED Current

The set resistor (R_{SET} in the Block Diagram) controls the LED current in all sixteen channels. LED current as a function of the R_{SET} resistance is shown in the Typical Performance Characteristics. Common values for LED current and their required resistor values are listed in Table 4. Since resistor error directly translates to LED current error, precision resistors are preferred (1% is recommended). The maximum allowed resistor value is 150k.

Table 4. LED Current vs R_{SET} Resistance

R_{SET} ($k\Omega$)	I _{LED} (mA)
150	10
75.0	20
49.9	30
37.4	40
30.1	50

Dimming Control

The sixteen PWM1-16 inputs control the dimming function. Each channel is modulated by its corresponding PWM1-16 input. On a rising edge of any PWM1-16, the IC's internal support circuitry is enabled and the specific channel turns on. LED current flows in the channel until the falling edge of the PWM1-16 input. In this way, the average LED current is modulated. The minimum on time

of a channel is $2\mu s$ and the maximum period is 10ms (at 100Hz). Therefore, the maximum dimming ratio is 5000:1. Since the maximum R_{SET} produces 10mA, the minimum modulated LED current is $2\mu A$.

When multiple channels are modulated, the rising edges of PWM1-16 must be synchronized. The falling edges may be asynchronous. A sample timing diagram is shown in Figure 3.




Figure 3. Timing Diagram for Multi-Channel Modulation



Board Layout Considerations

As with all switching regulators, careful attention must be paid to the PCB board layout and component placement. To prevent electromagnetic interference (EMI) problems, proper layout of high frequency switching paths is essential. Minimize the length and area of all traces connected to

the SW1-16 and PWM1-16 pins. Keep the sense voltage pins (V_{IN} and L1-16) away from the switching nodes. Place $C_{OUT1-16}$ and C_{IN} close to the V_{IN} pins. Always use a ground plane under the switching regulator to minimize interplane coupling. Recommended component placement is shown in Figures 4-7.




Figure 4. PCB Layer 1




Figure 5. PCB Layer 2






Figure 6. PCB Layer 3






Figure 7. PCB Layer 4

TYPICAL APPLICATION


30W LED Driver for 160 LEDs (16 Strings, 10 LEDs per String) at 50mA



Conversion Efficiency



5000:1 PWM Dimming at 100Hz




3595af



PACKAGE DESCRIPTION

$\begin{array}{c} \text{UHH Package} \\ \text{56-Lead Plastic QFN (5mm} \times \text{9mm)} \end{array}$

(Reference LTC DWG # 05-08-1727 Rev A)





ON THE TOP AND BOTTOM OF PACKAGE

TYPICAL APPLICATION

16-Channel LED Driver (Three LEDs per Channel), 20mA Current

V_{IN} 15V TO 0.47µF I_{SW} 20mA/DIV \$100k I_{LEI} 10mA/DI\ PWM9 PWM10 PWM11 PWM12 PWM13 LED BRIGHT-NESS CONTROL 400ns/DIV LED BRIGHTNESS PWM4 PWM5 V_{IN} = 15V 3 LEDS AT 20mA T = 10ms LT3595A CONTROL PWM14 PWM15 PWM16 $t_{ON} = 2\mu s$ PWM8 3V TO 5.5V

RELATED PARTS

PART NUMBER	DESCRIPTION	COMMENTS
LT3463/ LT3463A	Dual Output, Boost/Inverter, 250mA I _{SW} , Constant Off-Time, High Efficiency Step-Up DC/DC Converter with Integrated Schottky Diodes	V_{IN} : 2.3V to 15V, $V_{OUT(MAX)}$ = ±40V, I_Q = 40 μ A, I_{SD} < 1 μ A, 3mm \times 3mm DFN-10 Package
LT3465/ LT3465A	Constant-Current, 1.2MHz/2.7MHz, High Efficiency White LED Boost Regulator with Integrated Schottky Diode	V_{IN} : 2.7V to 16V, $V_{OUT(MAX)}$ = 34V, I_Q = 1.9mA, I_{SD} < 1 μ A, ThinSOT TM Package
LT3466/ LT3466-1	Dual Constant-Current, 2MHz, High Efficiency White LED Boost Regulator with Integrated Schottky Diode	$V_{IN}\!\!: 2.7V$ to 24V, $V_{OUT(MAX)}$ = 40V, I_Q = 5mA, I_{SD} < 16 μA , 3mm \times 3mm DFN-10 Package
LT3474	36V, 1A (I _{LED}), 2MHz, Step-Down LED Driver	V_{IN} : 4V to 36V, $V_{\text{OUT}(\text{MAX})}$ = 13.5V, 400:1 True Color PWM TM , I_{SD} < 1 μ A, TSSOP-16E Package
LT3475	Dual 1.5A (I _{LED}), 36V, 2MHz, Step-Down LED Driver	V_{IN} : 4V to 36V, $V_{\text{OUT}(\text{MAX})}$ = 13.5V, 3000:1 True Color PWM, I_{SD} < 1 μ A, TSSOP-20E Package
LT3476	Quad Output 1.5A, 2MHz High Current LED Driver with 1000:1 Dimming	V_{IN} : 2.8V to 16V, $V_{OUT(MAX)}$ = 36V, 1000:1 True Color PWM, I_{SD} < 10 μ A, 5mm \times 7mm QFN-10 Package
LT3486	Dual 1.3A , 2MHz High Current LED Driver	V_{IN} : 2.5V to 24V, $V_{\text{OUT}(\text{MAX})}$ = 36V, 1000:1 True Color PWM, I_{SD} < 1 μ A, 5mm \times 3mm DFN and TSSOP-16E Packages
LT3491	Constant-Current, 2.3MHz, High Efficiency White LED Boost Regulator with Integrated Schottky Diode	V_{IN} : 2.5V to 12V, $V_{OUT(MAX)}$ = 27V, I_Q = 2.6mA, I_{SD} < 8 μ A, 2mm \times 2mm DFN-6 and SC70 Packages
LT3497	Dual 2.3MHz, Full Function LED Driver with Integrated Schottky Diodes and 250:1 True Color PWM Dimming	V_{IN} : 2.5V to 10V, $V_{OUT(MAX)}$ = 32V, I_Q = 6 μA , I_{SD} < 12 μA , 3mm \times 2mm DFN-10 Package
LT3498	2.3MHz, 20mA LED Driver and OLED Driver with Integrated Schottky Diodes	V_{IN} : 2.5V to 12V, $V_{OUT(MAX)}$ = 32V, I_Q = 1.65mA, I_{SD} < 9 μA , 3mm \times 2mm DFN-12 Package
LT3517/LT3518	2.3A/1.3A 45V, 2.5MHz Full Featured LED Driver with True Color PWM Dimming	V_{IN} : 3V to 30V/40V, $V_{\text{OUT}(\text{MAX})}$ = 42V, 3000:1 True Color PWM, I_{SD} < 5 μ A, 4mm × 4mm QFN-16 Package
LT3590	48V Buck Mode LED Driver	$V_{IN}\!\!:4.5V$ to 55V, $V_{OUT(MAX)}$ = 5V, I_Q = 700 μA , I_{SD} < 15 μA , 2mm \times 2mm DFN-16 and SC70 Packages
LT3591	Constant-Current, 1MHz, High Efficiency White LED Boost Regulator with Integrated Schottky Diode and 80:1 True Color PWM Dimming	$V_{IN}\!\!: 2.5V$ to 12V, $V_{OUT(MAX)}$ = 40V, I_Q = 4mA, I_{SD} $<$ 9 μA , 3mm \times 2mm DFN-8 Package

0.47µF

True Color PWM and ThinSOT are trademarks of Linear Technology Corporation.



5000:1 PWM Dimming at 100Hz



OOO «ЛайфЭлектроникс" "LifeElectronics" LLC

ИНН 7805602321 КПП 780501001 P/C 40702810122510004610 ФАКБ "АБСОЛЮТ БАНК" (ЗАО) в г.Санкт-Петербурге К/С 3010181090000000703 БИК 044030703

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный) Email: org@lifeelectronics.ru