CS3845B

Current Mode PWM Control Circuit with 50% Max Duty Cycle

Description

The CS3845B provides all the necessary features to implement off-line fixed frequency current-mode control with a minimum number of external components.


The CS3845B incorporates a precision temperature-controlled oscillator to minimize variations in frequency. An internal toggle flip-flop, which blanks the output off every other clock cycle, ensures that the duty-cycle never exceeds 50%. The undervoltage lockout feature ensures that V_{REF} is stabilized within specification before the output stage is enabled. **The CS3845B has been optimized for lower start up current (500μA max).**

Other features include 1% trimmed band gap reference, pulse-by-pulse current limiting, and a high-current totem pole output for driving capacitive loads.

Absolute Maximum Ratings

Supply Voltage (I_{CC}<30mA) .....Self Limiting
Supply Voltage (Low Impedance Source).....30V
Output Current .....±1A
Output Energy (Capacitive Load) 5μJ
Analog Inputs (V_{FB}, V_{SENSE}).....-0.3V to 5.5V
Error Amp Output Sink Current.....10mA
Lead Temperature Soldering
Wave Solder (through hole styles only) .....10 sec. max, 260°C peak
Reflow (SMD styles only) .....60 sec. max above 183°C, 230°C peak

Block Diagram




Features


- Optimized for Off-line Use
- Temperature Compensated Oscillator
- 50% Maximum Duty-cycle Clamp
- Low Start-up Current (500μA max)
- Pulse-by-pulse Current Limiting
- Undervoltage Active Pull Down
- Double Pulse Suppression
- 1% Trimmed Bandgap Reference
- High Current Totem Pole Output

Package Options

8 Lead PDIP & SO



14 Lead SO Narrow



Cherry Semiconductor Corporation
2000 South County Trail, East Greenwich, RI 02818
Tel: (401)885-3600 Fax: (401)885-5786
Email: info@cherry-semi.com
Web Site: www.cherry-semi.com

Electrical Characteristics: $0 \le T_A \le 70^\circ C$, V_{CC}=15V; R_T=10kΩ, C_T=3.3nF for sawtooth mode, unless otherwise stated

PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNITS
■ Reference Section					
Output Voltage	T_J=25°C, I_{REF}=1mA	4.90	5.00	5.10	V
Line Regulation	$12 \le V_{CC} \le 25V$		6	20	mV
Load Regulation	$1 \le I_{REF} \le 20mA$		6	25	mV
Temperature Stability	(Note 1)		0.2	0.4	mV/°C
Total Output Variation	Line, Load, Temp. (Note 1)	4.82		5.18	V
Output Noise Voltage	$10Hz \le f \le 10kHz$, T_J=25°C (Note 1)		50		μV
Long Term Stability	T_A=125°C, 1000 Hrs. (Note 1)		5	25	mV
Output Short Circuit	T_A=25°C	-30	-100	-180	mA
■ Oscillator Section					
Initial Accuracy	Sawtooth Mode, T_J=25°C	47	52	57	kHz
Voltage Stability	$12 \le V_{CC} \le 25V$		0.2	1.0	%
Temperature Stability	Sawtooth Mode $T_{MIN} \le T_A \le T_{MAX}$ (Note 1)		5		%
Amplitude	V_{OSC} (peak to peak)(Note 1)		17		V
Discharge	T_J=25°C; (Note 1) $T_{MIN} \le T_A \le T_{MAX}$ (Note 1)	7.5 7.2	8.3	9.3 9.5	mA mA
■ Error Amp Section					
Input Voltage	V_{COMP}=2.5V	2.42	2.50	2.58	V
Input Bias Current	V_{FB}=0V		-0.3	-2.0	μA
AVOL	$2 \le V_{OUT} \le 4V$	65	90		dB
Unity Gain Bandwidth	(Note 1)	0.7	1.0		MHz
PSRR	$12 \le V_{CC} \le 25V$	60	70		dB
Output Sink Current	V_{FB}=2.7V, V_{COMP}=1.1V	2	6		mA
Output Source Current	V_{FB}=2.3V, V_{COMP}=5V	-0.5	-0.8		mA
V_{OUT} HIGH	V_{FB}=2.3V, R_L15kΩ to Gnd	5	6		V
V_{OUT} LOW	V_{FB}=2.7V, R_L=15kΩ to V_{REF}		0.7	1.1	V
■ Current Sense Section					
Gain	(Notes 2&3)	2.85	3.00	3.15	V/V
Maximum Input Signal	V_{COMP}=5V (Note 2)	0.9	1.0	1.1	V
PSRR	$12 \le V_{CC} \le 25V$ (Note 2)		70		dB
Input Bias Current	V_{Sense}=0V		-2	-10	μA
Delay to Output	T_J=25°C (Note 1)		150	300	ns
■ Output Section					
Output Low Level	I_{SINK}=20mA I_{SINK}=200mA		0.1 1.5	0.4 2.2	V V
Output High Level	I_{SOURCE}=20mA I_{SOURCE}=200mA	13.0 12.0	13.5 13.5		V V
Rise Time	T_J=25°C, C_L=1nF (Note 1)		50	150	ns
Fall Time	T_J=25°C, C_L=1nF (Note 1)		50	150	ns

Electrical Characteristics: continued


PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNITS
■ Total Standby Current					
Start-Up Current			300	500	μA
Operating Supply Current	V_{FB}=V_{Sense}=0V R_T=10kΩ, C_T=3.3nF		11	17	mA
V_{CC} Zener Voltage	I_{CC}=25mA		34		V
■ PWM Section					
Maximum Duty Cycle		46	48	50	%
Minimum Duty Cycle				0	%
■ Under-Voltage Lockout Section					
Start Threshold		7.8	8.4	9.0	V
Min. Operating Voltage	After Turn On	7.0	7.6	8.2	V

Notes:
1. These parameters, although guaranteed, are not 100% tested in production.
2. Parameter measured at trip point of latch with V_{FB}=0
3. Gain defined as: $A = \frac{\Delta V_{COMP}}{\Delta V_{Sense}}$; $0 \le V_{Sense} \le 0.8V$.

Package Pin Description

PACKAGE PIN #		PIN SYMBOL	FUNCTION
8L PDIP & SO	**14L SO**		
1	1	COMP	Error amp output, used to compensate error amplifier
2	3	V_{FB}	Error amp inverting input
3	5	Sense	Noninverting input in Current Sense Comparator
4	7	OSC	Oscillator timing network with Capacitor to Gnd, resistor to V_{REF}
5	9	Gnd	Ground
6	10	V_{OUT}	Output drive pin
7	12	V_{CC}	Positive power supply
8	14	V_{REF}	Output of 5V internal reference
	8	Pwr Gnd	Output driver Gnd
	11	V_{CC} Pwr	Output driver positive supply
	2, 4, 6, 13	NC	No Connection

Test Circuit



Circuit Description




Figure 1: Startup voltage for CS3845B.

Undervoltage Lockout

During Undervoltage Lockout (Figure 1), the output driver is biased to sink minor amounts of current. The output should be shunted to ground with a resistor to prevent activating the power switch with extraneous leakage currents.

PWM Waveform

To generate the PWM waveform, the control voltage from the error amplifier is compared to a current sense signal which represents the peak output inductor current (Figure 2). An increase in V_{CC} causes the inductor current slope to increase, thus reducing the duty cycle. This is an inherent feed-forward characteristic of current mode control, since the control voltage does not have to change during changes of input supply voltage.

When the power supply sees a sudden large output current increase, the control voltage will increase allowing the duty cycle to momentarily increase. Since the duty cycle tends to exceed the maximum allowed to prevent transformer saturation in some power supplies, the internal oscillator waveform provides the maximum duty cycle clamp as programmed by the selection of OSC components.




Figure 2: Timing Diagram




Figure 3: Timing Parameters.

Setting the Oscillator

The parameters T_c and T_d can be determined as follows:

$$t_c = R_T C_T \ln\left(\frac{V_{REF} - V_{lower}}{V_{REF} - V_{upper}}\right)$$

$$t_d = R_T C_T \ln\left(\frac{V_{REF} - I_d R_T - V_{lower}}{V_{REF} - I_d R_T - V_{upper}}\right)$$

Substituting in typical values for the parameters in the above formulas:

$V_{REF} = 5.0V$, $V_{upper} = 2.7V$, $V_{lower} = 1.0V$, $I_d = 8.3mA$, then

$$t_c \approx 0.5534 R_T C_T$$

$$t_d = R_T C_T \ln\left(\frac{2.3 - 0.0083\ R_T}{4.0 - 0.0083\ R_T}\right)$$

For better accuracy R_T should be ≥10kΩ.

Grounding

High peak currents associated with capacitive loads necessitate careful grounding techniques. Timing and bypass capacitors should be connected close to Gnd in a single point ground.

The transistor and 5kΩ potentiometer are used to sample the oscillator waveform and apply an adjustable ramp to Sense.

Package Specification


PACKAGE DIMENSIONS IN mm (INCHES)

Lead Count	D			
	Metric		English	
	Max	Min	Max	Min
8 Lead PDIP	10.16	9.02	.400	.355
8 Lead SO Narrow	5.00	4.80	.197	.189
14 Lead SO Narrow	8.75	8.55	.344	.337

PACKAGE THERMAL DATA


Thermal Data		8 L PDIP	8L SO	14 L SO	
R_{QJC}	typ	52	45	30	°C/W
R_{QJA}	typ	100	165	125	°C/W

PDIP: 300 mil wide



REF: JEDEC MS-001

SO Narrow; 150 mil wide



REF: JEDEC MS-012

Ordering Information

Part Number	0°C to 70°C	Description
CS3845BGN8	•	8L PDIP
CS3845BGD8	•	8L SO
CS3845BGDR8	•	8L SO *(tape & reel)*
CS3845BGD14	•	14L SO
CS3845BGDR14	•	14L SO *(tape & reel)*

Cherry Semiconductor Corporation reserves the right to make changes to the specifications without notice. Please contact Cherry Semiconductor Corporation for the latest available information.

© 1999 Cherry Semiconductor Corporation

LifeElectronics
Живое партнерство

ООО «ЛайфЭлектроникс» **“LifeElectronics” LLC**

ИНН 7805602321 КПП 780501001 Р/С 40702810122510004610 ФАКБ "АБСОЛЮТ БАНК" (ЗАО) в г.Санкт-Петербурге К/С 30101810900000000703 БИК 044030703

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- *Конкурентоспособные цены и скидки постоянным клиентам.*
- *Специальные условия для постоянных клиентов.*
- *Подбор аналогов.*
- *Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.*

- *Приемлемые сроки поставки, возможна ускоренная поставка.*
- *Доставку товара в любую точку России и стран СНГ.*
- *Комплексную поставку.*
- *Работу по проектам и поставку образцов.*
- *Формирование склада под заказчика.*

- *Сертификаты соответствия на поставляемую продукцию (по желанию клиента).*
- *Тестирование поставляемой продукции.*
- *Поставку компонентов, требующих военную и космическую приемку.*
- *Входной контроль качества.*
- *Наличие сертификата ISO.*

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- *Регистрацию проекта у производителя компонентов.*
- *Техническую поддержку проекта.*
- *Защиту от снятия компонента с производства.*
- *Оценку стоимости проекта по компонентам.*
- *Изготовление тестовой платы монтаж и пусконаладочные работы.*

Тел: +7 (812) 336 43 04 (многоканальный)
Email: org@lifeelectronics.ru

www.lifeelectronics.ru