FAIRCHILD SEMICONDUCTOR®

December 2012

# FDB3682 / FDP3682

## N-Channel PowerTrench® MOSFET
## 100V, 32A, 36mΩ


### Features

- $r_{DS(ON)}$ = 32mΩ (Typ.), $V_{GS}$ = 10V, $I_D$ = 32A
- $Q_g$(tot) = 18.5nC (Typ.), $V_{GS}$ = 10V
- Low Miller Charge
- Low $Q_{RR}$ Body Diode
- UIS Capability (Single Pulse and Repetitive Pulse)


### Applications

- DC/DC converters and Off-Line UPS
- Distributed Power Architectures and VRMs
- High Voltage Synchronous Rectifier


Formerly developmental type 82755




TO-263AB
FDB SERIES




TO-220AB
FDP SERIES




## MOSFET Maximum Ratings $T_C$ = 25°C unless otherwise noted

| Symbol | Parameter | Ratings | Units |
|---|---|---|---|
| $V_{DSS}$ | Drain to Source Voltage | 100 | V |
| $V_{GS}$ | Gate to Source Voltage | ±20 | V |
| $I_D$ | Drain Current<br>Continuous ($T_C$ = 25°C, $V_{GS}$ = 10V) | 32 | A |
| | Continuous ($T_C$ = 100°C, $V_{GS}$ = 10V) | 23 | A |
| | Continuous ($T_{amb}$ = 25°C, $V_{GS}$ = 10V, $R_{\theta JA}$ = 43°C/W) | 6 | A |
| | Pulsed | Figure 4 | A |
| $E_{AS}$ | Single Pulse Avalanche Energy (Note 1) | 55 | mJ |
| $P_D$ | Power dissipation | 95 | W |
| | Derate above 25°C | 0.63 | W/°C |
| $T_J$, $T_{STG}$ | Operating and Storage Temperature | -55 to 175 | °C |

## Thermal Characteristics

| | | | |
|---|---|---|---|
| $R_{\theta JC}$ | Thermal Resistance Junction to Case TO-220, TO-263 | 1.58 | °C/W |
| $R_{\theta JA}$ | Thermal Resistance Junction to Ambient TO-220, TO-263 (Note 2) | 62 | °C/W |
| $R_{\theta JA}$ | Thermal Resistance Junction to Ambient TO-263, 1in$^2$ copper pad area | 43 | °C/W |

©2012 Fairchild Semiconductor Corporation

## Package Marking and Ordering Information

| Device Marking | Device | Package | Reel Size | Tape Width | Quantity |
|---|---|---|---|---|---|
| FDB3682 | FDB3682 | TO-263AB | 330mm | 24mm | 800 units |
| FDP3682 | FDP3682 | TO-220AB | Tube | N/A | 50 units |

## Electrical Characteristics $T_C$ = 25°C unless otherwise noted

| Symbol | Parameter | Test Conditions | Min | Typ | Max | Units |
|---|---|---|---|---|---|---|
| **Off Characteristics** | | | | | | |
| $B_{VDSS}$ | Drain to Source Breakdown Voltage | $I_D$ = 250µA, $V_{GS}$ = 0V | 100 | - | - | V |
| $I_{DSS}$ | Zero Gate Voltage Drain Current | $V_{DS}$ = 80V | - | - | 1 | µA |
| | | $V_{GS}$ = 0V, $T_C$ = 150°C | - | - | 250 | |
| $I_{GSS}$ | Gate to Source Leakage Current | $V_{GS}$ = ±20V | - | - | ±100 | nA |
| **On Characteristics** | | | | | | |
| $V_{GS(TH)}$ | Gate to Source Threshold Voltage | $V_{GS}$ = $V_{DS}$, $I_D$ = 250µA | 2 | - | 4 | V |
| $r_{DS(ON)}$ | Drain to Source On Resistance | $I_D$=32A, $V_{GS}$=10V | - | 0.032 | 0.036 | Ω |
| | | $I_D$ = 16A, $V_{GS}$ = 6V, | - | 0.040 | 0.060 | |
| | | $I_D$=32A, $V_{GS}$=10V, $T_C$=175°C | - | 0.080 | 0.090 | |
| **Dynamic Characteristics** | | | | | | |
| $C_{ISS}$ | Input Capacitance | $V_{DS}$ = 25V, $V_{GS}$ = 0V, f = 1MHz | - | 1250 | - | pF |
| $C_{OSS}$ | Output Capacitance | | - | 190 | - | pF |
| $C_{RSS}$ | Reverse Transfer Capacitance | | - | 45 | - | pF |
| $Q_{g(TOT)}$ | Total Gate Charge at 10V | $V_{GS}$ = 0V to 10V; $V_{DD}$ = 50V, $I_D$ = 32A, $I_g$ = 1.0mA | - | 18.5 | 28 | nC |
| $Q_{g(TH)}$ | Threshold Gate Charge | $V_{GS}$ = 0V to 2V; $V_{DD}$ = 50V, $I_D$ = 32A, $I_g$ = 1.0mA | - | 2.4 | 3.6 | nC |
| $Q_{gs}$ | Gate to Source Gate Charge | $V_{DD}$ = 50V, $I_D$ = 32A, $I_g$ = 1.0mA | - | 6.5 | - | nC |
| $Q_{gs2}$ | Gate Charge Threshold to Plateau | $V_{DD}$ = 50V, $I_D$ = 32A, $I_g$ = 1.0mA | - | 4.1 | - | nC |
| $Q_{gd}$ | Gate to Drain “Miller” Charge | $V_{DD}$ = 50V, $I_D$ = 32A, $I_g$ = 1.0mA | - | 4.6 | - | nC |
| **Resistive Switching Characteristics** ($V_{GS}$ = 10V) | | | | | | |
| $t_{ON}$ | Turn-On Time | $V_{DD}$ = 50V, $I_D$ = 32A, $V_{GS}$ = 10V, $R_{GS}$ = 16Ω | - | - | 83 | ns |
| $t_{d(ON)}$ | Turn-On Delay Time | | - | 9 | - | ns |
| $t_r$ | Rise Time | | - | 46 | - | ns |
| $t_{d(OFF)}$ | Turn-Off Delay Time | | - | 26 | - | ns |
| $t_f$ | Fall Time | | - | 32 | - | ns |
| $t_{OFF}$ | Turn-Off Time | | - | - | 87 | ns |
| **Drain-Source Diode Characteristics** | | | | | | |
| $V_{SD}$ | Source to Drain Diode Voltage | $I_{SD}$ = 32A | - | - | 1.25 | V |
| | | $I_{SD}$ = 16A | - | - | 1.0 | V |
| $t_{rr}$ | Reverse Recovery Time | $I_{SD}$ = 32A, $dI_{SD}/dt$ = 100A/µs | - | - | 55 | ns |
| $Q_{RR}$ | Reverse Recovery Charge | $I_{SD}$ = 32A, $dI_{SD}/dt$ = 100A/µs | - | - | 90 | nC |

**Notes:**
**1:** Starting $T_J$ = 25°C, L = 0.27mH, $I_{AS}$ = 20A.
**2:** Pulse Width = 100s

## Typical Characteristics $T_C$ = 25°C unless otherwise noted





**Figure 1. Normalized Power Dissipation vs Ambient Temperature**





**Figure 2. Maximum Continuous Drain Current vs Case Temperature**





**Figure 3. Normalized Maximum Transient Thermal Impedance**





**Figure 4. Peak Current Capability**

## Typical Characteristics $T_C$ = 25°C unless otherwise noted






**Figure 5. Forward Bias Safe Operating Area**




NOTE: Refer to Fairchild Application Notes AN7514 and AN7515

**Figure 6. Unclamped Inductive Switching Capability**





**Figure 7. Transfer Characteristics**





**Figure 8. Saturation Characteristics**





**Figure 9. Drain to Source On Resistance vs Drain Current**





**Figure 10. Normalized Drain to Source On Resistance vs Junction Temperature**

## Typical Characteristics $T_C$ = 25°C unless otherwise noted





**Figure 11. Normalized Gate Threshold Voltage vs Junction Temperature**





**Figure 12. Normalized Drain to Source Breakdown Voltage vs Junction Temperature**





**Figure 13. Capacitance vs Drain to Source Voltage**





**Figure 14. Gate Charge Waveforms for Constant Gate Currents**

## Test Circuits and Waveforms





Figure 15. Unclamped Energy Test Circuit





Figure 16. Unclamped Energy Waveforms





Figure 17. Gate Charge Test Circuit





Figure 18. Gate Charge Waveforms





Figure 19. Switching Time Test Circuit





Figure 20. Switching Time Waveforms

## Thermal Resistance vs. Mounting Pad Area

The maximum rated junction temperature, $T_{JM}$, and the thermal resistance of the heat dissipating path determines the maximum allowable device power dissipation, $P_{DM}$, in an application. Therefore the application's ambient temperature, $T_A$ ($^oC$), and thermal resistance $R_{\theta JA}$ ($^oC/W$) must be reviewed to ensure that $T_{JM}$ is never exceeded. Equation 1 mathematically represents the relationship and serves as the basis for establishing the rating of the part.

$$P_{DM} = \frac{(T_{JM} - T_A)}{R_{\theta JA}} \quad \text{(EQ. 1)}$$

In using surface mount devices such as the TO-263 package, the environment in which it is applied will have a significant influence on the part's current and maximum power dissipation ratings. Precise determination of $P_{DM}$ is complex and influenced by many factors:

1. Mounting pad area onto which the device is attached and whether there is copper on one side or both sides of the board.
2. The number of copper layers and the thickness of the board.
3. The use of external heat sinks.
4. The use of thermal vias.
5. Air flow and board orientation.
6. For non steady state applications, the pulse width, the duty cycle and the transient thermal response of the part, the board and the environment they are in.

Fairchild provides thermal information to assist the designer's preliminary application evaluation. Figure 21 defines the $R_{\theta JA}$ for the device as a function of the top copper (component side) area. This is for a horizontally positioned FR-4 board with 1oz copper after 1000 seconds of steady state power with no air flow. This graph provides the necessary information for calculation of the steady state junction temperature or power dissipation. Pulse applications can be evaluated using the Fairchild device Spice thermal model or manually utilizing the normalized maximum transient thermal impedance curve.

Thermal resistances corresponding to other copper areas can be obtained from Figure 21 or by calculation using Equation 2 or 3. Equation 2 is used for copper area defined in inches square and equation 3 is for area in centimeter square. The area, in square inches or square centimeters is the top copper area including the gate and source pads.

$$R_{\theta JA} = 26.51 + \frac{19.84}{(0.262 + Area)} \quad \text{(EQ. 2)}$$

Area in Inches Squared

$$R_{\theta JA} = 26.51 + \frac{128}{(1.69 + Area)} \quad \text{(EQ. 3)}$$

Area in Centimeters Squared





**Figure 21. Thermal Resistance vs Mounting Pad Area**

## PSPICE Electrical Model

```
.SUBCKT FDB3682  2 1 3 ;       rev May 2002
CA  12  8 4e-10
Cb 15 14 5.5e-10
Cin 6 8 1.22e-9

Dbody 7 5 DbodyMOD
Dbreak 5 11 DbreakMOD
Dplcap 10 5 DplcapMOD

Ebreak 11 7 17 18 108
Eds 14 8 5 8 1
Egs 13 8 6 8 1
Esg 6 10 6 8 1
Evthres 6 21 19 8 1
Evtemp 20 6 18 22 1

It 8 17 1

Lgate 1 9 5.96e-9
Ldrain 2 5 1.0e-9
Lsource 3 7 3.19e-9

RLgate 1 9 59.6
RLdrain 2 5 10
RLsource 3 7 31.9

Mmed 16 6 8 8 MmedMOD
Mstro 16 6 8 8 MstroMOD
Mweak 16 21 8 8 MweakMOD

Rbreak 17 18 RbreakMOD 1
Rdrain 50 16 RdrainMOD 10.5e-3
Rgate 9 20 1.86
RSLC1 5 51 RSLCMOD 1.0e-6
RSLC2 5 50 1.0e3
Rsource 8 7 RsourceMOD 11.9e-3
Rvthres 22 8 RvthresMOD 1
Rvtemp 18 19 RvtempMOD 1
S1a 6 12 13 8 S1AMOD
S1b 13 12 13 8 S1BMOD
S2a 6 15 14 13 S2AMOD
S2b 13 15 14 13 S2BMOD

Vbat 22 19 DC 1

ESLC 51 50  VALUE={(V(5,51)/ABS(V(5,51)))*(PWR(V(5,51)/(1e-6*70),2.5))}


.MODEL DbodyMOD D (IS=2.4E-12  RS=4.4e-3 TRS1=2.0e-3 TRS2=4.5e-7
+ CJO=9e-10 M=0.57 TT=2.9e-8 XTI=4.0)
.MODEL DbreakMOD D (RS=0.6 TRS1=1.4e-3 TRS2=-5.0e-5)
.MODEL DplcapMOD D (CJO=2.7e-10 IS=1.0e-30 N=10 M=0.56)

.MODEL MstroMOD NMOS (VTO=4.16 KP=32 IS=1e-30 N=10 TOX=1 L=1u W=1u)
.MODEL MmedMOD NMOS (VTO=3.48 KP=2.7 IS=1e-30 N=10 TOX=1 L=1u W=1u RG=1.86)
.MODEL MweakMOD NMOS (VTO=2.97 KP=0.04 IS=1e-30 N=10 TOX=1 L=1u W=1u RG=18.6 RS=0.1)

.MODEL RbreakMOD RES (TC1=1.05e-3 TC2=-1.1e-8)
.MODEL RdrainMOD RES (TC1=1.6e-2 TC2=4e-5)
.MODEL RSLCMOD RES (TC1=3.0e-3 TC2=2.9e-6)
.MODEL RsourceMOD RES (TC1=1e-3 TC2=1e-6)
.MODEL RvthresMOD RES (TC1=-4.1e-3 TC2=-1.4e-5)
.MODEL RvtempMOD RES (TC1=-3.5e-3 TC2=1.3e-6)

.MODEL S1AMOD VSWITCH (RON=1e-5 ROFF=0.1 VON=-5.0 VOFF=-2.0)
.MODEL S1BMOD VSWITCH (RON=1e-5 ROFF=0.1 VON=-2.0 VOFF=-5.0)
.MODEL S2AMOD VSWITCH (RON=1e-5 ROFF=0.1 VON=-0.4 VOFF=0.3)
.MODEL S2BMOD VSWITCH (RON=1e-5 ROFF=0.1 VON=0.3 VOFF=-0.4)

.ENDS
```




Note: For further discussion of the PSPICE model, consult **A New PSPICE Sub-Circuit for the Power MOSFET Featuring Global Temperature Options**; IEEE Power Electronics Specialist Conference Records, 1991, written by William J. Hepp and C. Frank Wheatley.

## SABER Electrical Model

```
REV May 2002
template FDB3682 n2,n1,n3
electrical n2,n1,n3
{
var i iscl
dp..model dbodymod =  (isl=2.4e-12,rs=4.4e-3,trs1=2.0e-3,trs2=4.5e-7,cjo=9e-10,m=0.57,tt=2.9e-8,xti=4.0)
dp..model dbreakmod = (rs=0.6,trs1=1.4e-3,trs2=-5e-5)
dp..model dplcapmod =  (cjo=2.7e-10,isl=10e-30,nl=10,m=0.56)
m..model mstrongmod = (type=_n,vto=4.16,kp=32,is=1e-30, tox=1)
m..model mmedmod = (type=_n,vto=3.48,kp=2.7,is=1e-30, tox=1)
m..model mweakmod = (type=_n,vto=2.97,kp=0.04,is=1e-30, tox=1,rs=0.1)
sw_vcsp..model s1amod =  (ron=1e-5,roff=0.1,von=-5,voff=-2)
sw_vcsp..model s1bmod =  (ron=1e-5,roff=0.1,von=-2,voff=-5)
sw_vcsp..model s2amod =  (ron=1e-5,roff=0.1,von=-0.4,voff=0.3)
sw_vcsp..model s2bmod =  (ron=1e-5,roff=0.1,von=0.3,voff=-0.4)
c.ca n12 n8 = 4e-10
c.cb n15 n14 = 5.5e-10
c.cin n6 n8 = 1.22e-9

dp.dbody n7 n5 = model=dbodymod
dp.dbreak n5 n11 = model=dbreakmod
dp.dplcap n10 n5 = model=dplcapmod

spe.ebreak n11 n7 n17 n18 = 108
spe.eds n14 n8 n5 n8 = 1
spe.egs n13 n8 n6 n8 = 1
spe.esg n6 n10 n6 n8 = 1
spe.evthres n6 n21 n19 n8 = 1
spe.evtemp n20 n6 n18 n22 = 1

i.it n8 n17 = 1


l.lgate n1 n9 = 5.96e-9
l.ldrain n2 n5 = 1.0e-9
l.lsource n3 n7 = 3.19e-9

res.rlgate n1 n9 = 59.6
res.rldrain n2 n5 = 10
res.rlsource n3 n7 = 31.9

m.mmed n16 n6 n8 n8 = model=mmedmod, l=1u, w=1u
m.mstrong n16 n6 n8 n8 = model=mstrongmod, l=1u, w=1u
m.mweak n16 n21 n8 n8 = model=mweakmod, l=1u, w=1u

res.rbreak n17 n18  = 1, tc1=1.05e-3,tc2=-1.1e-8
res.rdrain n50 n16  = 10.5e-3, tc1=1.6e-2,tc2=4e-5
res.rgate n9 n20 = 1.86
res.rslc1 n5 n51  = 1.0e-6, tc1=3.0e-3,tc2=2.9e-6
res.rslc2 n5 n50 = 1.0e3
res.rsource n8 n7  = 11.9e-3, tc1=1e-3,tc2=1e-6
res.rvthres n22 n8  = 1, tc1=-4.1e-3,tc2=-1.4e-5
res.rvtemp n18 n19  = 1, tc1=-3.5e-3,tc2=1.3e-6
sw_vcsp.s1a n6 n12 n13 n8 = model=s1amod
sw_vcsp.s1b n13 n12 n13 n8 = model=s1bmod
sw_vcsp.s2a n6 n15 n14 n13 = model=s2amod
sw_vcsp.s2b n13 n15 n14 n13 = model=s2bmod

v.vbat n22 n19 = dc=1
equations {
i (n51->n50) +=iscl
iscl: v(n51,n50) = ((v(n5,n51)/(1e-9+abs(v(n5,n51))))*((abs(v(n5,n51)*1e6/70))** 2.5))
}
}
```



## SPICE Thermal Model

REV 20 May 2002

FDB3682_JC TH TL


CTHERM1 TH 6 1.6e-3
CTHERM2 6 5 4.5e-3
CTHERM3 5 4 5.0e-3
CTHERM4 4 3 8.0e-3
CTHERM5 3 2 8.2e-3
CTHERM6 2 TL 4.7e-2

RTHERM1 TH 6 3.3e-2
RTHERM2 6 5 7.9e-2
RTHERM3 5 4 9.5e-2
RTHERM4 4 3 1.4e-1
RTHERM5 3 2 2.9e-1
RTHERM6 2 TL 6.7e-1

## SABER Thermal Model

SABER thermal model FDB3682
template thermal_model th tl
thermal_c th, tl
{
ctherm.ctherm1 th 6 =1.6e-3
ctherm.ctherm2 6 5 =4.5e-3
ctherm.ctherm3 5 4 =5.0e-3
ctherm.ctherm4 4 3 =8.0e-3
ctherm.ctherm5 3 2 =8.2e-3
ctherm.ctherm6 2 tl =4.7e-2

rtherm.rtherm1 th 6 =3.3e-2
rtherm.rtherm2 6 5 =7.9e-2
rtherm.rtherm3 5 4 =9.5e-2
rtherm.rtherm4 4 3 =1.4e-1
rtherm.rtherm5 3 2 =2.9e-1
rtherm.rtherm6 2 tl =6.7e-1
}



FAIRCHILD SEMICONDUCTOR®

**TRADEMARKS**

The following includes registered and unregistered trademarks and service marks, owned by Fairchild Semiconductor and/or its global subsidiaries, and is not intended to be an exhaustive list of all such trademarks.

2Cool™
AccuPower™
AX-CAP™*
BitSiC®
Build it Now™
CorePLUS™
CorePOWER™
*CROSSVOLT*™
CTL™
Current Transfer Logic™
DEUXPEED®
Dual Cool™
EcoSPARK®
EfficentMax™
ESBC™
Fairchild®
Fairchild Semiconductor®
FACT Quiet Series™
FACT®
FAST®
FastvCore™
FETBench™
FlashWriter®*
FPS™
F-PFS™
FRFET®
Global Power Resource$^{SM}$
Green Bridge™
Green FPS™
Green FPS™ e-Series™
G*max*™
GTO™
IntelliMAX™
ISOPLANAR™
Marking Small Speakers Sound Louder and Better™
MegaBuck™
MICROCOUPLER™
MicroFET™
MicroPak™
MicroPak2™
MillerDrive™
MotionMax™
Motion-SPM™
mWSaver™
OptoHiT™
OPTOLOGIC®
OPTOPLANAR®
PowerTrench®
PowerXS™
Programmable Active Droop™
QFET®
QS™
Quiet Series™
RapidConfigure™
™
Saving our world, 1mW/W/kW at a time™
SignalWise™
SmartMax™
SMART START™
Solutions for Your Success™
SPM®
STEALTH™
SuperFET®
SuperSOT™-3
SuperSOT™-6
SuperSOT™-8
SupreMOS®
SyncFET™
Sync-Lock™
SYSTEM GENERAL ®*
The Power Franchise®
the power franchise®
TinyBoost™
TinyBuck™
TinyCalc™
TinyLogic®
TINYOPTO™
TinyPower™
TinyPWM™
TinyWire™
TranSiC®
TriFault Detect™
TRUECURRENT®*
μSerDes™
UHC®
Ultra FRFET™
UniFET™
VCX™
VisualMax™
VoltagePlus™
XS™

*Trademarks of System General Corporation, used under license by Fairchild Semiconductor.

**DISCLAIMER**

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

**LIFE SUPPORT POLICY**

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used here in:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
2. A critical component in any component of a life support, device, or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

**ANTI-COUNTERFEITING POLICY**

Fairchild Semiconductor Corporation's Anti-Counterfeiting Policy. Fairchild's Anti-Counterfeiting Policy is also stated on our external website, www.Fairchildsemi.com, under Sales Support.

Counterfeiting of semiconductor parts is a growing problem in the industry. All manufactures of semiconductor products are experiencing counterfeiting of their parts. Customers who inadvertently purchase counterfeit parts experience many problems such as loss of brand reputation, substandard performance, failed application, and increased cost of production and manufacturing delays. Fairchild is taking strong measures to protect ourselves and our customers from the proliferation of counterfeit parts. Fairchild strongly encourages customers to purchase Fairchild parts either directly from Fairchild or from Authorized Fairchild Distributors who are listed by country on our web page cited above. Products customers buy either from Fairchild directly or from Authorized Fairchild Distributors are genuine parts, have full traceability, meet Fairchild's quality standards for handing and storage and provide access to Fairchild's full range of up-to-date technical and product information. Fairchild and our Authorized Distributors will stand behind all warranties and will appropriately address and warranty issues that may arise. Fairchild will not provide any warranty coverage or other assistance for parts bought from Unauthorized Sources. Fairchild is committed to combat this global problem and encourage our customers to do their part in stopping this practice by buying direct or from authorized distributors.

**PRODUCT STATUS DEFINITIONS**

**Definition of Terms**

| Datasheet Identification | Product Status | Definition |
|---|---|---|
| Advance Information | Formative / In Design | Datasheet contains the design specifications for product development. Specifications may change in any manner without notice. |
| Preliminary | First Production | Datasheet contains preliminary data; supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design. |
| No Identification Needed | Full Production | Datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve the design. |
| Obsolete | Not In Production | Datasheet contains specifications on a product that is discontinued by Fairchild Semiconductor. The datasheet is for reference information only. |

Rev. I61

LifeElectronics
Живое партнерство

**ООО «ЛайфЭлектроникс»** **“LifeElectronics” LLC**

*ИНН 7805602321 КПП 780501001 Р/С 40702810122510004610 ФАКБ "АБСОЛЮТ БАНК" (ЗАО) в г.Санкт-Петербурге К/С 30101810900000000703 БИК 044030703*

*Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.*

*С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров*

*Мы предлагаем:*

- *Конкурентоспособные цены и скидки постоянным клиентам.*
- *Специальные условия для постоянных клиентов.*
- *Подбор аналогов.*
- *Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.*

- *Приемлемые сроки поставки, возможна ускоренная поставка.*
- *Доставку товара в любую точку России и стран СНГ.*
- *Комплексную поставку.*
- *Работу по проектам и поставку образцов.*
- *Формирование склада под заказчика.*

- *Сертификаты соответствия на поставляемую продукцию (по желанию клиента).*
- *Тестирование поставляемой продукции.*
- *Поставку компонентов, требующих военную и космическую приемку.*
- *Входной контроль качества.*
- *Наличие сертификата ISO.*

*В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.*

*Конструкторский отдел помогает осуществить:*

- *Регистрацию проекта у производителя компонентов.*
- *Техническую поддержку проекта.*
- *Защиту от снятия компонента с производства.*
- *Оценку стоимости проекта по компонентам.*
- *Изготовление тестовой платы монтаж и пусконаладочные работы.*

*Тел: +7 (812) 336 43 04 (многоканальный)*
*Email: org@lifeelectronics.ru*

***www.lifeelectronics.ru***