LTC1480



3.3V Ultralow Power RS485 Transceiver

FEATURES

- True RS485 from a Single 3.3V Supply
- Low Power: I_{CC} = 500µA Max with Driver Disabled
- $I_{CC} = 600 \mu A$ Max with Driver Enabled, No Load
- 1µA Quiescent in Shutdown Mode
- –7V to 12V Common Mode Range Permits ±7V Ground Difference Between Devices on the Data Line
- Thermal Shutdown Protection
- Power Up/Down Glitch-Free Driver Outputs Permit Live Insertion or Removal of Transceiver
- Driver Maintains High Impedance in Three-State or with the Power Off
- Up to 32 Transceivers on the Bus
- 50ns Typical Driver Propagation Delays with 10ns Skew
- Pin Compatible with the LTC485
- Available in 8-Lead DIP and SO Packages

APPLICATIONS

- Battery-Powered RS485/RS422 Applications
- Low Power RS485/RS422 Transceiver
- Level Translator

DESCRIPTION

The LTC[®]1480 is an ultralow power differential line transceiver which provides full RS485 compatibility while operating from a single 3.3V supply. It is designed for data transmission standard RS485 applications with extended common mode range (12V to -7V). It also meets the requirements of RS422 and features high speed operation up to 2.5Mb/s. The CMOS design offers significant power savings without sacrificing ruggedness against overload or ESD damage. Typical quiescent current is only 300µA while operating and 1µA in shutdown.

The driver and receiver feature three-state outputs, with the driver outputs maintaining high impedance over the entire common mode range. Excessive power dissipation caused by bus contention or faults is prevented by a thermal shutdown circuit which forces the driver outputs into a high impedance state. The receiver has a fail-safe feature which guarantees a high output state when the inputs are left open.

The LTC1480 is fully specified over the commercial and extended industrial temperature range. The LTC1480 is available in 8-pin SO and DIP packages.

T, LTC and LT are registered trademarks of Linear Technology Corporation. All other trademarks are the property of their respective owners.

TYPICAL APPLICATION



Driver Differential Output Voltage vs Output Current





ABSOLUTE MAXIMUM RATINGS

(Note 1)

Supply Voltage (V _{CC}) 7V
Control Input Voltage $-0.3V$ to V _{CC} + 0.3V
Driver Input Voltage $-0.3V$ to V _{CC} + 0.3V
Driver Output Voltage ±14V
Receiver Input Voltage ±14V
Receiver Output Voltage $-0.3V$ to V _{CC} + 0.3V
Operating Temperature Range
LTC1480C $0^{\circ}C \le T_A \le 70^{\circ}C$
LTC1480I $-40^{\circ}C \le T_A \le 85^{\circ}C$
Storage Temperature Range65°C to 150°C
Lead Temperature (Soldering, 10 sec) 300°C

PACKAGE/ORDER INFORMATION



ELECTRICAL CHARACTERISTICS The • denotes the specifications which apply over the full operating

temperature range. V_{CC} = 3.3V (Notes 2, 3).

SYMBOL	PARAMETER	CONDITIONS		MIN	ТҮР	MAX	UNITS
V _{OD1}	Differential Driver Output Voltage (Unloaded)	I ₀ = 0V				3.3	V
V _{OD2}	Differential Driver Output Voltage (with Load)		•	1.5 2.0		3.3	V V
ΔV_{OD}	Change in Magnitude of Driver Differential Output Voltage for Complementary Output States	$R = 27\Omega$ or $R = 50\Omega$ (Figure 1)	•			0.2	V
V _{OC}	Driver Common Mode Output Voltage	$R = 27\Omega$ or $R = 50\Omega$ (Figure 1)	•			2	V
$\Delta V_{0C} $	Change in Magnitude of Driver Common Mode Output Voltage for Complementary Output States	$R = 27\Omega$ or $R = 50\Omega$ (Figure 1)	•			0.2	V
VIH	Input HIGH Voltage	DE, DI, RE	•	2			V
V _{IL}	Input LOW Voltage	DE, DI, RE				0.8	V
I _{IN1}	Input Current	DE, DI, RE				±2	μA
I _{IN2}	Input Current (A, B)	$ \begin{array}{l} {\sf DE} = 0, {\sf V}_{CC} = 0{\sf V} \mbox{ or } 3.6{\sf V}, {\sf V}_{{\sf IN}} = 12{\sf V} \\ {\sf DE} = 0, {\sf V}_{CC} = 0{\sf V} \mbox{ or } 3.6{\sf V}, {\sf V}_{{\sf IN}} = -7{\sf V} \end{array} $	•			1.0 -0.8	mA mA
V _{TH}	Differential Input Threshold Voltage for Receiver	$-7V \le V_{CM} \le 12V$	•	-0.2		0.2	V
ΔV_{TH}	Receiver Input Hysteresis	$V_{CM} = 0V$			70		mV
V _{OH}	Receiver Output HIGH Voltage	$I_0 = -4mA, V_{ID} = 200mV$		2			V
V _{OL}	Receiver Output LOW Voltage	$I_0 = 4mA, V_{ID} = -200mV$				0.4	V
I _{OZR}	Three-State (High Impedance) Output Current at Receiver	$V_{CC} = Max, 0.4V \le V_0 \le 2.4V$	•			±1	μA
R _{IN}	Receiver Input Resistance	$-7V \le V_{CM} \le 12V$		12			kΩ
I _{CC}	Supply Current	No Load, Output Enabled No Load, Output Disabled	•		400 300	600 500	μΑ μΑ
I _{SHDN}	Supply Current in Shutdown Mode	$DE = 0, \overline{RE} = V_{CC}$			1	10	μA



1480fa

SWITCHING CHARACTERISTICS The \bullet denotes the specifications which apply over the full operating temperature range. V_{CC} = 3.3V (Notes 2, 3).

PARAMETER	CONDITIONS		MIN	ТҮР	MAX	UNITS
Driver Short-Circuit Current, V _{OUT} = HIGH	$-7V \le V_0 \le 12V$		35		250	mA
Driver Short-Circuit Current, V _{OUT} = LOW	$-7V \le V_0 \le 12V$		35		250	mA
Receiver Short-Circuit Current	$0V \le V_0 \le V_{CC}$		7		85	mA
Driver Input to Output	$\begin{array}{l} R_{DIFF} = 54\Omega, C_{L1} = C_{L2} = 100 pF, \\ (Figures \; 3, 5) \end{array}$	•	25	50	80	ns
Driver Input to Output			25	50	80	ns
Driver Output to Output				10	20	ns
Driver Rise or Fall Time			5	15	40	ns
Driver Enable to Output HIGH	C _L = 100pF (Figures 4, 6), S2 Closed			70	120	ns
Driver Enable to Output LOW	C _L = 100pF (Figures 4, 6), S1 Closed			70	120	ns
Driver Disable Time from LOW	C _L = 15pF (Figures 4, 6), S1 Closed			70	120	ns
Driver Disable Time from HIGH	C _L = 15pF (Figures 4, 6), S2 Closed			70	120	ns
Receiver Input to Output	$R_{DIFF} = 54\Omega$, $C_{L1} = C_{L2} = 100pF$, (Figures 3, 7)	•	30	140	200	ns
Receiver Input to Output			30	140	200	ns
t _{PLH} – t _{PHL} Differential Receiver Skew				13		ns
Receiver Enable to Output LOW	C _{RL} = 15pF (Figures 2, 8), S1 Closed			50	80	ns
Receiver Enable to Output HIGH	C _{RL} = 15pF (Figures 2, 8), S2 Closed			50	80	ns
Receiver Disable from LOW	C _{RL} = 15pF (Figures 2, 8), S1 Closed			50	80	ns
Receiver Disable from HIGH	C _{RL} = 15pF (Figures 2, 8), S2 Closed			50	80	ns
Maximum Data Rate			2.5			Mbits/s
Time to Shutdown	DE = 0, RE = _		50	200	600	ns
Driver Enable from Shutdown to Output HIGH	C _L = 100pF (Figures 4, 6), S2 Closed			70	120	ns
Driver Enable from Shutdown to Output LOW	C _L = 100pF (Figures 4, 6), S1 Closed			70	120	ns
Receiver Enable from Shutdown to Output HIGH	C _L = 15pF (Figures 2, 8), S2 Closed				4500	ns
Receiver Enable from Shutdown to Output LOW	C _L = 15pF (Figures 2, 8), S1 Closed				4500	ns
	PARAMETERDriver Short-Circuit Current, V _{OUT} = HIGHDriver Short-Circuit Current, V _{OUT} = LOWReceiver Short-Circuit CurrentDriver Input to OutputDriver Input to OutputDriver Output to OutputDriver Rise or Fall TimeDriver Enable to Output LOWDriver Disable Time from LOWDriver Disable Time from HIGHReceiver Input to OutputReceiver Input to OutputPriver Disable Time from HIGHReceiver Input to OutputReceiver Input to Output LOWReceiver Enable to Output HIGHReceiver Enable to Output HIGHReceiver Disable from HIGHMaximum Data RateTime to ShutdownDriver Enable from Shutdown to Output HIGHDriver Enable from Shutdown to Output HIGHPriver	PARAMETERCONDITIONSDriver Short-Circuit Current, V_{OUT} = HIGH $-7V \le V_0 \le 12V$ Receiver Short-Circuit Current, V_{OUT} = LOW $-7V \le V_0 \le 12V$ Receiver Short-Circuit Current $0V \le V_0 \le V_{CC}$ Driver Input to Output $0V \le V_0 \le V_{CL}$ Driver Input to Output $C_{L1} = C_{L2} = 100pF$, (Figures 3, 5)Driver Output to Output $C_L = 100pF$ (Figures 4, 6), S2 ClosedDriver Enable to Output HIGH $C_L = 100pF$ (Figures 4, 6), S1 ClosedDriver Disable Time from LOW $C_L = 15pF$ (Figures 4, 6), S2 ClosedDriver Disable Time from HIGH $C_L = 15pF$ (Figures 4, 6), S2 ClosedReceiver Input to Output $C_L = 15pF$ (Figures 4, 6), S2 ClosedDriver Disable Time from HIGH $C_L = 15pF$ (Figures 4, 6), S2 ClosedReceiver Input to Output $C_{L1} = 15pF$ (Figures 4, 6), S2 ClosedReceiver Input to Output $C_{L1} = 15pF$ (Figures 4, 6), S2 ClosedReceiver Input to Output $C_{L1} = 15pF$ (Figures 2, 8), S1 ClosedReceiver Input to Output $C_{RL} = 15pF$ (Figures 2, 8), S1 ClosedReceiver Enable to Output HIGH $C_{RL} = 15pF$ (Figures 2, 8), S2 ClosedReceiver Disable from LOW $C_{RL} = 15pF$ (Figures 2, 8), S2 ClosedReceiver Disable from HIGH $C_L = 100pF$ (Figures 4, 6), S2 ClosedMaximum Data Rate $C_L = 100pF$ (Figures 4, 6), S2 ClosedDriver Enable from Shutdown to Output HIGH $C_L = 100pF$ (Figures 4, 6), S2 ClosedDriver Enable from Shutdown to Output HIGH $C_L = 100pF$ (Figures 4, 6), S2 ClosedReceiver Disable from HIGH $C_L = 100pF$ (Figures 4,	PARAMETERCONDITIONSDriver Short-Circuit Current, $V_{OUT} = HIGH$ $-7V \le V_0 \le 12V$ •Driver Short-Circuit Current, $V_{OUT} = LOW$ $-7V \le V_0 \le 12V$ •Receiver Short-Circuit Current $0V \le V_0 \le V_{CC}$ •Driver Input to Output $V_0 \le V_{CC}$ •Driver Input to OutputRpJFF $= 54\Omega_{L}$ $C_{L1} = C_{L2} = 100pF$, $(Figures 3, 5)$ •Driver Input to Output $-7V \le V_0 \le 12V$ •Driver Input to Output $-7V \le V_0 \le V_{CC}$ •Driver Input to Output $V \le V_0 \le V_{CC}$ •Driver Input to Output $-7V \le V_0 \le 12V$ •Driver Input to Output $-7V \le V_0 \le 12V$ •Driver Dutput to Output $-7V \le V_0 \le 12V$ •Driver Dutput to Output $-7V \le V_0 \le 12V$ •Driver Dutput to Output $C_L = 100pF$ (Figures 4, 6), S2 Closed•Driver Disable Time from LOW $C_L = 15pF$ (Figures 4, 6), S2 Closed•Driver Disable Time from HIGH $C_L = 15pF$ (Figures 4, 6), S2 Closed•Receiver Input to Output $R_{DIFF} = 54\Omega, C_{L1} = C_{L2} = 100pF$, (Figures 3, 7)•Receiver Input to Output $C_{RL} = 15pF$ (Figures 2, 8), S1 Closed•Receiver Input to Output LOW $C_{RL} = 15pF$ (Figures 2, 8), S1 Closed•Receiver Input to Output HIGH $C_{RL} = 15pF$ (Figures 2, 8), S2 Closed•Receiver Input to Output HIGH $C_{RL} = 15pF$ (Figures 2, 8), S2 Closed•Receiver Enable from HIGH $C_L = 100pF$ (Figures 4, 6), S2 Closed•Receiver Disable	PARAMETERCONDITIONSMINDriver Short-Circuit Current, V_{0UT} = HIGH $-7V \le V_0 \le 12V$ \bullet 35 Driver Short-Circuit Current, V_{0UT} = LOW $-7V \le V_0 \le 12V$ \bullet 35 Receiver Short-Circuit Current $0V \le V_0 \le V_{0C}$ \bullet 7 Driver Input to Output $V_0 \le V_0 \le V_{0C}$ \bullet 7 Driver Input to Output $V_0 \le V_0 \le V_{0C}$ \bullet 7 Driver Input to Output $V_0 \le V_{0C}$ \bullet 25 Driver Output to Output \bullet \bullet 5 Driver Output to Output \bullet \bullet 5 Driver Bise or Fall Time $C_L = 100pF$ (Figures 4, 6), S2 Closed \bullet Driver Enable to Output HIGH $C_L = 15pF$ (Figures 4, 6), S1 Closed \bullet Driver Disable Time from LOW $C_L = 15pF$ (Figures 4, 6), S2 Closed \bullet Driver Disable Time from HIGH $C_L = 15pF$ (Figures 4, 6), S2 Closed \bullet Receiver Input to Output $P_{0IFF} = 54\Omega$, $C_{L1} = C_L = 100pF$, P_{0IFF} \bullet Receiver Input to Output $C_{RL} = 15pF$ (Figures 2, 8), S1 Closed \bullet It_{LH} - t_{PHL} Differential Receiver Skew \bullet \bullet \bullet Receiver Enable to Output HIGH $C_{RL} = 15pF$ (Figures 2, 8), S2 Closed \bullet \bullet Receiver Disable from HIGH $C_{RL} = 15pF$ (Figures 2, 8), S2 Closed \bullet \bullet Receiver Disable from HIGH $C_L = 100pF$ (Figures 4, 6), S2 Closed \bullet \bullet Receiver Disable from HIGH $C_R = 15pF$ (Figures 2, 8), S2 Closed \bullet \bullet Driver	PARAMETER CONDITIONS MIN TYP Driver Short-Circuit Current, $V_{OUT} = HGH$ $-7V \le V_0 \le 12V$ 6 35 Driver Short-Circuit Current, $V_{OUT} = LOW$ $-7V \le V_0 \le 12V$ 6 35 Receiver Short-Circuit Current $0V \le V_0 \le V_{CC}$ 6 7 Driver Input to Output $0V \le V_0 \le V_{CL}$ 6 25 50 Driver Input to Output $0V \le V_0 \le 12V$ 6 25 50 Driver Input to Output $0V \le V_0 \le 12V$ 6 25 50 Driver Output to Output $-100DF$ 6 5 15 Driver Cuput to Output $C_L = 100PF$ (Figures 4, 6), S2 Closed 6 700 Driver Enable to Output HIGH $C_L = 152F$ (Figures 4, 6), S1 Closed 6 700 Driver Disable Time from HIGH $C_L = 152F$ (Figures 4, 6), S2 Closed 6 700 Driver Disable Time from HIGH $C_L = 152F$ (Figures 2, 8), S1 Closed 6 300 1400 Ip_LH - typeL Differential Receiver Skew $C_{RL} = 152F$ (Figures 2, 8), S1 Closed 6 50 50 50	PRAMETER CONDITIONS MIN TYP MAX Driver Short-Circuit Current, $V_{OUT} = HIGH$ $-7V \le V_0 \le 12V$ $=$ 35 250 Receiver Short-Circuit Current $0V \le V_0 \le V_{CC}$ $=$ 7 85 Driver Input to Output $VV \le V_0 \le V_{CC}$ $=$ 7 85 Driver Input to Output $VV \le V_0 \le V_{CC}$ $=$ 7 85 Driver Input to Output $P_{DIFF} = 54\Omega, C_{L1} = C_{L2} = 100PF, (Figures 3, 5)$ $=$ 25 50 80 Driver Output to Output $=$ 25 50 80 20 80 20 80 80 Driver Output to Output $C_L = 100PF$ (Figures 4, 6), S2 Closed $=$ 70 120 70 120 Driver Disable Time from LOW $C_L = 15PF$ (Figures 4, 6), S2 Closed $=$ 70 120 Receiver Input to Output $C_L = 15PF$ (Figures 4, 6), S2 Closed $=$ 70 120 Receiver Input to Output $C_R = 15PF$ (Figures 2, 8), S1 Closed $=$ 30 <

Note 1: Absolute maximum ratings are those beyond which the satety of the device cannot be guaranteed.

Note 2: All currents into device pins are positive; all currents out ot device pins are negative. All voltages are referenced to device ground unless otherwise specified. Note 3: All typicals are given for $V_{CC} = 3.3V$ and $T_A = 25^{\circ}C$.

TYPICAL PERFORMANCE CHARACTERISTICS





Driver Differential Output Voltage vs Temperature





TYPICAL PERFORMANCE CHARACTERISTICS



PIN FUNCTIONS

R0 (Pin 1): Receiver Output. If the receiver output is enabled (\overline{RE} LOW) and A > B by 200mV, then RO will be HIGH. If A < B by 200mV, then RO will be LOW.

RE (**Pin 2**): Receiver Output Enable. A LOW enables the receiver output, RO. A HIGH input forces the receiver output into a high impedance state.

DE (Pin 3): Driver Outputs Enable. A HIGH on DE enables the driver output. A, B and the chip will function as a line driver. A low input will force the driver outputs into a high impedance state and the chip will function as a line receiver. If \overrightarrow{RE} is high and DE is LOW, the part will enter a low power (1µA) shutdown state. If \overrightarrow{RE} is low and DE is

high, the driver outputs will be fed back to the receiver and the receive output will correspond to the driver input.

DI (Pin 4): Driver Input. If the driver outputs are enabled (DE HIGH) then a low on DI forces the outputs A LOW and B HIGH. A HIGH on DI with the driver outputs enabled will force A HIGH and B LOW.

GND (Pin 5): Ground.

A (Pin 6): Driver Output/Receiver Input.

B (Pin 7): Driver Output/Receiver Input.

 V_{CC} (Pin 8): Positive Supply. 3.0V < V_{CC} < 3.6V.





FUNCTION TABLES

LTC1480 Transmitting

INPUTS			OUT	PUTS
RE	DE	DI	В	Α
Х	1	1	0	1
Х	1	0	1	0
0	0	Х	Z	Z
1	0	Х	Z*	Ζ*

*Shutdown mode

TEST CIRCUITS



Figure 1. Driver DC Test Load



Figure 3. Driver/Receiver Timing Test Circuit



	OUTPUTS		
RE	DE	A – B	RO
0	0	≥0.2V	1
0	0	≤-0.2V	0
0	0	Inputs Open	1
1	0	Х	Z*
t Olevet de vers e de			

*Shutdown mode



Figure 2. Receiver Timing Test Load



Figure 4. Driver Timing Test Load

SWITCHING TIME WAVEFORMS







SWITCHING TIME WAVEFORMS





APPLICATIONS INFORMATION

CMOS Output Driver

The LTC1480 transceiver provides full RS485 compatibility while operating from a single 3.3V supply. The RS485 specification requires that a transceiver withstand common mode voltages of up to 12V or -7V at the RS485 line connections. Additionally, the transceiver must be immune to both ESD and latch-up. This rules out traditional CMOS drivers, which include parasitic diodes from their driver outputs to each supply rail (Figure 9). The LTC1480 uses a proprietary process enhancement which adds a pair of Schottky diodes to the output stage (Figure 10), preventing





APPLICATIONS INFORMATION

current from flowing when the common mode voltage exceeds the supply rails. Latch-up at the output drivers is virtually eliminated and the driver is prevented from loading the line under RS485 specified fault conditions.

When two or more drivers are connected to the same transmission line, a potential condition exists whereby more than two drivers are simultaneously active. If one or more drivers is sourcing current while another driver is sinking current, excessive power dissipation may occur within either the sourcing or sinking element. This condition is defined as driver contention, since multiple drivers are competing for one transmission line. The LTC1480 provides a current limiting scheme to prevent driver contention failure. When driver contention occurs, the current drawn is limited to about 70mA preventing excessive power dissipation within the drivers.

The LTC1480 has a thermal shutdown feature which protects the part from excessive power dissipation. Under extreme fault conditions, up to 250mA can flow through the part causing rapid internal temperature rise. The thermal shutdown circuit will disable the driver outputs when the internal temperature reaches 150°C and turns them back on when the temperature cools to 130°C. This cycle will repeat as necessary until the fault condition is removed.

Receiver Inputs

The LTC1480 features an input common mode range covering the entire RS485 specified range of -7V to 12V. Differential signals of greater than ± 200 mV within the specified input common mode range will be converted to a TTL compatible signal at the receiver output. A small amount of input hysteresis is included to minimize the effects of noise on the line signals. If the receiver inputs are floating (unterminated) an internal pull-up of 10µA at the A input will force the receiver output to a known high state.

Low Power Operation

The LTC1480 draws very little supply current whenever the driver outputs are disabled. In shutdown mode the quiescent current is typically less than 1μ A. With the receiver active and the driver outputs disabled, the LTC1480 will typically draw 300μ A quiescent current. With the

driver outputs enabled but unterminated, quiescent current will rise as one of the two outputs sources current into the internal receiver input resistance. With the minimum receiver input resistance of 12k and the maximum output swing of 3.3V, the quiescent current will rise by a maximum of 275μ A. Typical quiescent current rise with the driver enabled is about 100 μ A.

The quiescent current rises significantly if the driver is enabled when it is externally terminated. With 1/2 termination load (120Ω between the driver outputs) the quiescent current will jump to at least 13mA as the drivers force a minimum of 1.5V across the termination resistance. With a fully terminated 60Ω line attached, the current will rise to greater than 25mA with the driver enabled, completely overshadowing the extra 100μ A drawn by internal receiver inputs.

Shutdown Mode

Both the receiver output (RO) and the driver outputs (A, B) can be placed in three-state mode by bringing \overline{RE} HIGH and DE LOW respectively. In addition, the LTC1480 will enter shutdown mode when \overline{RE} is HIGH and DE is LOW.

In shutdown the LTC1480 typically draws only 1μ A of supply current. In order to guarantee that the part goes into shutdown, RE must be high and DE must be LOW for at least 600ns simultaneously. If this time duration is less than 50ns the part will not enter shutdown mode.

Propagation Delay

Many digital encoding schemes are dependent upon the difference in the propagation delay times of the driver and receiver. Figure 11 shows the test circuit for the LTC1480 propagation delay.

The receiver delay times are:

 $|t_{PLH} - t_{PHL}| = 13$ ns Typ, V_{CC} = 3.3V

The driver's skew times are:

 $t_{SKEW} = 10$ ns Typ, $V_{CC} = 3.3V$

20ns Max, V_{CC} = 3.3V, T_A = -40°C to 85°C



APPLICATIONS INFORMATION





PACKAGE DESCRIPTION



RELATED PARTS

PART NUMBER	DESCRIPTION	COMMENTS
LTC485	5V Low Power RS485 Interface Transceiver	Low Power
LTC1481	5V Ultralow Power RS485 Transceiver with Shutdown	Lowest Power
LTC1483	5V Ultralow Power RS485 Low EMI Transceiver with Shutdown	Low EMI/Lowest Power
LTC1485	5V Differential Bus Transceiver	High Speed, 10Mbps
LTC1487	5V Ultralow Power RS485 with Low EMI, Shutdown and High Input Impedance	High Input Impedance/Low EMI/Lowest Power

LT/LT 0605 REV A · PRINTED IN USA

1480fa



ООО "ЛайфЭлектроникс"

ИНН 7805602321 КПП 780501001 Р/С 40702810122510004610 ФАКБ "АБСОЛЮТ БАНК" (ЗАО) в г.Санкт-Петербурге К/С 3010181090000000703 БИК 044030703

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный) Email: org@lifeelectronics.ru

www.lifeelectronics.ru