



# kester®

Technical Data Sheet

## 186-18 Soldering Flux

### Mildly Activated Rosin Liquid Flux



### Product Description

Kester 186-18, under MIL-F-14256, was QPL approved as Type RMA. Although the fluxing ability approaches that of Type RA flux, the flux residue after soldering is non-corrosive and non-conductive. 186-18 rosin flux has been developed for use in critical applications where difficult assemblies are to be soldered, but process requirements stipulate use of Type RMA flux. This flux possess high thermal stability for soldering multi-layer assemblies which require a high preheat temperature. Exposure to high preheat temperatures does not degrade solubility of the residue in normal cleaning solvents. There is no surface insulation resistance degradation caused by the flux residue. The use of a minimum of ionic activating agents and the inactive nature of the residue permits leaving the residue on circuit board assemblies for many applications. The flux residue is also moisture and fungus resistant.

### Performance Characteristics:

- High thermal stability
- Improves soldering performance
- Eliminates the need and expense of cleaning
- Classified as ROL0 per J-STD-004 & J-STD-004B



### RoHS Compliance

This product meets the requirements of the Restriction of Hazardous Substances (RoHS) Directive. Additional RoHS information is located at <https://www.kester.com/downloads/environmental>.



### Physical Properties

**Specific Gravity @ 25°C:** 0.831  
(typical)

**Percent Solids (typical):** 18%

**Flash Point:** 18°C (64°F)



### Reliability Properties

**Copper Mirror Corrosion:** Low  
IPC-TM-650, Method 2.3.32

**Chloride and Bromides:** 0.02%  
IPC-TM-650, Method 2.3.35

**Surface Insulation Resistivity (SIR),  
IPC (typical):** Pass  
IPC-TM-650, Method 2.6.3.3

**Corrosion Test:** Low  
IPC-TM-650, Method 2.6.15

**Surface Insulation Resistivity (SIR),  
IPC:** Pass  
IPC-TM-650, Method 2.6.3.7

**Silver Chromate:** Pass  
IPC-TM-650, Method 2.3.33



## Flux Application

186-18 can be applied to circuit boards by a foam or dip process. An air knife after the flux tank is recommended to remove excess flux from the circuit board and prevent dripping on the preheated surface.

## Process Considerations

The optimum preheat temperature for most circuit assemblies is 90-105°C (194-221°F) as measured on the top or component side of the printed circuit board. Dwell time in the wave is typically 2-4 seconds. The wave soldering speed should be adjusted to accomplish proper preheating and evaporate excess solvent, which could cause spattering. For best results, speeds of 1.1-1.8 m/min (3½-6 ft/min) are used. The surface tension has been adjusted to help the flux form a thin film on the board surface allowing rapid solvent evaporation.

## Flux Control

Specific gravity is normally the most reliable method to control the flux concentration of rosin-based fluxes. To check concentration, a hydrometer should be used. Control of the flux in the foam flux tank during use is necessary for assurance of consistent flux distribution on the circuit boards. The complex nature of the solvent system for the flux makes it imperative that Kester 120 Thinner be used to replace evaporative losses. When excessive debris from circuit boards, such as board fibers and from the air line build up in the flux tank, these particulates will redeposit on the circuit boards which may create a build up of residues on probe test pins. It is, therefore, necessary to clean the tank and then replenish it with fresh flux when excessive debris accumulates in the flux tank.

## Cleaning

186-18 residues are non-conductive, non-corrosive and do not require removal in most applications. If residue removal is required, it can be removed using commercially available flux residue cleaner. Contact Kester Technical Support for additional assistance.

## Storage, Handling and Shelf Life

186-18 is flammable. Store away from sources of ignition. Shelf life is 2 years from the date of manufacture when handled properly and held at 10-25°C (50-77°F).

## Health and Safety

This product, during handling or use, may be hazardous to your health or the environment. Read the Safety Data Sheet and warning label before using this product. Safety Data Sheets are available at <https://www.kester.com/downloads/sds>.



Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: [org@lifeelectronics.ru](mailto:org@lifeelectronics.ru)

[www.lifeelectronics.ru](http://www.lifeelectronics.ru)