

BASIC SIGNAL PROCESSOR


- DEVICE INCLUDES AUDIO PROCESSOR, STEREO DECODER AND NOISEBLANKER
- HIGH PERFORMANCE SIGNAL PROCESSOR WITH BASIC FUNCTIONS
- AM, FM, (MPX) AND CASSETTE INPUTS
- NO EXTERNAL COMPONENTS REQUIRED
- FULLY PROGRAMMABLE VIA I²C BUS
- LOW DISTORTION AND NOISE

DESCRIPTION

The TDA7403 is a high performance signal processor specifically designed for car radio applications focused on the low-end market.

The device includes a complete audioprocessor and a stereo decoder with noiseblanker.

Switched-capacitors design technique allows to obtain all these features without external components or adjustments. Using TDA7403 results is in a very performant low-cost signal processing



SO20


ORDERING NUMBER: TDA7403D

application

The device is fully programmable by I²C bus interface allowing to customize key device parameters and especially filter characteristics.

The BICMOS process combined with the optimized signal processing assure low noise and low distortion performances.

BLOCK DIAGRAM



ABSOLUTE MAXIMUM RATINGS

| Symbol | Parameter | Value | Unit |
|------------------|-------------------------------------|------------|------|
| V _s | Operating Supply Voltage | 10.5 | V |
| T _{amb} | Operating Ambient Temperature Range | -40 to 80 | °C |
| T _{stg} | Operating Storage Temperature Range | -55 to 150 | °C |


SUPPLY

| Symbol | Parameter | Test Condition | Min. | Typ. | Max. | Unit |
|----------------|-------------------------|-----------------------------------|------|------|------|------|
| V _s | Supply Voltage | | 7.5 | 9 | 10 | V |
| I _s | Supply Current | V _s = 9V | 25 | 30 | 35 | mA |
| SVRR | Ripple Rejection @ 1KHz | Audioprocessor (all filters flat) | | 60 | | dB |
| | | Stereodecoder + Audioprocessor | | 55 | | dB |

ESD

All pins are protected against ESD according to the MIL883 standard.

PIN CONNECTION



THERMAL DATA

| Symbol | Parameter | Value | Unit |
|------------------------|--------------------------------------|-------|------|
| R _{th-j pins} | Thermal Resistance Junction-pins Max | 85 | °C/W |

PIN DESCRIPTION

| N. | Name | Function | Type |
|----|-------|-----------------------------|------|
| 1 | CASSR | Cassette Input Right | I |
| 2 | CASSL | Cassette Input Left | I |
| 3 | n.c. | not connected | |
| 4 | n.c. | not connected | |
| 5 | n.c. | not connected | |
| 6 | n.c. | not connected | |
| 7 | n.c. | not connected | |
| 8 | AM | AM Input | I |
| 9 | MPX | FM Input (MPX) | I |
| 10 | LEVEL | Level Input Stereodecoder | I |
| 11 | SM | Soft Mute Drive | I |
| 12 | SCL | I ² C Clock Line | I/O |
| 13 | SDA | I ² C Data Line | I/O |
| 14 | GND | Supply Ground | S |
| 15 | VS | Supply Voltage | S |
| 16 | OUTRR | Right Rear Speaker Output | O |
| 17 | OUTLR | Left Rear Speaker Output | O |
| 18 | OUTRF | Right Front Speaker Output | O |
| 19 | OUTLF | Left Front Speaker Output | O |
| 20 | CREF | Reference Capacitor Pin | S |

(1) See input configuration tree and data byte specification "configuration"

Pin type legenda:

I = Input

O = Output

I/O = Input/Output

S = Supply

AUDIO PROCESSOR PART**Input Multiplexer**

- MPX input
- Cassette stereo input
- AM mono

Volume control

- 1dB attenuator
- Max. gain 20dB
- Max. attenuation 79dB

Soft-step gain control

Bass Control

- 2nd order frequency response
- Center frequency programmable in 4(5) steps

- DC gain programmable
- 7 x 2dB steps

Treble Control

- 2nd order frequency response
- Center frequency programmable in 4 steps
- 7 x 2dB steps

Speaker Control

- 4 independent speaker controls (1dB steps control range 50dB)

Mute Functions

- Direct mute driven by pin SM
- Digitally controlled softmute with 4 programmable time constants

ELECTRICAL CHARACTERISTICS ($V_S = 9V$; $T_{amb} = 25^\circ C$; $R_L = 10K\Omega$; all gains = 0dB; $f = 1KHz$; unless otherwise specified).

| Symbol | Parameter | Test Condition | Min. | Typ. | Max. | Unit |
|---------------------|---|--------------------------------------|-------|------|------|------------------|
| INPUT SELECTOR | | | | | | |
| R _{in} | Input Resistance | all inputs except Phone | 70 | 100 | 130 | KΩ |
| V _{CL} | Clipping Level | | 2.2 | 2.6 | | V _{RMS} |
| S _{IN} | Input Separation | | 80 | 100 | | dB |
| G _{IN MIN} | Min. Input Gain | | -1 | 0 | 1 | dB |
| G _{IN MAX} | Max. Input Gain | | | 14 | | dB |
| G _{STEP} | Step Resolution | | | 2 | | dB |
| V _{DC} | DC Steps | Adjacent Gain Step | | 0 | | mV |
| | | G _{MIN} to G _{MAX} | | 1 | | mV |
| VOLUME CONTROL | | | | | | |
| G _{MAX} | Max Gain | | | 20 | | dB |
| A _{MAX} | Max Attenuation | | | 79 | | dB |
| A _{STEP} | Step Resolution | | | 1 | | dB |
| E _A | Attenuation Set Error | G = -20 to 20dB | -1.25 | 0 | 1.25 | dB |
| | | G = -60 to 20dB | -4 | 0 | 3 | dB |
| E _T | Tracking Error | | | | 2 | dB |
| V _{DC} | DC Steps | Adjacent Attenuation Steps | | 0.1 | 3 | mV |
| | | From 0dB to G _{MIN} | | 0.5 | 5 | mV |
| SOFT MUTE | | | | | | |
| A _{MUTE} | Mute Attenuation | | 70 | 100 | | dB |
| T _D | Delay Time | T1 | | 0.48 | | ms |
| | | T2 | | 0.96 | | ms |
| | | T3 | | 40.4 | | ms |
| | | T4 | | 324 | | ms |
| V _{THlow} | Low Threshold for SM Pin ⁽¹⁾ | | | | 1 | V |
| V _{THhigh} | High Threshold for SM Pin | | 2.5 | | | V |
| R _{PU} | Internal Pull-up Resistor | | 70 | 100 | 130 | KΩ |
| V _{PU} | Pull-up Voltage | | | 4.7 | | V |

ELECTRICAL CHARACTERISTICS (continued)


| Symbol | Parameter | Test Condition | Min. | Typ. | Max. | Unit |
|---------------------|-------------------------------|--|------|--------------------|------|------------------|
| SOFT STEP | | | | | | |
| T _{SW} | Switch Time | | | 10 | | ms |
| BASS CONTROL | | | | | | |
| C _{RANGE} | Control Range | | | ±14 | | dB |
| A _{STEP} | Step Resolution | | | 2 | | dB |
| f _c | Center Frequency | f _{c1} | | 60 | | Hz |
| | | f _{c2} | | 70 | | Hz |
| | | f _{c3} | | 80 | | Hz |
| | | f _{c4} | | 100 ⁽²⁾ | | Hz |
| Q _{BASS} | Quality Factor | Q ₁ | | 1 | | |
| | | Q ₂ | | 1.25 | | |
| | | Q ₃ | | 1.5 | | |
| | | Q ₄ | | 2 | | |
| DC _{GAIN} | Bass-Dc-Gain | DC = off | | 0 | | dB |
| | | DC = on | | 4.4 | | dB |
| TREBLE CONTROL | | | | | | |
| C _{RANGE} | Control Range | | | ±14 | | dB |
| A _{STEP} | Step Resolution | | | 2 | | dB |
| f _c | Center Frequency | f _{c1} | | 10 | | KHz |
| | | f _{c2} | | 12.5 | | KHz |
| | | f _{c3} | | 15 | | KHz |
| | | f _{c4} | | 17.5 | | KHz |
| SPEAKER ATTENUATORS | | | | | | |
| C _{RANGE} | Control Range | | | 50 | | dB |
| A _{STEP} | Step Resolution | | | 1 | | dB |
| A _{MUTE} | Output Mute Attenuation | | | 80 | | dB |
| E _E | Attenuation Set Error | | | | 3 | dB |
| V _{DC} | DC Steps | Adjacent Attenuation Steps | | 0.1 | 10 | mV |
| AUDIO OUTPUTS | | | | | | |
| V _{CLIP} | Clipping Level | d = 0.3% | 2.2 | 2.6 | | V _{RMS} |
| R _L | Output Load Resistance | | 2 | | | KΩ |
| C _L | Output Load Capacitance | | | | 10 | nF |
| R _{OUT} | Output Impedance | | | 30 | 120 | Ω |
| V _{DC} | DC Voltage Level | | | 3.8 | | V |
| GENERAL | | | | | | |
| e _{NO} | Output Noise | BW = 20 Hz to 20 KHz output muted | | 5 | | μV |
| | | BW = 20 Hz to 20 KHz all gain = 0dB | | 10 | | μV |
| S/N | Signal to Noise Ratio | all gain = 0dB flat; V _O = 2V _{RMS} | | 106 | | dB |
| | | bass treble at 12dB; V _O = 2.6V _{RMS} | | 96 | | dB |
| d | Distortion | V _{IN} = 1V _{RMS} ; all stages 0dB | | 0.002 | | % |
| | | V _{IN} = 1V _{RMS} ; Bass & Treble = 12dB | | 0.05 | | % |
| S _c | Channel separation Left/Right | | 80 | 100 | | dB |
| E _T | Total Tracking Error | A _v = 0 to -20dB | | 0 | 1 | dB |
| | | A _v = -20 to -60dB | | 0 | 2 | dB |

1) SM pin is active low (mute condition)

2) See description of Audioprocessor Part - Bass & Treble filter characteristics programming

DESCRIPTION OF THE AUDIOPROCESSOR

Figure 1. Input stages



Input stages

The input circuits are the same as in preceding ST audioprocessors with exception of the CD inputs (see figure 1).

The typical input impedance is 100k Ω .

AutoZero

In order to reduce the number of pins there is no AC coupling between the In-Gain and the following stage, so that any offset generated by or before the In-Gain stage would be transferred or even amplified to the output.

To avoid that effect a special offset cancellation stage called AutoZero is implemented.


To avoid audible clicks the audioprocessor is muted before the loudness stage during this time. In some cases, for example if the μ P is executing a refresh cycle of the I²C bus programming, it is not useful to start a new AutoZero action because no new source is selected and an undesired mute would appear at the outputs. For such applications the TDA7403 could be switched in the "AutoZero Remain" mode (Bit 6 of the subaddress byte). If this bit is set to high, the DATABYTE 0 could be loaded without invoking the AutoZero and the old adjustment value remains.

Softmute

The digitally controlled softmute stage allows muting/demuting the signal with a I²C bus programmable slope. The mute process can either be activated by the softmute pin or by the I²C bus. The slope is realized in a special S shaped curve to mute slow in the critical regions (see figure 2).


For timing purposes the Bit 3 of the I²C bus output register is set to 1 from the start of muting until the end of demuting.

Figure 2. Softmute Timing



Note: Please notice that a started Mute action is always terminated and could not be interrupted by a change of the mute signal.

Figure 3. Soft Step Timing



Note: For steps more than 1dB the softstep mode should be deactivated because it could generate a 1dB error during the blend-time

Softstep Volume

When volume level is changed often an audible click appears at the output. The root cause of those clicks could be either a DC offset before the volume stage or the sudden change of the envelope of the audio signal. With the Softstep feature both kinds of clicks could be reduced to a minimum and are no more audible (see figure 3).

Bass

There are three parameters programmable in the bass stage (see figs 4, 5, 6, 7):

- Attenuation
- Center Frequency (60, 70, 80 and 100Hz)
- Quality Factors (1, 1.25, 1.5 and 2)

DC Mode

In this mode the DC gain is increased by 4.4dB. In addition the programmed center frequency and quality factor is decreased by 25% which can be used to reach alternative center frequencies or quality factors.





Treble

There are two parameters programmable in the treble stage (see figs 8, 9):



- Attenuation
- Center Frequency (10, 12.5, 15 and 17.5kHz).

Speaker Attenuator

Due to practical aspects the steps in the speaker attenuators are not linear over the full range. At attenuations more than 24dB the steps increase from 1.5dB to 10dB (please see data byte specification).

Figure 4. Bass Control @ $f_c = 80\text{Hz}$, $Q = 1$ **Figure 5. Bass Center @ Gain = 14dB, $Q = 1$** **Figure 6. Bass Quality factors @ Gain = 14dB, $f_c = 80\text{Hz}$** **Figure 7. Bass normal and DC Mode @ Gain = 14dB, $f_c = 80\text{Hz}$** 

Note: In general the center frequency, Q and DC-mode can be set independently. The exception from this rule is the mode (5/xx1111xx) where the center frequency is set to 150Hz instead of 100Hz.

Figure 8. Treble Control @ $f_c = 17.5\text{KHz}$ **Figure 9. Treble Center Frequencies @ Gain = 14dB**

STEREODECODER PART

- No external components necessary
- PLL with adjustment free fully integrated VCO
- Automatic pilot dependent MONO/STEREO switching
- Very high suppression of intermodulation and interference
- Programmable Roll-Off compensation
- Dedicated RDS Softmute
- Highcut and Stereoblend characteristics programmable in a wide range
- Internal Noiseblanker with threshold controls
- Multipath detector with programmable internal/external influence
- I²C bus control of all necessary functions

ELECTRICAL CHARACTERISTICS ($V_S = 9V$; deemphasis time constant = $50\mu s$, $V_{MPX} = 500mV$, 75KHz deviation, $f = 1KHz$, $G_I = 6dB$, $T_{amb} = 25^\circ C$; unless otherwise specified).

| Symbol | Parameter | Test Condition | Min. | Typ. | Max. | Unit |
|-----------------|----------------------------------|-----------------------------------|------|------|------|------------|
| V_{IN} | MPX Input Level | Input Gain = 3.5dB | | 0.5 | 1.25 | V_{RMS} |
| R_{in} | Input Resistance | | | 100 | | K Ω |
| G_{min} | Minimum Input Gain | | | 3.5 | | dB |
| G_{max} | Max Input Gain | | | 11 | | dB |
| G_{STEP} | Step Resolution | | | 2.5 | | dB |
| SVRR | Supply Voltage Ripple Rejection | $V_{ripple} = 100mV$, $f = 1kHz$ | | 60 | | dB |
| α | Max Channel Separation | | | 50 | | dB |
| THD | Total Harmonic Distortion | | | 0.05 | | % |
| $\frac{S+N}{N}$ | Signal plus Noise to Noise Ratio | $S = 2V_{rms}$ | | 86 | | dB |

MONO/STEREO SWITCH

| | | | | | | |
|--------------|-------------------------|---------------------|--|----|--|----|
| V_{PTHST1} | Pilot Threshold Voltage | for Stereo, PTH = 1 | | 15 | | mV |
| V_{PTHST0} | Pilot Threshold Voltage | for Stereo, PTH = 0 | | 25 | | mV |
| V_{PTHMO1} | Pilot Threshold Voltage | for Mono, PTH = 1 | | 12 | | mV |
| V_{PTHMO0} | Pilot Threshold Voltage | for Stereo, PTH = 0 | | 19 | | mV |

PLL

| | | | | | | |
|--------------|---------------|--|-----|--|--|---|
| $\Delta f/f$ | Capture Range | | 0.5 | | | % |
|--------------|---------------|--|-----|--|--|---|

DEEMPHASIS and HIGHCUT

| | | | | | | |
|---------------|--------------------------|--|--|-----|--|---------|
| τ_{HC50} | Deemphasis Time Constant | Bit = 7, Subadr. 10 = 0 $V_{LEVEL} \gg V_{HCH}$ | | 50 | | μs |
| τ_{HC75} | Deemphasis Time Constant | Bit = 7, Subadr. 10 = 1 $V_{LEVEL} \gg V_{HCH}$ | | 75 | | μs |
| τ_{HC50} | Highcut Time Constant | Bit = 7, Subadr. 10 = 0 $V_{LEVEL} \gg V_{HCL}$ | | 150 | | μs |
| τ_{HC75} | Highcut Time Constant | Bit = 7, Subadr. 10 = 1 $V_{LEVEL} \gg V_{HCL}$ | | 225 | | μs |

STEREOBLEND and HIGHCUT-CONTROL

| | | | | | | |
|---------------|----------------------------|--|--|------|--|--------|
| REF5V | Internal Reference Voltage | | | 5 | | V |
| TCREF5V | Temperature Coefficient | | | 3300 | | ppm |
| L_{Gmin} | Min. LEVEL Gain | | | 0 | | dB |
| L_{Gmax} | Max. LEVEL Gain | | | 10 | | dB |
| L_{Gstep} | LEVEL Gain Step Resolution | | | 0.67 | | dB |
| V_{SBLmin} | Min. Voltage for Mono | | | 33 | | %REF5V |
| V_{SBLmax} | Max. Voltage for Mono | | | 58 | | %REF5V |
| $V_{SBLstep}$ | Step Resolution | | | 8.4 | | %REF5V |

ELECTRICAL CHARACTERISTICS (continued)

| Symbol | Parameter | Test Condition | Min. | Typ. | Max. | Unit |
|---|--------------------------------|---|------|------|------|--------|
| STEREOBLEND and HIGHCUT CONTROL | | | | | | |
| VHCH _{min} | Min. Voltage for NO Highcut | | | 42 | | %REF5V |
| VHCH _{max} | Max. Voltage for NO Highcut | | | 66 | | %REF5V |
| VHCH _{step} | Step Resolution | | | 8.4 | | %REF5V |
| VHCL _{min} | Min. Voltage for FULL High cut | | | 17 | | %VHCH |
| VHCL _{max} | Max. Voltage for FULL High cut | | | 33 | | %VHCH |
| Carrier and harmonic suppression at the output | | | | | | |
| α_{19} | Pilot Signal | f = 19KHz | | 50 | | dB |
| α_{38} | Subcarrier | f = 38KHz | | 75 | | dB |
| α_{57} | Subcarrier | f = 57KHz | | 62 | | dB |
| α_{76} | Subcarrier | f = 76KHz | | 90 | | dB |
| Intermodulation (Note1) | | | | | | |
| α_2 | Pilot Signal | f _{mod} = 10KHz; f _{spur} = 1KHz; | | 65 | | dB |
| α_3 | | f _{mod} = 13KHz; f _{spur} = 1KHz; | | 75 | | dB |
| Traffic Radio (Note 2) | | | | | | |
| α_{57} | Signal | f = 57KHz | | 70 | | dB |
| SCA - Subsidiary Communications Authorization (Note 3) | | | | | | |
| α_{67} | Signal | f = 67KHz | | 75 | | dB |
| ACI - Adjacent Channel Interference (Note 4) | | | | | | |
| α_{114} | Signal | f = 114KHz | | 95 | | dB |
| α_{190} | Signal | f = 190KHz | | 84 | | dB |

Notes to the characteristics:

- Intermodulation Suppression: measured with: 91% pilot signal; fm = 10kHz or 13kHz.
- Traffic Radio (V.F.) Suppression: measured with: 91% stereo signal; 9% pilot signal; fm=1kHz; 5% subcarrier (f = 57kHz, fm = 23Hz AM, m = 60%).
- SCA (Subsidiary Communications Authorization) measured with: 81% mono signal; 9% pilot signal; fm = 1kHz; 10%SCA - subcarrier (fs = 67kHz, unmodulated).
- ACI (Adjacent Channel Interference) measured with: 90% mono signal; 9% pilot signal; fm =1kHz; 1% spurious signal (fs = 110 kHz or 186kHz, unmodulated).

NOISE BLANKER PART

- internal 2nd order 140kHz high pass filter
- programmable trigger threshold
- additional circuits for trigger adjustment (deviation, field-strength)
- very low offset current during hold time
- four selectable pulse suppression times

ELECTRICAL CHARACTERISTICS (continued)

| Symbol | Parameter | Test Condition | | Min. | Typ. | Max. | Unit |
|-----------------------|--|---|-----------|------|----------|------|------------------|
| V _{TR} | Trigger Threshold ^{0) 1)} | meas. with V _{PEAK} = 0.9V | NBT = 111 | | 30 | | mV _{OP} |
| | | | NBT = 110 | | 35 | | mV _{OP} |
| | | | NBT = 101 | | 40 | | mV _{OP} |
| | | | NBT = 100 | | 45 | | mV _{OP} |
| | | | NBT = 011 | | 50 | | mV _{OP} |
| | | | NBT = 010 | | 55 | | mV _{OP} |
| | | | NBT = 001 | | 60 | | mV _{OP} |
| | | | NBT = 000 | | 65 | | mV _{OP} |
| V _{TRNOISE} | Noise Controlled Trigger Threshold ²⁾ | meas. with V _{PEAK} = 1.5V | NCT = 00 | | 260 | | mV _{OP} |
| | | | NCT = 01 | | 220 | | mV _{OP} |
| | | | NCT = 10 | | 180 | | mV _{OP} |
| | | | NCT = 11 | | 140 | | mV _{OP} |
| V _{RECT} | Rectifier Voltage | V _{MPX} = 0mV | | | 0.9 | | V |
| | | V _{MPX} = 50mV; f = 150kHz | | | 1.7 | | V |
| | | V _{MPX} = 100mV; f = 50kHz | | | 2.5 | | V |
| V _{RECT DEV} | deviation dependent rectifier Voltage ³⁾ | means. with V _{MPX} = 300mV (75Hz a3v.) | OVD = 11 | | 0.9(off) | | V _{OP} |
| | | | OVD = 10 | | 1.2 | | V _{OP} |
| | | | OVD = 01 | | 2.0 | | V _{OP} |
| | | | OVD = 00 | | 2.8 | | V _{OP} |
| V _{RECT FS} | Fieldstrength Controlled Rectifier Voltage ⁴⁾ | means. with V _{MPX} = 0mV V _{LEVEL} << V _{SBL} (fully mono) | FSC = 11 | | 0.9(off) | | V |
| | | | FSC = 10 | | 1.3 | | V |
| | | | FSC = 01 | | 1.8 | | V |
| | | | FSC = 00 | | 2.3 | | V |

0) All thresholds are measured using a pulse with T_R = 2 μs, T_{HIGH} = 2 μs and T_F = 10 μs.

1) NBT represents the Noiseblanker-Byte bits D2; D0 for the noise blanker trigger threshold

2) NCT represents the Noiseblanker-Byte bit pair D4,D3 for the noise controlled trigger adjustment

3) OVD represents the Noiseblanker-Byte bit pair D7,D6 for the over deviation detector

4) FSC represents the Fieldstrength-Byte bit pair D1,D0 for the fieldstrength control




Figure 10. Trigger Threshold vs. VPEAK




Figure 11. Deviation Controlled Trigger Adjustment




Figure 12. Fieldstrength Controlled Trigger Adjustment





Figure 13. Block diagram of the stereo decoder



DESCRIPTION OF STEREODECODER

The stereodecoder part of the TDA7403 (see Fig. 16) contains all functions necessary to demodulate the MPX signal like pilot tone dependent MONO/STEREO switching as well as "stereoblend" and "highcut" functions.

Adaptations like programmable input gain, roll-off compensation, selectable deemphasis time constant and a programmable fieldstrength input allow to use different IF devices.

Stereodecoder Mute

The TDA7403 has a fast and easy to control RDS mute function which is a combination of the audioprocessor softmute and the high-ohmic mute of the stereodecoder. If the stereodecoder is selected and a softmute command is sent (or activated through the SM pin) the stereodecoder will be set automatically to the high-ohmic mute condition after the audio signal has been softmuted.

Hence a checking of alternate frequencies could be performed. To release the system from the mute condition simply the unmute command must be sent: the stereodecoder is unmuted immediately and the audioprocessor is softly unmuted. Fig. 14 shows the output signal V_o as well as the internal stereodecoder mute signal. This influence of Softmute on the stereodecoder mute can be switched off by setting bit 3 of the Softmute byte to "0". A stereodecoder mute command (bit 0, stereodecoder byte set to "1") will set the stereodecoder in any case independently to the high-ohmic mute state.

If any other source than the stereodecoder is selected the decoder remains muted and the MPX pin is connected to V_{ref} to avoid any discharge of the coupling capacitor through leakage currents.


Input Stages

The Ingain stage allows to adjust the MPX signal to a magnitude of about 1Vrms internally which is the recommended value. The 4.th order input filter has a corner frequency of 80kHz and is used to attenuate spikes and noise and acts as an anti-aliasing filter for the following switch capacitor filters.

Demodulator

In the demodulator block the left and the right channel are separated from the MPX signal. In this stage also the 19 kHz pilot tone is cancelled. For reaching a high channel separation the TDA7403 offers an I2C bus programmable roll-off adjustment which is able to compensate the low-

Figure 14. Signals during stereodecoder's softmute



pass behaviour of the tuner section. If the tuner attenuation at 33kHz is in a range from 20.2% to 31% the TDA7403 needs no external network before the MPX pin. Within this range an adjustment to obtain at least 40dB channel separation is possible.

The bits for this adjustment are located together with the fieldstrength adjustment in one byte. This gives the possibility to perform an optimization step during the production of the carradio where the channel separation and the fieldstrength control are trimmed.

Deemphasis and Highcut

The lowpass filter for the deemphasis allows to choose between a time constant of 50μs and 75μs (bit D7, Stereodecoder byte).

The highcut control range will be in both cases $t_{HC} = 2 \cdot t_{Deemp}$. Inside the highcut control range (between VHCH and VHCL) the LEVEL signal is converted into a 5 bit word which controls the lowpass time constant between $t_{Deemp} \dots 3 \cdot t_{Deemp}$. There by the resolution will remain always 5 bits independently of the absolute voltage range between the VHCH and VHCL values.

The highcut function can be switched off by I2C bus (bit D7, Fieldstrength byte set to "0").

PLL and Pilot Tone Detector

The PLL has the task to lock on the 19kHz pilot tone during a stereo transmission to allow a correct demodulation. The included detector enables the demodulation if the pilot tone reaches the selected pilot tone threshold VPTHST. Two different thresholds are available. The detector output (signal STEREO, see block diagram) can be checked

by reading the status byte of the TDA7403 via I2C bus.

Fieldstrength Control

The fieldstrength input is used to control the high cut and the stereoblend function. In addition the signal can be also used to control the noise-blanker thresholds.

LEVEL Input and Gain

To suppress undesired high frequency modulation on the highcut and stereoblend function the LEVEL signal is lowpass filtered firstly. The filter is a combination of a 1st order RC lowpass at 53kHz (working as anti-aliasing filter) and a 1st-order switched capacitor lowpass at 2.2kHz. The second stage is a programmable gain stage to adapt the LEVEL signal internally to different IF.


The gain is widely programmable in 16 steps from 0dB to 10dB (step = 0.67dB). These 4 bits are located together with the Roll-Off bits in the "Stereodecoder Adjustment" byte to simplify a possible adaptation during the production of the carradio.

Stereoblend Control

The stereoblend control block converts the internal LEVEL voltage (LEVEL INTERN) into an demodulator compatible analog signal which is used to control the channel separation between 0dB and the maximum separation. Internally this control range has a fixed upper limit which is the internal reference voltage REF5V. The lower limit can be programmed to be 33%, 42%, 50% or 58% of REF5V (see fig. 16).

To adjust the external LEVEL voltage to the internal range two values must be defined: the LEVEL

Figure 15. Internal stereoblend characteristics



gain L_G and VSBL. To adjust the voltage where the full channel separation is reached (VST) the LEVEL gain L_G has to be defined. The following equation can be used to estimate the gain:

$$L_G = \frac{\text{REF5V}}{\text{Field strength voltage [STEREO]}}$$


The gain can be programmed through 4 bits in the "Stereodecoder-Adjustment" byte.

The MONO voltage VMO (0dB channel separation) can be chosen selecting 33, 42, 50 or 58% of REF5V.

All necessary internal reference voltages like REF5V are derived from a bandgap circuit. Therefore they have a temperature coefficient near zero. This is useful if the fieldstrength signal is also temperature compensated.

But most IF devices apply a LEVEL voltage with a TC of 3300ppm. The TDA7403 offers this TC for the reference voltages, too. The TC is selectable with bit D7 of the "stereodecoder adjustment" byte.


Figure 16. Relation between internal and external LEVEL voltage and setup of Stereoblend



Highcut Control

The highcut control setup is similar to the stereoblend control setup : the starting point VHCH can be set with 2 bits to be 42, 50, 58 or 66% of REF5V whereas the range can be set to be 17 or 33% of VHCH (see fig. 17).

Figure 17. Highcut characteristics



FUNCTIONAL DESCRIPTION OF THE NOISE-BLANKER

In the automotive environment the MPX signal is disturbed by spikes produced by the ignition and for example the wiper motor. The aim of the noiseblanker part is to cancel the audible influence of the spikes. Therefore the output of the stereodecoder is held at the actual voltage for 40µs.

In a first stage the spikes must be detected but to avoid a wrong triggering on high frequency (white) noise a complex trigger control is implemented. Behind the triggerstage a pulse former generates the "blanking" pulse. To avoid any crosstalk to the signalpath the noiseblanker is

supplied by his own biasing circuit.

Trigger Path

The incoming MPX signal is highpass filtered, amplified and rectified. This second order high-pass-filter has a corner frequency of 140kHz. The rectified signal, RECT, is lowpass filtered to generate a signal called PEAK. Also noise with a frequency 140kHz increases the PEAK voltage. The PEAK voltage is fed to a threshold generator, which adds to the PEAK voltage a DC dependent threshold VTH. Both signals, RECT and PEAK+VTH are fed to a comparator which triggers a re-triggerable monoflop. The monoflop's output activates the sample-and-hold circuits in the signalpath for 40µs.

The block diagram of the noiseblanker is given in fig.18.

Automatic Noise Controlled Threshold Adjustment (ATC)


There are mainly two independent possibilities for programming the trigger threshold:

- the low threshold in 8 steps (bits D0 to D2 of the noiseblanker byte)
- the noise adjusted threshold in 4 steps (bits D3 and D4 of the noiseblanker byte, see fig. 13).

The low threshold is active in combination with a good MPX signal without any noise; the PEAK voltage is less than 1V. The sensitivity in this operation is high.

If the MPX signal is noisy the PEAK voltage increases due to the higher noise, which is also rectified. With increasing of the PEAK voltage the trigger threshold increases, too. This particular gain is programmable in 4 steps (see fig. 10).

Figure 18. Block diagram of the noiseblanker



Automatic Threshold Control

Besides the noise controlled threshold adjustment there is an additional possibility for influencing the trigger threshold. It is depending on the stereoblend control.

The point where the MPX signal starts to become noisy is fixed by the RF part. Therefore also the starting point of the normal noise-controlled trigger adjustment is fixed (fig. 15). In some cases the behaviour of the noiseblanker can be improved by increasing the threshold even in a region of higher fieldstrength. Sometimes a wrong triggering occurs for the MPX signal often shows distortion in this range which can be avoided even if using a low threshold.

Because of the overlap of this range and the range of the stereo/mono transition it can be controlled by stereoblend. This threshold increase is programmable in 3 steps or switched off with bits D0 and D1 of the fieldstrength control byte.

Over Deviation Detector


If the system is tuned to stations with a high deviation the noiseblanker can trigger on the higher frequencies of the modulation. To avoid this wrong behaviour, which causes noise in the output signal, the noiseblanker offers a deviation dependent threshold adjustment.

By rectifying the MPX signal a further signal representing the actual deviation is obtained. It is used to increase the PEAK voltage. Offset and gain of this circuit are programmable in 3 steps with the bits D6 and D7 of the stereodecoder byte (the first step turns off the detector, see fig. 15).

TEST MODE

During the test mode which can be activated by setting bit D0 of the testing byte and bit D5 of the subaddress byte to "1" several internal signals are available at the CASSR pin. During this mode the input resistance of 100kOhm is disconnected from the pin. The internal signals available are shown in the software specification.

Figure 19. Application Example.




I²C BUS INTERFACE DESCRIPTION**Interface Protocol**

The interface protocol comprises:

- a start condition (S)
- a chip address byte (the LSB bit determines read

/ write transmission)

- a subaddress byte
- a sequence of data (N-bytes + acknowledge)
- a stop condition (P)



D97AU627

S = Start

ACK = Acknowledge

AZ = AutoZero-Remain

T = Testing

I = Autoincrement

P = Stop

MAX CLOCK SPEED 500kbts/s

The transmitted data is automatically updated after each ACK.

Transmission can be repeated without new chip address.

Auto increment

If bit I in the subaddress byte is set to "1", the autoincrement of the subaddress is enabled.

TRANSMITTED DATA (send mode)

| MSB | | | | LSB | | | |
|-----|---|---|---|-----|----|---|---|
| X | X | X | X | ST | SM | X | X |

SM = Soft mute activated

ST = Stereo

X = Not Used

SUBADDRESS (receive mode)

| MSB | | | | LSB | | | | FUNCTION |
|-----|----|---|---|-----|----|----|----|--|
| X | AZ | T | I | A3 | A2 | A1 | A0 | |
| | | | | 0 | 0 | 0 | 0 | Not allowed |
| | | | | 0 | 0 | 0 | 1 | Auto-Zero |
| | | | | 0 | 0 | 1 | 0 | Volume |
| | | | | 0 | 0 | 1 | 1 | Softmute |
| | | | | 0 | 1 | 0 | 0 | Bass / Treble Attenuator |
| | | | | 0 | 1 | 0 | 1 | Bass / Treble Configuration |
| | | | | 0 | 1 | 1 | 0 | Speaker attenuator LF |
| | | | | 0 | 1 | 1 | 1 | Speaker attenuator LR |
| | | | | 1 | 0 | 0 | 0 | Speaker attenuator RF |
| | | | | 1 | 0 | 0 | 1 | Speaker attenuator RR / Blanktime adjust |
| | | | | 1 | 0 | 1 | 0 | Stereodecoder |
| | | | | 1 | 0 | 1 | 1 | Noiseblanker |
| | | | | 1 | 1 | 0 | 0 | Fieldstrength Control |
| | | | | 1 | 1 | 0 | 1 | Configuration |
| | | | | 1 | 1 | 1 | 0 | Stereodecoder Adjustment |
| | | | | 1 | 1 | 1 | 1 | Testing |

T = Testmode

I = Autoincrement

AZ = Auto Zero Remain

X = not used

DATA BYTE SPECIFICATION

Input Selector

| MSB | | | | | | | LSB | FUNCTION |
|-----|----|----|----|----|----|----|-----|---------------------------|
| D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | |
| | | | | | 0 | 0 | 0 | Source Selector |
| | | | | | 0 | 0 | 1 | don't use |
| | | | | | 0 | 1 | 0 | Cassette |
| | | | | | 0 | 1 | 1 | don't use |
| | | | | | 1 | 0 | 0 | AM |
| | | | | | 1 | 0 | 1 | Stereo Decoder |
| | | | | | 1 | 1 | 0 | don't use |
| | | | | | 1 | 1 | 1 | Mute |
| | | | | | 1 | 1 | 1 | don't use |
| | | | | X | | | | Don't Care |
| | | | 1 | | 0 | 1 | 1 | AM/FM Mode |
| | | | 0 | | 0 | 1 | 1 | AM mono |
| | | | 0 | | 1 | 0 | 0 | AM stereo |
| | | | 1 | | 1 | 0 | 0 | AM through Stereo/Decoder |
| | | | | | | | | FM- Stereo/Decoder |
| 0 | 0 | 0 | | | | | | In-Gain |
| 0 | 0 | 1 | | | | | | 14dB |
| : | : | : | | | | | | 12dB |
| 1 | 1 | 0 | | | | | | : |
| 1 | 1 | 1 | | | | | | 2 dB |
| | | | | | | | | 0 dB |

For example to select the CD input in quasi-differential mode with gain of 3dB the Data Byte is: 0/01111000

Autozero

| MSB | | | | | | | LSB | LOUDNESS |
|-----|----|----|----|----|----|----|-----|-------------|
| D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | |
| 1 | | 1 | 1 | 0 | 0 | 0 | 0 | setting fix |

Mute, Beep and Mixing

| MSB | | | | | | | LSB | MUTE/BEEP/MIXING |
|-----|----|----|----|----|----|----|-----|--|
| D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | |
| | | | | | 0 | 0 | 0 | Mute Enable Softmute Disable Softmute Mute time =0.48 ms Mute time =0.96 ms Mute time =40.4 ms Mute time =324 ms Stereo Decoder Softmute Influence = off Stereo Decoder Softmute Influence = on |
| | | | | | 0 | 1 | 1 | |
| | | | | | 1 | 0 | | |
| | | | | 0 | 1 | 1 | | |
| | | | | 1 | | | | |
| 1 | 1 | 1 | 1 | | | | | Must be "1" |

Note: for more information to the Stereodecoder-Softmute-Influence please refer to the stereodecoder description.

Volume

| MSB | | | | | | | LSB | ATTENUATION |
|-----|----|----|----|----|----|----|-----|---|
| D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | |
| | 0 | 0 | 0 | 0 | 0 | 0 | 0 | Gain/Attenuation +32dB +31dB : +20dB +19dB +18dB : +1dB 0dB - 1dB : -78dB -79dB |
| | 0 | 0 | 0 | 0 | 0 | 0 | 1 | |
| | : | : | : | : | : | : | : | |
| | 0 | 0 | 0 | 1 | 1 | 0 | 0 | |
| | 0 | 0 | 0 | 1 | 1 | 0 | 1 | |
| | 0 | 0 | 0 | 1 | 1 | 1 | 0 | |
| | : | : | : | : | : | : | : | |
| | 0 | 0 | 1 | 1 | 1 | 1 | 1 | |
| | 0 | 1 | 0 | 0 | 0 | 0 | 0 | |
| | 0 | 1 | 0 | 0 | 0 | 0 | 1 | |
| | : | : | : | : | : | : | : | |
| | 1 | 1 | 0 | 1 | 1 | 1 | 0 | |
| | 1 | 1 | 0 | 1 | 1 | 1 | 1 | |
| 0 | | | | | | | | Softstep Softstep Volume = off Softstep Volume = on |
| 1 | | | | | | | | |

Note: It is not recommended to use a gain more than 20dB for system performance reason. In general, the max. gain should be limited by software to the maximum value, which is needed for the system.

Bass & Treble Attenuation

| MSB | | | | | | | LSB | BASS & TREBLE ATTENUATION |
|-----|----|----|----|----|----|----|-----|---------------------------|
| D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | |
| | | | | 0 | 0 | 0 | 0 | Treble Steps |
| | | | | 0 | 0 | 0 | 1 | -14dB |
| | | | | : | : | : | : | -12dB |
| | | | | 0 | 1 | 1 | 0 | : |
| | | | | 0 | 1 | 1 | 1 | -2dB |
| | | | | 1 | 1 | 1 | 1 | 0dB |
| | | | | 1 | 1 | 1 | 0 | 0dB |
| | | | | : | : | : | : | +2dB |
| | | | | 1 | 0 | 0 | 1 | : |
| | | | | 1 | 0 | 0 | 0 | +12dB |
| | | | | | | | | +14dB |
| 0 | 0 | 0 | 0 | | | | | Bass Steps |
| 0 | 0 | 0 | 1 | | | | | -14dB |
| : | : | : | : | | | | | -12dB |
| 0 | 1 | 1 | 0 | | | | | : |
| 0 | 1 | 1 | 1 | | | | | -2dB |
| 1 | 1 | 1 | 1 | | | | | 0dB |
| 1 | 1 | 1 | 0 | | | | | 0dB |
| : | : | : | : | | | | | +2dB |
| 1 | 0 | 0 | 1 | | | | | : |
| 1 | 0 | 0 | 0 | | | | | +12dB |
| | | | | | | | | +14dB |

For example 12dB Treble and -8dB Bass give the following DATA BYTE: 0 0 1 1 1 0 0 1.

Bass & Treble Filter Characteristics

| MSB | | | | | | | LSB | BASS & TREBLE FILTER |
|-----|----|----|----|----|----|----|-----|-----------------------------|
| D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | |
| | | | | | | 0 | 0 | Treble |
| | | | | | | 0 | 1 | Center Frequency = 10 KHz |
| | | | | | | 1 | 0 | Center Frequency = 12.5 KHz |
| | | | | | | 1 | 1 | Center Frequency = 15 KHz |
| | | | | | | | | Center Frequency = 17.5 KHz |
| | | | | 0 | 0 | | | Bass |
| | | | | 0 | 1 | | | Center Frequency = 60 Hz |
| | | | | 1 | 0 | | | Center Frequency = 70 Hz |
| | | | | 1 | 1 | | | Center Frequency = 80 Hz |
| | | | | 1 | 1 | | | Center Frequency = 100Hz |
| | | 1 | 1 | | 1 | | | Center Frequency = 150Hz |
| | | 0 | 0 | | | | | Quality factor = 1 |
| | | 0 | 1 | | | | | Quality factor = 1.25 |
| | | 1 | 0 | | | | | Quality factor = 1.5 |
| | | 1 | 1 | | | | | Quality factor = 2 |
| | 0 | | | | | | | DC-Gain = 0dB |
| | 1 | | | | | | | DC-Gain = ± 4.4 dB |
| 1 | | | | | | | | must be "1" |

For example Treble center frequency = 15kHz, Bass center frequency = 100Hz, Bass Q = 1 and DC = 0dB give the following DATA BYTE: 1 0 0 1 1 1 0

Speaker Attenuation (LF, LR, RF, RR)

| MSB | | | | | | | LSB | |
|-----|----|----|----|----|----|----|-----|--|
| D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | |
| | | 0 | 0 | 0 | 0 | 0 | 0 | Attenuation |
| | | 0 | 0 | 0 | 0 | 0 | 1 | 0dB |
| | | : | : | : | : | : | : | -1dB |
| | | 0 | 1 | 0 | 1 | 1 | 1 | : |
| | | 0 | 1 | 1 | 0 | 0 | 0 | -23dB |
| | | 0 | 1 | 1 | 0 | 0 | 1 | -24.5dB |
| | | 0 | 1 | 1 | 0 | 0 | 1 | -26dB |
| | | 0 | 1 | 1 | 0 | 1 | 0 | -28dB |
| | | 0 | 1 | 1 | 0 | 1 | 1 | -30 |
| | | 0 | 1 | 1 | 1 | 0 | 0 | -32dB |
| | | 0 | 1 | 1 | 1 | 0 | 1 | -35dB |
| | | 0 | 1 | 1 | 1 | 1 | 0 | -40dB |
| | | 0 | 1 | 1 | 1 | 1 | 1 | -50dB |
| 1 | 1 | 1 | | | | | | Speaker Mute |
| | | | | | | | | Must be "1" (except RR speaker; see below) |
| 0 | 0 | | | | | | | Blank Time at i. (only at RR speaker) |
| 0 | 1 | | | | | | | 38μs |
| 1 | 0 | | | | | | | 25.5μs |
| 1 | 1 | | | | | | | 32μs |
| | | | | | | | | 22μs |

Stereodecoder

| MSB | | | | | | | LSB | FUNCTION |
|-----|----|----|----|----|----|----|-----|----------------------------------|
| D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | |
| | | | | | | | 0 | STD Unmuted |
| | | | | | | | 1 | STD Muted |
| | | | | | 0 | 0 | | IN-Gain 11dB |
| | | | | | 0 | 1 | | IN-Gain 8.5dB |
| | | | | | 1 | 0 | | IN-Gain 6dB |
| | | | | | 1 | 1 | | IN-Gain 3.5dB |
| | | | | 1 | | | | must be "1" |
| | | 1 | 0 | | | | | Forced MONO |
| | | 1 | 1 | | | | | MONO/STEREO switch automatically |
| | 0 | | | | | | | Pilot Threshold HIGH |
| | 1 | | | | | | | Pilot Threshold LOW |
| 0 | | | | | | | | Deemphasis 50μs |
| 1 | | | | | | | | Deemphasis 75μs |

Noiseblanker

| MSB | | | | | | | LSB | FUNCTION |
|-----|----|----|----|----|----|----|-----|----------------------------------|
| D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | |
| | | | | | 0 | 0 | 0 | Low Threshold 65mV |
| | | | | | 0 | 0 | 1 | Low Threshold 60mV |
| | | | | | 0 | 1 | 0 | Low Threshold 55mV |
| | | | | | 0 | 1 | 1 | Low Threshold 50mV |
| | | | | | 1 | 0 | 0 | Low Threshold 45mV |
| | | | | | 1 | 0 | 1 | Low Threshold 40mV |
| | | | | | 1 | 1 | 0 | Low Threshold 35mV |
| | | | | | 1 | 1 | 1 | Low Threshold 30mV |
| | | | 0 | 0 | | | | Noise Controlled Threshold 320mV |
| | | | 0 | 1 | | | | Noise Controlled Threshold 260mV |
| | | | 1 | 0 | | | | Noise Controlled Threshold 200mV |
| | | | 1 | 1 | | | | Noise Controlled Threshold 140mV |
| | | 0 | | | | | | Noise blanker OFF |
| | | 1 | | | | | | Noise blanker ON |
| 0 | 0 | | | | | | | Over deviation Adjust 2.8V |
| 0 | 1 | | | | | | | Over deviation Adjust 2.0V |
| 1 | 0 | | | | | | | Over deviation Adjust 1.2V |
| 1 | 1 | | | | | | | Over deviation Detector OFF |

Fieldstrength Control

| MSB | | | | | | | LSB | FUNCTION |
|-----|----|----|----|----|----|----|-----|--------------------------------------|
| D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | |
| | | | | | | 0 | 0 | Noiseblanker Field strength Adj 2.3V |
| | | | | | | 0 | 1 | Noiseblanker Field strength Adj 1.8V |
| | | | | | | 1 | 0 | Noiseblanker Field strength Adj 1.3V |
| | | | | | | 1 | 1 | Noiseblanker Field strength Adj OFF |
| | | | | 0 | 0 | | | VSBL at 33% REF 5V |
| | | | | 0 | 1 | | | VSBL at 42% REF 5V |
| | | | | 1 | 0 | | | VSBL at 50% REF 5V |
| | | | | 1 | 1 | | | VSBL at 58% REF 5V |
| | | 0 | 0 | | | | | VHCH at 42% REF 5V |
| | | 0 | 1 | | | | | VHCH at 50% REF 5V |
| | | 1 | 0 | | | | | VHCH at 58% REF 5V |
| | | 1 | 1 | | | | | VHCH at 66% REF 5V |
| | 1 | | | | | | | VHCL at 17% VHCH |
| | 0 | | | | | | | VHCL at 33% VHCH |
| 0 | | | | | | | | High cut OFF |
| 1 | | | | | | | | High cut ON |

Configuration

| MSB | | | | | | | LSB | FUNCTION |
|-----|----|----|----|----|----|----|-----|-------------|
| D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | |
| 1 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | setting fix |

Stereodecoder Adjustment

| MSB | | | | | | | LSB | FUNCTION |
|--------|-----------------------|-----------------------|-----------------------|-----------------------|---------------------------------|---------------------------------|---------------------------------|---|
| D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | |
| | | | | | 0 0 0 : 1 : 1 | 0 0 1 : 0 : 1 | 0 1 0 : 0 : 1 | Roll-Off Compensation not allowed 20.2% 21.9% : 25.5% : 31.0% |
| | 0 0 0 : 1 | 0 0 0 : 1 | 0 0 1 : 1 | 0 1 0 : 1 | | | | LEVEL Gain 0dB 0.66dB 1.33dB : 10dB |
| 0 1 | | | | | | | | Temperature compensation at LEVEL input TC = 0 TC = 16.7mV/k (3300ppm) |


Testing

| MSB | | | | | | | LSB | FUNCTION |
|--------|--------|--|--|---|---|--------|--------|---|
| D7 | D6 | D5 | D4 | D3 | D2 | D1 | D0 | |
| | | | | | | | 0 1 | Stereodecoder test signals OFF Test signals enabled if bit D5 of the subaddress (test mode bit) is set to "1", too |
| | | | | | | 0 1 | | External Clock Internal Clock |
| | | 0 0 0 0 0 0 0 0 1 1 1 1 1 1 1 1 | 0 0 0 0 1 1 1 1 0 0 0 1 1 1 1 1 | 0 0 1 1 0 1 1 0 0 0 1 0 1 0 1 | 0 1 0 1 0 1 1 0 0 1 0 1 0 1 1 | | | Testsignals at CASS_R VHCC Level intern Pilot magnitude VCOCON; VCO Control Voltage Pilot threshold HOLDN NB threshold F228 VHCCCL VSBL not used not used PEAK not used REF5V not used |
| | 0 1 | | | | | | | VCO OFF ON |
| 0 1 | | | | | | | | Audioprocessor test mode only if bit D5 of the subaddress (test mode bit) is set to "1" OFF |


Note : This byte is used for testing or evaluation purposes only and must not be set to other values than the default "11111110" in the application!

| DIM. | mm | | | inch | | |
|------|--------------------|------|-------|-------|-------|-------|
| | MIN. | TYP. | MAX. | MIN. | TYP. | MAX. |
| A | 2.35 | | 2.65 | 0.093 | | 0.104 |
| A1 | 0.1 | | 0.3 | 0.004 | | 0.012 |
| B | 0.33 | | 0.51 | 0.013 | | 0.020 |
| C | 0.23 | | 0.32 | 0.009 | | 0.013 |
| D | 12.6 | | 13 | 0.496 | | 0.512 |
| E | 7.4 | | 7.6 | 0.291 | | 0.299 |
| e | | 1.27 | | | 0.050 | |
| H | 10 | | 10.65 | 0.394 | | 0.419 |
| h | 0.25 | | 0.75 | 0.010 | | 0.030 |
| L | 0.4 | | 1.27 | 0.016 | | 0.050 |
| K | 0° (min.)8° (max.) | | | | | |

**OUTLINE AND
MECHANICAL DATA**



SO20



SO20MEC

Obsolete Product(s) - Obsolete Product(s)

Information furnished is believed to be accurate and reliable. However, STMicroelectronics assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of STMicroelectronics. Specification mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. STMicroelectronics products are not authorized for use as critical components in life support devices or systems without express written approval of STMicroelectronics.

The ST logo is a registered trademark of STMicroelectronics

© 2002 STMicroelectronics – Printed in Italy – All Rights Reserved

STMicroelectronics GROUP OF COMPANIES

Australia - Brazil - Canada - China - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco -
Singapore - Spain - Sweden - Switzerland - United Kingdom - United States.

<http://www.st.com>

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: org@lifeelectronics.ru

www.lifeelectronics.ru