

# TA1K & TA2K

## High Wattage Heat Sinkable Planar Resistor

The TAP series delivers 1000W or 2000W of continuous power when properly mounted to a liquid cooled heat sink (based on 85°C mounting plate temperature)

Applications include power conditioning, power distribution, power conversion, and power control.



### FEATURES

- High Energy Rating
- Low Inductance
- Resistor Element Electrically Isolated
- High Dielectric Strength
- Small Footprint

### APPLICATIONS

- Power semiconductor balancing
- Motor control
- Inrush Current Limiting

### CHARACTERISTICS

|                                    |                                       |
|------------------------------------|---------------------------------------|
| <b>Resistor Element</b>            | Thick Film on Alumina Substrate       |
| <b>Power Rating</b>                | 1000W or 2000W at 85°C mounting plate |
| <b>Resistance Values</b>           | 0.5Ω to 1000Ω                         |
| <b>Resistance Tolerance</b>        | +10% std.                             |
| <b>Max Operating Voltage</b>       | 2000VDC                               |
| <b>Temperature Coefficient</b>     | ± 250 PPM/°C                          |
| <b>Dielectric Strength</b>         | 6KV standard                          |
| <b>Operating Temperature Range</b> | -55°C to 85°C                         |
| <b>Terminal Screws</b>             | #10-32                                |
| <b>Max Contacts Torque</b>         | 10 in-lb                              |
| <b>Mounting Screws</b>             | #8-32                                 |
| <b>Max Mounting Torque</b>         | 15 in-lb                              |
| <b>Creepage Distance</b>           | 50mm ± 1mm (min)                      |

| Test  | Rating                         |         |
|---|--------------------------------|---------|
|   | Continuous                     | Pulse   |
| <b>Rated Power, max. current and heat sink plate temperature limited</b>                                    | (TA1K0) 1000W<br>(TA2K0) 2000W |         |
| <b>Operating Voltage</b>  | $\sqrt{P \cdot R}$             | N/A     |
| <b>Max. Applied Voltage, ohms law limited</b>   | 223V                           | 2000VDC |
| <b>Max. Current</b>   | 10A                            | 53.33A  |
| <b>Critical Resistance; below this resistance max power has to be de-rated due to exceeding max current</b> | (TA1K0) 10Ω<br>(TA2K0) 20Ω     |         |

| Test                       | Method   | Maximum ΔR                  |
|----------------------------|--|-----------------------------|
| <b>Short Time Overload</b> | $1.14 \times \sqrt{P \cdot R} / 10 \text{ sec @ } 70^\circ\text{C}$                | Max % ΔRsto = ±(2% + 0.05Ω) |
| <b>Moisture Resistance</b> | (TA1K0) 1000 hrs @ 40°C, 90-95% RH<br>(TA2K0) 1750 hrs @ 40°C, 90-95% RH           | ≤1%                         |
| <b>Thermal Shock</b>       | MIL-STD-202, Method 107  | MIL-STD-202, Method 107     |
| <b>Vibration, elec.</b>    | MIL-STD-202, Method 201  | ±2% Resistance              |
| <b>Vibration, mech.</b>    | MIL-STD-202, Method 201  | No Loose Terminal Screws    |
| <b>Load Life</b>           | (TA1K0) 1000 Hrs 90 min ON / 30 min OFF<br>(TA2K0) 1750 Hrs 90 min ON / 30 min OFF | ≤1%                         |
| <b>Pulse Tolerance</b>     | 52μF @ 2KV / 60 sec intervals, 104J, 20,000 Pulses                                 | ≤1%                         |
| <b>Dielectric Strength</b> | 6KVDC for 1 minute   | ≤1%                         |

### Derating



(continued)

# TA1K & TA2K

## High Wattage Heat Sinkable Planar Resistor

### DIMENSIONS



### APPLICATION NOTES

Proper heat sinking techniques are essential to performance of a TAP resistor. Please follow these guidelines when designing TAP system:

- Heatsink plate (base plate of the resistor) temperature must be monitored to establish proper de-rating. Best technique is to attach a thermocouple to the side of the base plate of the resistor. Temperature of plastic housing or heat sink cannot be used to establish rating of the resistor. Usage of laser thermometers should be avoided.
- To obtain a power rating of 1000W or 2000W, the bottom case temp must not exceed 85°C. This can only be achieved if the thermal conduction to the heatsink  $R_{th-cs} < 0.025^\circ\text{K/W}$ . This value can be reached by using thermal transfer compound with a heat conductivity of 1W/mK. The flatness of the cooling plate must be better than 0.05mm overall. The roughness of the surface should not exceed 6.4µm.
- Due to very high power density, only liquid cooled heat sinks are recommended for applications when >300W power rating is desired.
- Properly designed heat sink should have more than 2 cooling pipes under the surface of the TAP resistor. The Ohmite CP4 heat sink (<https://www.ohmite.com/cp4-series-chillplate/>) is an example of properly designed heat sink.

### ORDERING INFORMATION

RoHS Compliant

**TA1K0PH2R50KE**

|       |         |              |                           |                               |
|-------|---------|--------------|---------------------------|-------------------------------|
| Style | Wattage | Package Type | Resistance                | Tolerance                     |
|       |         |              | 2.5Ω = 2R50<br>50Ω = 50R0 | K = 10% (standard)<br>L = 20% |

#### Standard Part Numbers

| Ohms | 1000 Watt<br>10% Tolerance |             | Ohms          | 2000 Watt<br>10% Tolerance |  |
|------|----------------------------|-------------|---------------|----------------------------|--|
|      | Part Number                | Part Number |               |                            |  |
| 0.5  | TA1K0PHR500KE              | 0.5         | TA2K0PHR500KE |                            |  |
| 1    | TA1K0PH1R00KE              | 1           | TA2K0PH1R00KE |                            |  |
| 2.5  | TA1K0PH2R50KE              | 2.5         | TA2K0PH2R50KE |                            |  |
| 5    | TA1K0PH5R00KE              | 5           | TA2K0PH5R00KE |                            |  |
| 7.5  | TA1K0PH7R50KE              | 7.5         | TA2K0PH7R50KE |                            |  |
| 10   | TA1K0PH10R0KE              | 10          | TA2K0PH10R0KE |                            |  |
| 15   | TA1K0PH15R0KE              | 15          | TA2K0PH15R0KE |                            |  |
| 25   | TA1K0PH25R0KE              | 25          | TA2K0PH25R0KE |                            |  |
| 50   | TA1K0PH50R0KE              | 50          | TA2K0PH50R0KE |                            |  |
| 100  | TA1K0PH100RKE              | 100         | TA2K0PH100RKE |                            |  |
| 250  | TA1K0PH250RKE              | 250         | TA2K0PH250RKE |                            |  |
| 500  | TA1K0PH500RKE              | 500         | TA2K0PH500RKE |                            |  |
| 750  | TA1K0PH750RKE              | 750         | TA2K0PH750RKE |                            |  |
| 1000 | TA1K0PH1K00KE              | 1000        | TA2K0PH1K00KE |                            |  |

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: [org@lifeelectronics.ru](mailto:org@lifeelectronics.ru)