OMRON

Special-Purpose Photoelectric Sensors | E3C

Miniature Sensors with Separate Amplifiers Fit Tight Spaces

- Fast, 1 ms response time
- Light incident indicator on sensor
- Dust-resistant flat lens surface
- New, thin side view model
- Prewired sensors have 2 m (6.56 ft) cable
- Amplifier with built-in ON-, OFF- and one-shot delays available
- New prewired DC amplifier designed for track mounting has alarm output to signal unstable sensing conditions

Ordering Information

■ SENSORS

Through-beam Type

Shape							
Sensing distance	10 cm (3.94 in)	20 cm (7.87 in	30 cm (11.81 in)		50 cm (19.69 in)	1 m (3.28 ft)	2 m (6.56 ft)
Part number	**E3C-S10**	**E3C-S20W**	**E3C-S30W**	**E3C-S30T**	**E3C-S50**	**E3C-1**	**E3C-2**

Diffuse Reflective Type

Shape		
Sensing distance	5 cm (1.97 in)	10 cm (3.94 in)
Part number	**E3C-DS5W**	**E3C-DS10**

■ AMPLIFIERS

Shape	Fits 1/16 DIN panel cutout		For S3D8 controller	Miniature		 Slim, prewired	
Supply voltage	100 to 240 VAC, 50/60 Hz		12 to 24 VDC				
Output	Relay and NPN solid-state		NPN and PNP solid-state	NPN solid-state	PNP solid-state	NPN	PNP
Timer functions	—	ON-delay OFF-delay One-shot	—	—		40 ms OFF-delay	
Mounting style	Socket (included)		Track	Socket Track (order separately)			
Part number	**E3C-A**	**E3C-C**	**E3C-WH4F**	**E3C-GE4**	**E3C-GF4**	**E3C-JC4P**	**E3C-JB4P**

■ ACCESSORIES

Description		Part number
Mounting brackets	U-shaped, for E3C-S10, with 10 mm (0.394 in) sensing distance gap	**OAC-T1**
	U-shaped, for E3C-S10, with 20 mm (0.787 in) sensing distance gap	**OAC-T2**
	U-shaped, for E3C-S10, with 30 mm (1.181 in) sensing distance gap	**OAC-T3**
	L-shaped, for E3C-DS10	**E39-L42**
	L-shaped, for E3C-S50	**E39-L31**
Sockets required for E3C-G❑4 amplifier	Bottom surface mount socket	**PYF08M**
	Combination bottom surface and track-mount socket	**PYF08A-E**
Mounting track	DIN rail, 50 cm (1.64 ft) length	**PFP-50N**
	DIN rail, 1 m (3.28 ft) length	**PFP-100N**
	End plate	**PFP-M**
	Spacer	**PFP-S**

■ REPLACEMENT PARTS

Description	Part number
Track-mount socket for E3C-A and E3C-C amplifiers	**PF113A-E**
Mounting bracket for E3C-1	**E39-L41**
Mounting bracket for E3C-2	**E39-L42**
Mounting bracket for E3C-J❑4P	**E39-L48**

■ TYPICAL APPLICATIONS

Detect parts coming from a bowl feeder in a space-confined location



Space-saving flat sensors can detect small parts in tight spaces



Specifications

■ THROUGH-BEAM TYPE

Part number		E3C-S10	E3C-S20W	E3C-S30❑	E3C-S50	E3C-1	E3C-2
Sensing distance		10 cm (3.94 in)	20 cm (7.87 in)	50 cm (1.64 ft)		1 m (3.28 ft)	2 m (3.28 ft)
Light source		Pulse modulated infrared LED					
Detectable object	Type	Opaque materials					
	Size	2 mm (0.08 in) min. dimension	2 mm (0.09 in) min. dimension	3 mm (1.18 in) min. dimension		4 mm (0.16 in) min. dimension	8 mm (0.32 in) min. dimension
Required amplifier		E3C-A, E3C-C, E3C-GE4, E3C-GF4, E3C-JC4P, E3C-JB4P, E3C-WH4F					
Indicators	Emitter	Light Incident (red LED)					
	Receiver	None					
Materials	Lens	Plastic, polycarbonate					
	Case	Plastic, polycarbonate					Zinc die-cast
	Cable sheath	Plastic, polyethylene					
Mounting		Side surface with two through holes. Brackets OAC-T1, OAC-T2, OAC-T3 optional, see Accessories	Side surface with two through holes.	Side surface with two through holes. Bracket E39-L31 optional, see Accessories		Side surface with two through holes. Bracket E39-L41 and hardware included.	Side surface with two through holes. Bracket E39-L42 and hardware included.
Connections	Prewired	Emitter: 2-conductor cable, 2 m (6.56 ft) length Receiver: 2-conductor cable, 2 m (6.56 ft) length					
Weight	Emitter	25 g (0.9 oz.)				30 g (1.1 oz.)	60 g (2.2 oz.)
	Receiver	25 g (0.9 oz.)				30 g (1.1 oz.)	60 g (2.2 oz.)
Enclosure ratings	UL	—					
	NEMA	1, 2, 12	1	1	1, 2, 12	1, 2, 4, 4X, 12	
	IEC 144	IP64	IP50	IP60	IP64	IP66	
Approvals	UL	—					
	CSA	—					
Ambient temperature	Operating	-25° to 70°C (-13° to 158°F)					
	Storage	-25° to 70°C (-13° to 158°F)					

■ DIFFUSE REFLECTIVE TYPE

Part number		E3C-DS5W	E3C-DS10
Sensing distance		5 cm (1.97 in) with 10 X 10 cm (3.94 in) 90% reflectance white mat paper	10 cm (3.94 in) with 5 X 5 cm (1.97 in) 90% reflectance white mat paper
Detectable object type		Opaque and transparent materials	
Required amplifier		E3C-A, E3C-C, E3C-GE4, E3C-GF4, E3C-JC4P, E3C-JB4P, E3C-WH4F	
Indicators		Light Incident (red LED)	
Materials	Lens	Plastic, polycarbonate	
	Case	Plastic, polycarbonate	
	Cable sheath	Plastic, polyethylene	
Mounting		Side surface with two through holes.	Side surface with two through holes. Bracket E39-L42 optional, see Accessories.
Connections	Prewired	4-conductor cable, 2 m (6.56 ft) length	
Weight		50 g (1.8 oz.)	
Enclosure ratings	UL	—	
	NEMA	1	1, 2, 12
	IEC 144	IP50	IP64
Approvals	UL	—	
	CSA	—	
Ambient temperature	Operating	-25° to 70°C (-13° to 158°F)	
	Storage	-25° to 70°C (-13° to 158°F)	

■ AMPLIFIERS

AC Powered

Part number			E3C-A	E3C-C
Supply voltage			100 to 240 VAC, 50/60 Hz	
Power consumption			3 VA max.	
Operation mode			Light-ON/Dark-ON, switch selectable	
Sensitivity			Adjustable	
Control output	Relay	Type	SPDT	
		Max. load	1 A, 240 VAC (p.f. = 1)	
		Min. load	1 mA, 5 VDC	
	DC solid-state	Type	NPN-SPST with constant current source	
		Max. load	Load (relay, sink) logic, 80 mA, 24 VDC Voltage logic (source): 1.5 to 4 mA	
		Max. on-state voltage drop	1.0 VDC	
Response time	ON	Solid-state	1 ms or 2 ms max., switch selectable	
		Contact	20 ms max.	
	OFF	Solid-state	1 ms or 2 ms max., switch selectable	
		Contact	20 ms max.	
Timer functions		Type	—	ON-delay, OFF-delay, one-shot, switch selectable
		Range	—	0.1 to 1 second or 1 to 10 seconds, switch selectable
Circuit protection		Output short-circuit	Not available	
Indicators			Light Incident (red LED), Output Stability (green LED), Output Operation (red LED)	
Materials		Case	Plastic	
Mounting			Requires PF113A-E socket (included); socket mount to DIN rail track	
Connections			Terminal screws on socket	
Weight			220 g (7.8 oz.), including socket	
Enclosure ratings	UL		—	
	NEMA		1	
	IEC144		IP20	
Approvals	UL		—	
	CSA		—	
Ambient temperature	Operating		-10° to 55°C (14° to 131°F)	
	Storage		-25° to 70°C (-13° to 158°F)	

DC Powered

Part number			E3C-JB4P	E3C-JC4P	E3C-GE4	E3C-GF4	E3C-WH4F
Supply voltage			12 to 24 VDC ±10%; 1 V max. permissible ripple peak-to-peak				
Current consumption			50 mA				
Operation mode			Light-ON/Dark-ON switch selectable		Light-ON/Dark-ON, jumper selectable		Light-ON/Dark-ON switch selectable
Sensitivity			Adjustable				
Control output	DC solid-state	Type	PNP output	NPN output	NPN output with constant current source	PNP output	NPN and PNP open collector outputs
		Max. load	100 mA max. 24 VDC	100 mA max. 24 VDC	Load (relay, sink) logic: 80 mA, 24 VDC Voltage logic (source): 1.5 to 4 mA	100 mA max. 24 VDC	100 mA, 40 VDC (each output)
		Max. on-state voltage drop	0.7 VDC	0.7 VDC	1.2 VDC		0.7 VDC
Alarm output		Type	PNP	NPN	—		
		Max. load	50 mA, 24 VDC	50 mA, 24 VDC	—		
Response time		ON	1 ms		1 ms or 2 ms max., selectable		1 ms or 2 ms max. switch selectable
		OFF	1 ms or 40 ms, selectable		1 ms or 2 ms max., selectable		1 ms or 2 ms max. switch selectable
Circuit protection		Output short-circuit	Yes		Yes		Yes
		DC power supply reverse polarity	Yes		Yes		Yes

DC Amplifiers, continued

Part number		E3C-JB4P	E3C-JC4P	E3C-GE4	E3C-GF4	E3C-WH4F
Indicators		Light Incident (red LED), Output Stability (green LED)				
Materials	Case	Plastic				
Mounting		DIN rail track or mounting bracket E39-L48 (included) or side surface with two through holes		Requires PYF08A-E or PYF08M socket (not included). Order separately from Accessories.		DIN rail track or bottom surface with two through holes.
Connections		Prewired with 5 conductor cable, 2 m (6.56 ft) length		Terminal screws on socket		Terminal screws or direct connection to S3D8 Sensor Controller with E99-C connector (included).
Weight		80 g (2.8 oz.)		15 g (0.5 oz.)		100 g (3.5 oz.)
Enclosure	UL	—		—		
	NEMA	1, 2		1		
	IEC 144	IP50		IP20		
Approvals	UL	—				
	CSA	—				
Ambient temperature	Operating	-10° to 55°C (14° to 131°F)				
	Storage	-25° to 70°C (-13° to 158°F)				

■ OUTPUT CIRCUIT DIAGRAMS

Amplifiers E3C-A, E3C-C



Amplifiers E3C-J❑4P

PNP output type
E3C-JB4P



NPN output type
E3C-JC4P



OUTPUT CIRCUIT DIAGRAMS, continued

Amplifier E3C-GE4



PNP Output E3C-GF4



Amplifier E3C-WH4F



Engineering Data

■ EXCESS GAIN RATIO

E3C-S10



E3C-S20W



E3C-S30T, E3C-S30W



EXCESS GAIN RATIO, continued

E3C-S50



E3C-1



E3C-2



E3C-DS5W



E3C-DS10



■ LIGHT SOURCE/RECEIVER SETTING RANGE

Separate type

E3C-S10



E3C-S20W



E3C-S30T, E3C-S30W



LIGHT SOURCE/RECEIVER SETTING RANGE, continued

E3C-S50



E3C-1



E3C-2



■ OPERATING RANGE

Diffuse Reflective Type

E3C-DS5W



E3C-DS10 (Example 1)



E3C-DS10 (Example 2)



Dimensions

Unit: mm

■ SENSORS

E3C-S10





Mounting Brackets for E3C-S10

Mount the emitter and receiver on the legs of the U-shaped bracket so they face each other. Dimension "A" shows the fixed sensing distance.

Part number	Dimension A
OAC-T1	10 mm (0.394 in)
OAC-T1	20 mm (0.787 in)
OAC-T3	30 mm (1.81 in)



E3C-S20W





E3C-S30T





E3C-S30W





E3C-S50





E39-L31 Optional Mounting Bracket



E3C-1





NOTE:
E3C-1 is shown mounted in E39-L41 bracket supplied with each sensor.

E3C-2





NOTE:
E3C-2 is shown mounted in E39-L42 bracket supplied with each sensor.

E3C-DS5W





E3C-DS10





NOTE:
Use mounting bracket E39-L42, shown on E3C-2; order separately from Accessories.

■ AMPLIFIERS

E3C-A, E3C-C







NOTE: Socket PF113A-E and two hold-down clips are included with these amplifiers.

E3C-JB4P, E3C-JC4P







* Attach the caution label after adjusting the sensitivity adjuster.
** This is not necessary when mounting the amplifier on DIN rail track.

E3C-GE4, E3C-GF4



NOTE:
Order required socket PYF08A-E or PYF08M from Accessories section.

E3C-WH4F





Mounting holes



■ SOCKETS

PF113A-E Track-Mount Socket

Socket PF113A-E and two hold-down clips are supplied with E3C-A and E3C-C amplifiers.





Terminal arrangement (top view)



Mounting holes



PYF08A-E Combination Track and Bottom Mount Socket for E3C-GE4, E3C-GF4





Terminal arrangement (top view)



Mounting holes



PYF08M Bottom Surface Mount Socket for E3C-GE4, E3C-GF4





Terminal arrangement (top view)



Mounting holes



■ MOUNTING TRACK AND ACCESSORIES

PFP-100N/PFP-50N DIN Rail



PFP-M End Plate



PFP-S Spacer



Connections

Amplifier model	Sensors	
	Through-beam type	Diffuse reflective type
	E3C-S10, E3C-S20W, E3C-S30□, E3C-S50, E3C-1, E3C-2	E3C-DS5W, E3C-DS10
E3C-A, E3C-C		
E3C-JB4P and E3C-JC4P		
E3C-GE4		
Notes	*Shielded wires must not be peeled in excess of 2 cm (0.787 in) for receiver (white lead) and 5 cm (1.969 in) for the light source (red lead). **Response time is 1 ms when terminal 8 is left open and 2 ms when terminal 8 is short-circuited with the 0 V terminal of the power supply (negative side).	*Shielded wires must not be peeled in excess of 2 cm (0.787 in). **Response time is 1 ms when terminal 8 is left open and 2 ms when terminal 8 is short-circuited with the 0 V terminal of the power supply (negative side).

Connections, continued

Amplifier model	Sensors	
	Through-beam type	Diffuse reflective type
	E3C-S10, E3C-S20W, E3C-S30□, E3C-S50, E3C-1, E3C-2	E3C-DS5W, E3C-DS10
E3C-WH4F	 NOTE: Terminals 5, 6, 7, and 8 are not used when connected to S3D8 or S3D-F sensor controllers.	 NOTE: Terminals 5, 6, 7, and 8 are not used when connected to S3D8 or S3D-F sensor controllers.
Notes	*Shielded wires must not be peeled in excess of 2 cm (0.787 in) for the receiver (white lead) and 5 cm (1.969 in) for the light source (red lead).	*Shielded wires must not be peeled in excess of 2 cm (0.787 in).

Operation

■ E3C-A Amplifier



■ E3C-A Timing Chart



Selection of operation mode

DARK ON [■] **LIGHT ON** When light is incident, the output relay operates and solid-state output becomes high (H).

DARK ON [■] **LIGHT ON** When light is interrupted, the output relay operates and the solid-state output becomes high (H).

NOTE: 1. Control output is produced only during the input time.
2. When t exceeds 1 ms or 2 ms, solid-state output is produced. To produce relay contact output, t must be longer than 20 ms.

Selection of response time

2 msec (B) [■] 1 msec (A) The response time is set to 2 ms.

2 msec (B) [■] 1 msec (A) The response time is set to 1 ms.

■ E3C-C AMPLIFIER



Gate input operation
When the gate input terminal 9 is opened at HIGH level (6 to 30 VDC), the output relay performs the timer operation according to the input signal (light incident or light interrupted).

When the gate input terminal 9 is short-circuited with the 0 V terminal 2 at LOW level (0 to 2 VDC), the output relay releases without regard to the input signal or output state. The terminal generates an inhibit signal.

Selection of operation mode



When light is incident, the output relay operates and solid-state output becomes high (H).

When light is interrupted, the output relay operates the solid-state output becomes high (H).

Selection of response time



The response time is set to 2 ms.

The response time is set to 1 ms.

Setting the delay time



The delay time can be set within a range of 0.1 to 1 second.

The delay time can be set within a range of 1 to 10 seconds.



After selecting the delay time range by slide switch, set the delay time adjuster to the specific value. Turn the adjuster clockwise to increase the delay time.

Selecting timer function

ON D. (ON-delay) operation	
OFF D. (OFF-delay) operation	
O.S.D. (One-shot delay) operation	

E3C-C ON-Delay Timing Chart



E3C-C One-Shot Timing Chart



E3C-C OFF-Delay Timing Chart



■ E3C-JB4P, E3C-JC4P AMPLIFIERS



Timing Charts

Light-ON



Dark-ON



Alarm Output Timing Chart

The alarm output operates when the control output approaches critical OFF or ON state for more than 300 ms. An unstable state occurs when the amount of light incident upon the receiving element is within 20% of the amount of light needed to change the control output state.

The alarm output feature is designed to indicate gradual changes in sensor/reflector position, atmosphere, temperature or ambient light which result in an unstable control output. A change occurring less than 300 ms will not cause the alarm output to operate.

A 300 ms time delay is built into the alarm output circuit. This prevents false triggering of the alarm output as the leading and trailing edges of the object to be detected are sensed. The time can be extended by using an ON-delay timer in the circuit.



■ E3C-GE4 , E3C-GF4 AMPLIFIER



Selection of response time

Response	Wiring
1 ms	Terminal 8 open
2 ms	Terminal 8 shorted with terminal 4 (0 V)

E3C-GF4 Timing Chart



NOTE: t_1 and t_2 must exceed selected response time (1 or 2 ms) before solid-state output states will change.

■ E3C-WH4F AMPLIFIER



E3C-WH4F Timing Chart



NOTE: t_1 and t_2 must exceed selected response time (1 or 2 ms) before solid-state output states will change.

Selection of operation mode



Selection of response time



OMRON

OMRON ELECTRONICS LLC
One East Commerce Drive
Schaumburg, IL 60173
1-800-55-OMRON

OMRON ON-LINE
Global - http://www.omron.com
USA - http://www.omron.com/oei
Canada - http://www.omron.com/oci

OMRON CANADA, INC.
885 Milner Avenue
Scarborough, Ontario M1B 5V8
416-286-6465

Cat. No. CEDSAX4 11/01

Specifications subject to change without notice.

Printed in the U.S.A.

ООО «ЛайфЭлектроникс» “LifeElectronics” LLC

ИНН 7805602321 КПП 780501001 Р/С 40702810122510004610 ФАКБ "АБСОЛЮТ БАНК" (ЗАО) в г.Санкт-Петербурге К/С 30101810900000000703 БИК 044030703

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- *Конкурентоспособные цены и скидки постоянным клиентам.*
- *Специальные условия для постоянных клиентов.*
- *Подбор аналогов.*
- *Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.*

- *Приемлемые сроки поставки, возможна ускоренная поставка.*
- *Доставку товара в любую точку России и стран СНГ.*
- *Комплексную поставку.*
- *Работу по проектам и поставку образцов.*
- *Формирование склада под заказчика.*

- *Сертификаты соответствия на поставляемую продукцию (по желанию клиента).*
- *Тестирование поставляемой продукции.*
- *Поставку компонентов, требующих военную и космическую приемку.*
- *Входной контроль качества.*
- *Наличие сертификата ISO.*

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- *Регистрацию проекта у производителя компонентов.*
- *Техническую поддержку проекта.*
- *Защиту от снятия компонента с производства.*
- *Оценку стоимости проекта по компонентам.*
- *Изготовление тестовой платы монтаж и пусконаладочные работы.*

Тел: +7 (812) 336 43 04 (многоканальный)
Email: org@lifeelectronics.ru

www.lifeelectronics.ru