TO PIDSA HQ

DELIVERY SPECIFICATIONS						
(Orderer (Customer) Part Number Panasonic Global Part Number	AN48846B-NL				
	Vendor Issue Number	1203004				
DERER (CUSTOMER)	<u>Confirmation of Security Control</u> We confirm and certify that the products of these specific below). "Military Purpose" in this statement means the de without limitation nuclear weapons, biological weapons,	cations shall not be supplied so as to be used for Military Purpose (defined herein esign, development, manufacture, storage or use of any weapons, including chemical weapons and missiles.				
IDOR ORD	Receipt Date: / / "Changes in the description of Delivery Specifications" according to advance consultation.	and "changes that affect performance, quality or environment" are implemented パナソニック株式会社				
VEN	Issuance Date: / /	2012. 3.12 デバイス社 半導体事業グループ 汎用LSI BU SMART Puniness distraction S423141-04#01				



Panasonic

Request for your special attention and precautions in using the technical information and semiconductors described in this book

(1) If any of the products or technical information described in this book is to be exported or provided to non-residents, the laws and regulations of the exporting country, especially, those with regard to security export control, must be observed.
(2) The technical information described in this book is intended only to show the main characteristics and application circuit examples of the products. No license is granted in and to any intellectual property right or other right owned by Panasonic Corporation or any other company. Therefore, no responsibility is assumed by our company as to the infringement upon any such right owned by any other company which may arise as a result of the use of technical information de-scribed in this book.
(3) The products described in this book are intended to be used for general applications (such as office equipment, communications equipment, measuring instruments and household appliances), or for specific applications (such as for airplanes, aerospace, automotive equipment, traffic signaling equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
It is to be understood that our company shall not be held responsible for any damage incurred as a result of or in connection with your using the products described in this book for any special application.
(4) When designing your equipment. comply with the range of absolute maximum rating and the guaranteed operating conditions (such as result), other-wise, we will not be liable for any defect which may arise later in your equipment.
(5) Comply with the products may company agrees to your using the products in this book for any special application.
(4) When designing your equipment.
(5) Event and the guaranteed values, take into the consideration of incidence of break down and failure

Reprint from WARNING LABEL STANDARDS SC3-11-00007

This delivery specifications may include old company names such as "Matsushita Electronics Corporation" or "Semiconductor Company, Matsushita Electric Industrial Co., Ltd.""Semiconductor Company, Panasonic Corporation " Please interpret these old company names as Industrial Devices Company, Panasonic Corporation" as of January 1, 2012.

Regulations			10					Total Page	es	Page
No.	103	-56						14		1
)roo		\+ C	Stan	do	rde		
		Γ	100	IUC		Dlaii	ua	105		
			Part No			ΔΝΔ	8246	R		
	Р	ack	age Code	∍ No.		SMIN	II-5DE			
	Ŀ		age eeu							
				Semio	conduc	tor Compa	any			
				Pana	asonic	Corporatio	on			
		Esta	ablished by	Appl	ied by	Checked by	/ Pr	epared by		
					-					
								.		
		H.,	Shidooka	M.Hir	amatsu	N.Fujita		ramasaki		
2011-03-11										
Established	Revis	ed								

Product Standards

2

Contents

Overview	3
Features	3
Applications	3
Package	3
■ Туре	3
Block Diagram	4
Pin Descriptions	5
Absolute Maximum Ratings	6
■ Operating Supply Voltage Range	6
■ Allowable Voltage Range	6
Electrical Characteristics	7
Electrical Characteristics (Reference values for design)	8
■ Test Circuit Diagram	9
Technical Data	11
Usage Notes	12
■ Caution on Use of Hall ICs	13

AN48846B

1.8 V Supply voltage, Low current consumption, high sensitivity CMOS Hall IC Operates on Alternating Magnetic Field (low-speed rotation for lock direction)

Overview

AN48846B is a Hall IC (a magnetic sensor) for 1.8 V supply voltage by using Bi-CMOS technology. In this Hall IC, a Hall element, a offset cancel circuit, an amplifier circuit, a sample and hold circuit, a Schmidt circuit, and output stage FET are integrated on a single chip housed in a small package by IC technique.

Features

- High sensitivity (4 mT max) due to offset cancel circuit and a new sample and hold circuit.
- Small current by using intermittent action. (average supply current : 55 μ A typ. sampling cycle : 660 μ s typ at V_{CC} = 1.8 V)
- Small package (SMD)
- CMOS inverter output (no pull-up resistance)

Applications

• Magneto-electric Conversion Switch.

Package

- 5 pin Plastic Small Surface Mount Package (SMINI Type).
- Туре
- Bi-CMOS IC.

	Product Standards	AN48846B		
		Total Pages	Page	
		14	4	

Block Diagram



Note) This block diagram is for explaining functions. Part of the block diagram may be omitted, or it may be simplified.

		AN48846B		
Product Standar	Product Standards	Total Pages	Page	
		14	5	

Pin Descriptions

Pin No.	Pin name	Туре	Description
1	N.C.		N.C.
2	GND	Ground	Ground pin
3	N.C		N.C.
4	VCC	Power supply	Supply pin
5	OUT	Output	Output pin

	Product Standards	AN48846B		
		Total Pages	Page	
		14	6	

Absolute Maximum Ratings

Note) Absolute maximum ratings are limit values which do not result in damages to this IC, and IC operation is not guaranteed at these limit values.

A No.	Parameter	Symbol	Rating	Unit	Notes
1	Supply voltage	V _{CC}	4.0	V	*1
2	Supply current	I _{CC}	5	mA	_
3	Power dissipation	P _D	48	mW	*2
4	Operating ambient temperature	T _{opr}	-40 to +85	°C	*3
5	Storage temperature	T _{stg}	-55 to +125	°C	*3

Notes)*1: The values under the condition not exceeding the above absolute maximum ratings and the power dissipation.

*2 : The power dissipation shown is the value at $T_a = 85^{\circ}C$ for the independent (unmounted) IC package without a heat sink. When using this IC, refer to the P_D - T_a diagram of the package standard and design the heat radiation with sufficient margin so that the allowable value might not be exceeded based on the conditions of power supply voltage, load, and ambient temperature.

*3 : Except for the power dissipation, operating ambient temperature, and storage temperature, all ratings are for $T_a = 25^{\circ}C$.

Operating Supply Voltage Range

Parameter	Symbol	Range	Unit	Notes
Supply voltage range	V _{CC}	1.65 to 3.6	V	*1

Note) *1: The values under the condition not exceeding the above absolute maximum ratings and the power dissipation.

Allowable Voltage Range

Notes) • Allowable current and voltage ranges are limit ranges which do not result in damages to this IC, and IC operation is not guaranteed within these limit ranges.

• Voltage values, unless otherwise specified, are with respect to GND.

• Do not apply external currents or voltages to any pin not specifically mentioned.

Pin No.	No. Pin name Range		Unit	Note
2	GND	0	V	
5	OUT	-0.3 to (V _{CC} + 0.3)	V	*1

Note) *1 : (V_{CC} + 0.3) V ≤ 4.0 V.

Due du st Otens de vole	AN48	846B
Product Standards	Total Pages	Page
	14	7

Electrical Characteristics at $V_{CC} = 1.8 \text{ V}$ Note) $T_a = 25^{\circ}\text{C} \pm 2^{\circ}\text{C}$ unless otherwise specified.

В	B Devenuetor		Test	Canditiana	Limits			Linit	notoo
No.	Parameter	Symbol	Circuit	Conditions	Min	Тур	Max	Unit	notes
1	Operating magnetic flux density $H \rightarrow L$ BH		1	_	0.5	2.5	4.0	mT	*1
2	Operating magnetic flux density $L \rightarrow H$	BLH	1	_	-4.0	-2.5	-0.5	mT	*1
3	Output voltage Low	V _{OL}	2	$I_0 = 2 \text{ mA}, \text{ B} = 4.0 \text{ mT}$		0.1	0.3	V	
4	Output voltage High	V _{OH}	3	$I_0 = -2 \text{ mA}, \text{ B} = -4.0 \text{ mT}$	1.5	1.7		V	
5	Average supply current	I _{CC} (AVE)	4			55	65	μA	*2
6	Sampling Period T _{sam}		5		215	660	1030	μs	_

2011-03-11	
Established	Revised

Dreduct Sterederde	AN48	846B
Product Standards	Total Pages	Page
	14	8

Electrical Characteristics (Reference values for design) at V_{CC} = 1.8 V

Note) $T_a = 25^{\circ}C \pm 2^{\circ}C$ unless otherwise specified.

The characteristics listed below are reference values derived from the design of the IC and are not guaranteed by inspection. If a problem does occur related to these characteristics, we will respond in good faith to user concerns.

B		Queen al	Test	Conditions	Reference Values			1.1	Natas
No.	No. Parameter		Circuit		Min	Тур	Max	Unit	Notes
7	Hysteresis width BW 1			_	5.0	_	mT	_	
8	Active supply current I _{CC} (ON)		4	_			5.0	mA	*3
9	9 Standby supply current $I_{CC}(OFF)$		4				4	μA	*3
10	Active time t(ON)		5		_	21	_	μs	*3
11	Standby time	t(OFF)	5			640		μs	*3

Notes)*1: Symbol BHL shows the operating magnetic flux density at which output level is changed from high to low, and Symbol BLH shows the operating magnetic flux density at which output level is changed from low to high.

*2: $I_{CC}(AVE) = \{I_{CC}(ON) \times t(ON) + I_{CC}(OFF) \times t(OFF)\} / \{t(ON) + t(OFF)\}.$

*3: Power Supply Timing Chart

Normal operation starts approx. 660 μs after power supply is turned on.



2011-03-11
Established Revised

Draduat Standarda	AN48	846B
Product Standards	Total Pages	Page
	14	9

Test Circuit Diagram

1. Test Circuit 1 BHL, BLH

Change the applied magnetic flux density and measure the magnetic flux density when the output level changes to Low from High, or to High from Low.

Note) Operating flux density "BHL", "BLH", and Hysteresis width, "BW" are defined as shown in Figure 2





Figure1. Direction of applied magnetic field



Applied magnetic flux density B



2011-03-11	
2011-03-11	
Established	Revised

AN48846B					
Total Pages	Page				
14	10				

Test Circuit Diagram (continued)

2. Test Circuit 2 V_{OL}



3. Test Circuit 3 V_{OH}



4. Test Circuit 4 I_{CC}(ON), I_{CC}(OFF), I_{CC}(AVE)

5. Test Circuit 5 t(ON), t(OFF),Tsam



2011-03-11	
Established	Revised

	AN48846B	
Product Standards	Total Pages	Page
	14	11

Technical Data

• I/O block circuit diagrams and pin function descriptions

Note) The characteristics listed below are reference values derived from the design of the IC and are not guaranteed.

Pin No.	Waveform and voltage	Internal circuit	Impedance	Description
2	DC Voltage (0 V)		0 Ω	Ground pin [GND]
4	DC Voltage (0 V to 3.6 V)		Hi-Z	Supply pin [VCC]
5	Pulse Output (0 V to 3.6 V)		Hi-Z	Positive output pin [OUT]

2011-03-11	
Established	Revised

	AN48846B	
Product Standards	Total Pages	Page
	14	12

Usage Notes

- Special attention and precaution in using
 - 1. This IC is intended to be used for general electronic equipment.
 - Consult our sales staff in advance for information on the following applications:
 - Special applications in which exceptional quality and reliability are required, or if the failure or malfunction of this IC may directly jeopardize life or harm the human body.
 - Any applications other than the standard applications intended.
 - (1) Space appliance (such as artificial satellite, and rocket)
 - (2) Traffic control equipment (such as for automobile, airplane, train, and ship)
 - (3) Medical equipment for life support
 - (4) Submarine transponder
 - (5) Control equipment for power plant
 - (6) Disaster prevention and security device
 - (7) Weapon
 - (8) Others : Applications of which reliability equivalent to (1) to (7) is required

It is to be understood that our company shall not be held responsible for any damage incurred as a result of or in connection with your using the IC described in this book for any special application, unless our company agrees to your using the IC in this book for any special application.

- 2. Pay attention to the direction of LSI. When mounting it in the wrong direction onto the PCB (printed-circuit-board), it might smoke or ignite.
- 3. Pay attention in the PCB (printed-circuit-board) pattern layout in order to prevent damage due to short circuit between pins. In addition, refer to the Pin Description for the pin configuration.
- 4. Perform a visual inspection on the PCB before applying power, otherwise damage might happen due to problems such as a solderbridge between the pins of the semiconductor device. Also, perform a full technical verification on the assembly quality, because the same damage possibly can happen due to conductive substances, such as solder ball, that adhere to the LSI during transportation.
- 5. Take notice in the use of this product that it might break or occasionally smoke when an abnormal state occurs such as output pin-V_{CC} short (Power supply fault), output pin-GND short (Ground fault), or output-to-output-pin short (load short). And, safety measures such as an installation of fuses are recommended because the extent of the above-mentioned damage and smoke emission will depend on the current capability of the power supply.
- 6. When designing your equipment, comply with the range of absolute maximum rating and the guaranteed operating conditions (operating power supply voltage and operating environment etc.). Especially, please be careful not to exceed the range of absolute maximum rating on the transient state, such as power-on, power-off and mode-switching. Otherwise, we will not be liable for any defect which may arise later in your equipment.

Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.

- 7. When using the LSI for new models, verify the safety including the long-term reliability for each product.
- When the application system is designed by using this LSI, be sure to confirm notes in this book. Be sure to read the notes to descriptions and the usage notes in the book.
- 9. This IC is not applicable to automotive electronic parts.

	Product Standards	AN48846B	
		Total Pages	Page
		14	13

Caution on Use of Hall ICs

As the Hall-IC often detects movement, the position of the Hall-IC may be changed, and there is the risk of a change in detection level, if exposed to shock or vibration over a long period. Secure the IC by applying adhesive to the package or placing in a dedicated case.

1.When using an adhesive

Some kinds of adhesive generate gas (such as chrole gas) during curing. This corrosive gas corrodes the aluminum on the surface of the Hall-IC, and may cause a functional defect of disconnection.

If Hall-IC is to be sealed after installation, attention should be given to the adhesive used for Hall-IC installation, as well as for the adhesive or resin used for peripherals and substrate cleaner.

Please confirm the above matter to those manufacturers before using.

We could not select the specified adhesive, for we find it difficult to guarantee the ingredient of each adhesive.

2.When bending lead wire

Bend the lead wire without stressing the package.



Bending method of lead wire



Bending position of lead wire

3. Power supply line/ Power transmission line

If a power supply line/power transmission line becomes longer, noise and/or oscillation may be found on the line. In this case, set the capacitor of 0.1 μ F to 10 μ F near the Hall IC to prevent it.

If a voltage of 5.4 V or more is thought to be applied to the power supply line (reverse electromotive force from coil or the ignition pulse, etc.), protect it with external components (capacitor, resistor, zener diode, diode, surge absorbing elements, etc.).

4. Mounting the surface mount type (SMINI-5DE package)

When mounted on printed circuit board, the Hall-IC may be highly stressed by the warpage that may occur from the soldering. This may also cause a change in the operating magnetic flux density and a deterioration of its resistance to moisture.



Observe the recommended conditions since electrical characteristics can easily change due to stress when mounting. Avoid solding by using soldoring iron or solder flow (dip) method.

2011-03-11	
Established	Revised

	Product Standards	AN48846B	
		Total Pages	Page
		14	14

Caution on Use of Hall ICs (continued)

5. Mounting the insertion type (SE-3S package)

If the insertion type Hall-IC is inserted to the bottom of its lead into the printed circuit board, it will be stressed so that reliability can not be maintained. Set a space of at least 2.0 mm between the package and printed circuit board.

6.V_{cc} and GND

Do not connect VCC and GND pins reversely. Otherwise, the IC will be damaged. If the voltage of GND pin is set higher than that of the other pins, which is the same configuration as diode forward connection, it is set to ON at current may flow (About 0.7V), resulting in damage to the IC. (This is common to monolithic IC.)

7. Cautions of Hall IC at Power-On

When a Hall IC is turned on, the position of the magnet or looseness may cause the output of a Hall IC to be changed, and a pulse may be generated.

Therefore, care should be exercised whenever the output state of a Hall IC is critical when the supply power is ON.

8. When Hall-IC is fixed with holder

When a Hall-IC is mounted on the printed circuit board with a holder and the coefficient of expansion of the holder is large, the lead wire of the Hall-IC will be stretched and it may give a stress to the Hall IC.

If the lead wire is stressed intensely due to the distortion of holder or substrate, the adhesiveness between the package and the lead wire may be weakened and cause a minute gap resulting in the deterioration of its resistance to moisture.

9. On using flux in soldering

Choose a flux which does not include ingredients from the chloric group. The ingredients of chloric group may enter through the joint of the lead frame and package resin, causing corrosion and disconnection of the aluminum wiring on the surface of IC chip.

Regulations	SC2S2017			Total pages	Page
No.	30332017			6	1
					٦
			\mathbf{O}		
	Pack	lage (Stand	ards	
		U			
	Package Co	ode	SMINI-5	DF	
	S	emiconduc	tor Compan	ıу	
		Panasonic	Corporation	l	
	Established by	Applied by	Checked by	Prepared by	
	H.Shidooka	H.Yoshida	M.Okajima	M.Itoh	
ļ	1				
- Established P	- evised				

Package Standards	Total pages	Page	
	6	2	

1. Outline Drawing

Unit:mm

Package Code : SMINI-5DE



-

2. Package Structure (Technical Report : Reference Value) Package Code : SMINI-5DE

Chip Material		Si	1	
Leadframe material		Cu alloy	2	
Inner lead surface		Ag plating	3	
Outer lead surface		SnBi plating	4	
Chip mount Method Resin adhesive method		G		
	Material	Adhesive material		
Wirebond	Method	Thermo-compression bonding	6	
Wirebolid	Material	Au		
Molding	Method	Transfer molding		
	Material	Br/Sb Free Epoxy resin		
Mass		6 mg		



Semiconductor Company, Panasonic Corporation

Package Standards	Total pages	Page
	6	4

3. Mark Layout

Package Code : SMINI-5DE



Package Standards	Total pages	Page
-	6	5

4. Power Dissipation (Technical Report)

Package Code : SMINI-5DE



5. Power Dissipation (Supplementary Explanation)

[Experiment environment]

Power Dissipation (Technical Report) is a result in the experiment environment of SEMI standard (Ambient air temperature (Ta) is 25 degrees C)

[Supplementary information of PWB to be used for measurement]

The supplement of PWB information for Power Dissipation data (Technical Report) are shown below.

Indication	Total Layer	Resin Material
Glass-Epoxy	1-layer	FR-4
4-layer	4-layer	FR-4

[Notes about Power Dissipation (Thermal Resistance)]

Power Dissipation values (Thermal Resistance) depend on the conditions of the surroundings, such as specification of PWB and a mounting condition, and a ambient temperature. (Power Dissipation (Thermal Resistance) is not a fixed value.)

The Power Dissipation value (Technical Report) is the experiment result in specific conditions (evaluation environment of SEMI standard conformity), and keep in mind that Power Dissipation values (Thermal resistance) depend on circumference conditions and also change.

[Definition of each temperature and thermal resistance]

Ta : Ambient air temperature

The temperature of the air is defined at the position where the convection, radiation, etc. don't affect the temperature value, and it's separated from the heating elements.

- Tc : It's the temperature near the center of a package surface. The package surface is defined at the opposite side if the PWB.
- Tj : Semiconductor element surface temperature (Junction temperature.)
- Rth(j-c) : The thermal resistance (difference of temperature of per 1 Watts) between a semiconductor element junction part and the package surface
- Rth(c-a) : The thermal resistance (difference of temperature of per 1 Watts) between the package surface and the ambient air

Rth(j-a) : The thermal resistance (difference of temperature of per 1 Watts) between a semiconductor element junction part and the ambient air



Recommended		
	Total pages	page
Soldering Conditions	2	1

Product name : AN48846B-NL Package : SMINI-5DE

1. Recommended Soldering Conditions

In case that the semiconductor packages are mounted on the PCB, the soldering should be performed under the following conditions.

Reflow soldering

max. 260 °C Reflow peak temp. :



No.	mark	contents	value
1	T1	Pre-heating temp.	150 °C∼180 °C
2	t1	Pre-heating temp. hold time	60 s∼120 s
3	а	Rising rate	2 °C/s~5 °C/s
4	Тр	Peak temp.	255 °C+5 °C、-0 °C
5	tp	Peak temp. hold time	10 s±3 s
6	tw	High temp. region hold time	within 60 s $~(\geqq220~^\circ\!C)$
7	b	Down rate	2 °C/s~5 °C/s
8	-	Number of reflow	within 2 times

* Peak temperature : less than 260 $^\circ C$

*Temperature is measured at package surface point

2012/3/6	
Prepared	Revised

No. 11-158

Recommended		
	Total pages	page
Soldering Conditions	2	2

2. Storage environment after dry pack opening



Because the taping and the magazine materials are not the heat-resistant materials, the bake at 125°C cannot be done.
 Therefore, please solder everything or control everything in the rule time.
 Please keep them in an equal environment with the moisture-proof packaging or dry box.

(Temperature: room temperature, relative humidity: 30% or less.)

To control storage time, when bake in the taping and the magazine is necessary, it is

necessary for each type to set a bake condition. Please inquire of our company.

☆ AN48846B-NL limitation, low temperature bake condition : <u>40 °C / 25 %RH or less / 192 h</u>

3. Note

- (1) Storage environment conditions: keep the following conditions Ta=5 $^{\circ}C \sim 30 ^{\circ}C$, RH=30 % $\sim 70 ^{\circ}N$.
- ② Storage period before opening dry pack shall be 1year from a shipping day under Ta=5 $^{\circ}$ C \sim 30 $^{\circ}$ C, RH=30 $^{\circ}$ \sim 70 $^{\circ}$. When the storage exceeds, Bake at 125 $^{\circ}$ C with 15 h to 25 h.
- 3 Baking cycle should be only one time.

Please be cautious of solderability at baking.

- (4) In case that use reflow two times, 2nd reflow must be finished within 365 days.
- ⑤ Remove flux sufficiently from product in the washing process.

(Flux : Chlorineless rosin flux is recommended.)

⁶ In case that use ultrasonic for product washing,

There is the possibility that the resonance may occur due to the frequency and shape of PCB.

It may be affected to the strength of lead. Please be cautious of this matter.

No. 11-158

2012/3/6	
Prepared	Revised

推奨ランド図	SMIN	–5DE
Recommended	Total pages	page
Land Pattern	1	1

(参考ランド寸法 / PWB pad dimensions)

単位 / Unit:mm



2009.10.14	
Prepared	Revised



	包装仕様		
	Backing Specifications	Total pages	page
	racking specifications	3	2
2 梱包図 Packin	g figure		Unit:mm
1) エンボスキャリアテーフ Emboss carrier tape and	『概要と収納方向 I IC package direction of storage		
		引き出し方向 Direction of unreeli	ng
2)リール概要 Reel	3)内装箱寸法 Inn	er case size	
ϕ 13.0 ϕ 13.0 ψ 130+0/-3.0 (reference) 欠落部品な The lack of the product is	185 typ 185 typ	0. 185 C3ラベル貼りた	ict typ. typ.
4)外装箱寸法 Outer ca	se size	C3 Label sticks	this position
200 typ.	05typ.	ур.	

3 梱包数量 Packing quantity

	IC package quantity	contents
Reel	3,000 Pcs.	1 Reel
Inner case	15,000 Pcs.	5 Reels
Outer case	90,000 Pcs.	30 Reels



2. カバーテープ/Cover tape

項	目	照合文字	寸法	備考
Ite	m	Symbol	Dimensions	Remarks
製品挿入凹み角穴	縦/Length	A0	2.20+0.10 -0.08	
Dented square	横/Width	B0	2.40 ± 0.10	
hole for product	深さ/Depth	К	0.95 ± 0.10	
insertion	ピッチ/Pitch	P1	4.0±0.1	累積誤差±0.2max/10ピッチ Accumulated error ±0.2max/10 pitches
	直径/Diameter	D0	1.5+0.1/-0.0	
送り穴 Sprocket hole	ピッチ/Pitch	P0	4.0±0.1	累積誤差±0.2max/10ピッチ Accumulated error ±0.2max/10 pitches
	位置/Position	E	1.75 ± 0.10	
エンボス穴 Emboss hole	直径/Diameter	D1	1.0+0.3/-0.0	
中心線間距離 Center-to-center	縦方向/ Longitudinal	P2	2.00 ± 0.05	
distance	橫方向/Traverse	F	3.50 ± 0.05	
+ .× = -+	幅/Width	W1	5.4±0.1	
カハーテーフ Cover tape	材質/Material	木 [°] リエチレンテレ Polyethylene	7タレート(PET) terephthalate	帯電防止処理有り/Antistatic
キャリマニ プ	幅/Width	W	8.0 ± 0.3	
イヤリアナーフ Carrier tane	厚さ/Thickness	t1	0.2 ± 0.1	
	材質/Material	ポリスチレ	レン (PS)	帯電防止処理有り/Antistatic
穴部外形深さ/Hole	outer depth	K1	1.10 ± 0.15	
全体の厚さ/Total t	hickness	t2	1.20 ± 0.15	

注:1)各コーナー部のRは、0.25R以下/The radius at each corner shall be 0.25R or less.

※リール材質 : ポリスチレン (耐電防止処理有り) / Reel material : Polystyrene (Antistatic)

2009.12.15	
Prepared	Revised

Panasonic

Industrial Devices Company, Panasonic Corporation

1 Kotari-yakemachi, Nagaokakyo City, Kyoto 617-8520, Japan Tel:075-951-8151



ООО "ЛайфЭлектроникс"

ИНН 7805602321 КПП 780501001 Р/С 40702810122510004610 ФАКБ "АБСОЛЮТ БАНК" (ЗАО) в г.Санкт-Петербурге К/С 3010181090000000703 БИК 044030703

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный) Email: org@lifeelectronics.ru

www.lifeelectronics.ru