

Part Number: WP3A10F3C


### Features

- Mechanically and spectrally matched to the phototransistor.
- RoHS compliant.

### Description

F3 Made with Gallium Arsenide Infrared Emitting diodes.

### Package Dimensions



#### Notes:

1. All dimensions are in millimeters (inches).
2. Tolerance is  $\pm 0.25(0.01)$  unless otherwise noted.
3. Lead spacing is measured where the leads emerge from the package.
4. The specifications, characteristics and technical data described in the datasheet are subject to change without prior notice.



## Selection Guide

| Part No.  | Dice      | Lens Type   | Po (mW/sr) [2]<br>@ 20mA |      | Po (mW/sr) [2]<br>@ 50mA |      | Viewing<br>Angle [1] |
|-----------|-----------|-------------|--------------------------|------|--------------------------|------|----------------------|
|           |           |             | Min.                     | Typ. | Min.                     | Typ. | 2 $\theta$ 1/2       |
| WP3A10F3C | F3 (GaAs) | Water Clear | 8                        | 12   | 18                       | 32   | 50°                  |
|           |           |             | *3                       | *8   | *8                       | *15  |                      |

Notes:

1.  $\theta$ 1/2 is the angle from optical centerline where the luminous intensity is 1/2 of the optical peak value.
  2. Radiant Intensity/ luminous flux: +/-15%.
- \*Radiant intensity value is traceable to the CIE127-2007 compliant national standards.

## Electrical / Optical Characteristics at TA=25°C

| Parameter                | P/N | Symbol                 | Typ. | Max. | Units | Test Conditions           |
|--------------------------|-----|------------------------|------|------|-------|---------------------------|
| Forward Voltage [1]      | F3  | V <sub>F</sub>         | 1.2  | 1.6  | V     | I <sub>F</sub> =20mA      |
| Reverse Current          | F3  | I <sub>R</sub>         |      | 10   | uA    | V <sub>R</sub> = 5V       |
| Capacitance              | F3  | C                      | 90   |      | pF    | V <sub>F</sub> =0V;f=1MHz |
| Peak Spectral Wavelength | F3  | $\lambda$ <sub>P</sub> | 940  |      | nm    | I <sub>F</sub> =20mA      |
| Spectral Bandwidth       | F3  | $\Delta\lambda$ 1/2    | 50   |      | nm    | I <sub>F</sub> =20mA      |

Notes:


1. Forward Voltage: +/-0.1V.
2. Wavelength value is traceable to the CIE127-2007 compliant national standards.

## Absolute Maximum Ratings at TA=25°C





| Parameter                   | Symbol              | F3         | Units |
|-----------------------------|---------------------|------------|-------|
| Power dissipation           | P <sub>D</sub>      | 80         | mW    |
| DC Forward Current          | I <sub>F</sub>      | 50         | mA    |
| Peak Forward Current [1]    | i <sub>FS</sub>     | 1.2        | A     |
| Reverse Voltage             | V <sub>R</sub>      | 5          | V     |
| Operating Temperature       | T <sub>A</sub>      | -40 To +85 | °C    |
| Storage Temperature         | T <sub>STG</sub>    | -40 To +85 | °C    |
| Lead Solder Temperature [2] | 260°C For 3 Seconds |            |       |
| Lead Solder Temperature [3] | 260°C For 5 Seconds |            |       |

Notes:

1. 1/100 Duty Cycle, 10 $\mu$ s Pulse Width.
2. 2mm below package base.
3. 5mm below package base.






## WP3A10F3C



**PACKING & LABEL SPECIFICATIONS**

**WP3A10F3C**



|  |  |
|--|--|
| <b>Kingbright</b>  |  |
| P/NO: WP3A10XXX  |  |
| QTY: 1,000 pcs   | Q.C. <span style="border: 1px solid black; border-radius: 50%; padding: 2px;">Q C<br/>XX-XX-XXXX<br/>PASSED</span> |
| S/N: XXXX  |  |
| CODE: XXX  |  |
| LOT NO:  |  |
| <br>xxxxxxxxxxxxxxxxxxxxxxxxxxxx |  |
| RoHS Compliant   |  |

## PRECAUTIONS

1. The lead pitch of the LED must match the pitch of the mounting holes on the PCB during component placement. Lead-forming may be required to insure the lead pitch matches the hole pitch. Refer to the figure below for proper lead forming procedures. (Fig. 1)




Fig.1

”○” Correct mounting method ”×” Incorrect mounting method

2. When soldering wire to the LED, use individual heat-shrink tubing to insulate the exposed leads to prevent accidental contact short-circuit. (Fig.2)
3. Use stand-offs (Fig.3) or spacers (Fig.4) to securely position the LED above the PCB.




Fig. 2

Fig. 3

Fig. 4

4. Maintain a minimum of 2mm clearance between the base of the LED lens and the first lead bend. (Fig. 5 and 6)
5. During lead forming, use tools or jigs to hold the leads securely so that the bending force will not be transmitted to the LED lens and its internal structures. Do not perform lead forming once the component has been mounted onto the PCB. (Fig. 7)

6. Do not bend the leads more than twice. (Fig. 8)



Fig. 5



Fig. 6



Fig. 7



Fig. 8

7. During soldering, component covers and holders should leave clearance to avoid placing damaging stress on the LED during soldering.




8. The tip of the soldering iron should never touch the lens epoxy.

9. Through-hole LEDs are incompatible with reflow soldering.

10. If the LED will undergo multiple soldering passes or face other processes where the part may be subjected to intense heat, please check with Kingbright for compatibility.

11. Recommended Wave Soldering Profiles:



Notes:

1. Recommend pre-heat temperature of 105°C or less (as measured with a thermocouple attached to the LED pins) prior to immersion in the solder wave with a maximum solder bath temperature of 260°C
2. Peak wave soldering temperature between 245°C ~ 255°C for 3 sec (5 sec max).
3. Do not apply stress to the epoxy resin while the temperature is above 85°C.
4. Fixtures should not incur stress on the component when mounting and during soldering process.
5. SAC 305 solder alloy is recommended.
6. No more than one wave soldering pass.

All design applications should refer to Kingbright application notes available at <http://www.KingbrightUSA.com/ApplicationNotes>

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: [org@lifeelectronics.ru](mailto:org@lifeelectronics.ru)