NEW

"3 in 1" Combi-Terminal Switch

"3 in 1" combi-terminals function as .250 Quick Connect, Solder Lug or Screw Terminals.

In an effort aimed at reducing distributor inventory and increasing flexibility, Carling Technologies is pleased to introduce our new "Combi" terminal switches. These terminals function as both a .250 Quick Connect and Solder Lug terminal. In addition a screw and saddle clamp are included to provide a Screw Terminal option. This new offering is available on all full size Carling one to three pole rocker and toggle switches, and is a direct replacement for the discontinued Eaton 7800 series toggles with similar terminations.

Additional features include:

- UL, CSA approved
- Available with all circuits
- Parts provided in individual polybags
- Eliminates the need to stock three separate terminal configurations
- Available with standard #5 rating (10A 250VAC 15A 125 VAC 3/4 HP 125-250 VAC)
- Additional ratings to 20A 125 VAC available (consult factory for specifics)
- Full Choice of actuator colors and styles
- No additional lead-time

Product Availability:

- Samples and production orders are available

Product Bulletin #87R-1 April 18, 2002

For additional information on the "3 in 1" Combi-Terminal Switch, please contact a Carling Technologies Technical Customer Service Rep:

phone	(860) 793-9281
fax	(860) 793-9231
email	sales@carlingtech.com
internet	www.carlingtech.com
mail	Carling Technologies, Inc. 60 Johnson Avenue Plainville, CT 06062-1177

Carling Technologies™
Innovative Designs. Powerful Solutions.

“3 in 1” Combi-Terminal Rocker Switch Ordering Scheme

SINGLE POLE IN SINGLE POLE BASE

TILA57	-	1S	-	BL	-	FN
1 Base Part Number		*2 Actuator*		*3 Color*		*1 Base Part Number*

1 BASE PART NUMBER: SERIES / SINGLE POLE / CIRCUITRY / RATING 5 / TERMINATION[3]

RATING 5 = 10A 250 VAC, 15A 125 VAC, 3/4 HP 125-250 VAC[1]

TIL-Series Rocker

	single pole
circuit[4]	
ON-NONE-OFF	**TILA57**
(ON)-NONE-OFF	**TILA5H**
ON-NONE-(OFF)	**TILA5Y**
ON-NONE-ON	**TILB57**
ON-NONE-(ON)	**TILB5H**
ON-OFF-ON	**TILC57**
ON-OFF-(ON)	**TILC5H**
(ON)-OFF-(ON)	**TILC5Y**

2 ACTUATOR STYLE

1S	Angular/Smooth Face Gloss
1C	Angular/Cross Serration Gloss
1F	Flatted/Smooth Face Gloss
1L	Angular/Longline Serration Gloss

3 ACTUATOR COLOR[2]

BL	Black
WH	White
RD	Red

4 BRACKET STYLE[3]

FN	Metal Snap-In
FN BLK	Black Metal Snap-In
FN SS	Stainless Steel Snap-In
FW	Wide Stainless Steel Snap-In

NOTES

Three and four pole switches also available. Consult factory for details.

1 Rating appropriate for usage in low voltage DC applications. For additional rating requirements, consult factory.

2 Custom colors are available, consult factory.

3 Additional terminations and bracket styles are also available. Consult factory for catalog number callout.

4 ( ) - momentary

“3 in 1” Combi-Terminal Rocker Switch Ordering Scheme

SINGLE OR DOUBLE POLE IN DOUBLE POLE BASE

TIGK57	-	6M	-	BL	-	WBL
1 Base Part Number		*2 Actuator*		*3 Color*		*1 Base Part Number*

1 BASE PART NUMBER: SERIES / DOUBLE POLE BASE / CIRCUITRY / RATING 5 / TERMINATION[9]

RATING 5 = 10A 250 VAC, 15A 125 VAC, 3/4 HP 125-250 VAC[7]

TIG-Series Rocker

	single pole	*double pole*
circuit[9]		
ON-NONE-OFF	**TIGA57**	**TIGK57**
(ON)-NONE-OFF	**TIGA5H**	**TIGK5H**
ON-NONE-(OFF)	**TIGA5Y**	**TIGK5Y**
ON-NONE-ON	**TIGB57**	**TIGL57**
ON-NONE-(ON)	**TIGB5H**	**TIGL5H**
ON-OFF-ON	**TIGC57**	**TIGM57**
ON-OFF-(ON)	**TIGC5H**	**TIGM5H**
(ON)-OFF-(ON)	**TIGC5Y**	**TIGM5Y**

2 ACTUATOR STYLE

1S	Angular/Smooth Face Gloss[1]
1C	Angular/Cross Serrations Gloss[1]
1F	Flatted/Smooth Face Gloss[1]
1L	Angular/Longline Serrations Gloss[1]
6M	Curved/Smooth Face Matte[2]
6S	Curved/Smooth Face Gloss[2]
7S	Rounded Paddle/Smooth Face Gloss[1]

3 ACTUATOR COLOR[8]

BL	Black
WH	White
RD	Red

4 BRACKET STYLE[8]

NBL	Nylon Black
WBL	Watershedding Black[3]
MBL	Marine Style Black[3,5]
FN	Metal Snap-In[4]
FN BLK	Black Metal Snap-In[4]
FN SS	Stainless Steel Snap-In[4]
FW	Wide Stainless Steel Snap-In[4]

NOTES

Three and four pole switches also available. Consult factory for details.

1 NBL, FN, & FW brackets only.
2 NBL, WBL, & MBL brackets only. With 6M actuator, brackets also will be matte finish.
3 6M & 6S actuators only
4 Not available with 6M & 6S actuators.
5 Consists of WBL bracket, neoprene seal, and dummy rivets at open holes. Consult factory for agency approval status.
6 Rating appropriate for usage in low voltage DC applications. For additional rating requirements, consult factory.
7 Custom colors are available, consult factory.
8 Additional terminations and bracket styles are also available. Consult factory for catalog number callout.
9 ( ) - momentary

"3 in 1" Combi-Terminal Toggle Switch Ordering Scheme

SINGLE POLE IN SINGLE POLE BASE

2FA52 - **73**

1 Base Part Number — 2 Actuator

1 BASE PART NUMBER: SERIES / SINGLE POLE / CIRCUITRY / RATING 5 / TERMINATION

RATING 5 = 10A 250 VAC, 15A 125 VAC, 3/4 HP 125-250 VAC[2]

F-Series Toggle

circuit[1]	*single pole*
ON-NONE-OFF	**2FA52**
(ON)-NONE-OFF	**6FA5H**
ON-NONE-(OFF)	**6FA5Y**
ON-NONE-ON	**2FB52**
ON-NONE-(ON)	**6FB52**
ON-OFF-ON	**2FC52**
ON-OFF-(ON)	**6FC5Y**
(ON)-OFF-(ON)	**6FC5H**

2 BAT STYLE TOGGLE

unsealed	*toggle length*	*bushing length*
73	0.687	0.465
E3	2.000	0.465
sealed	*toggle length*	*bushing length*
78	0.687	0.465
E8	2.000	0.465

SINGLE AND DOUBLE POLE IN DOUBLE POLE BASE

2GK57 - **73**

1 Base Part Number — 2 Actuator

1 BASE PART NUMBER: SERIES / DOUBLE POLE BASE/ CIRCUITRY / RATING 5 / TERMINATION

RATING 5 = 10A 250 VAC, 15A 125 VAC, 3/4 HP125-250VAC[2]

G-Series Toggle

	single pole	*double pole*
circuit[1]		
ON-NONE-OFF	**2GA57**	**2GK57**
(ON)-NONE-OFF	**6GA5H**	**6GK5H**
ON-NONE-(OFF)	**6GA5Y**	**6GK5Y**
ON-NONE-ON	**2GB57**	**2GL57**
ON-NONE-(ON)	**6GB5H**	**6GL5H**
ON-OFF-ON	**2GC57**	**2GM57**
ON-OFF-(ON)	**6GC5H**	**6GM5H**
(ON)-OFF-(ON)	**6GC5Y**	**6GM5Y**

2 TOGGLE

bat style

unsealed	*toggle length*	*bushing length*
73	0.687	0.465
D-3B-B	0.687	0.379
sealed	*toggle length*	*bushing length*
78	0.687	0.465

paddle style

unsealed	*toggle length*	*bushing length*
NBL3	0.687	0.465
sealed	*toggle length*	*bushing length*
NBL8	0.687	0.465
D-4B-B	0.687	0.379

NOTES
Additional ratings available. Consult factory for ordering information.
Three and four pole switches also available. Consult factory for details.
1 ( ) - momentary
2 Rating appropriate for usage in low voltage DC applications. For additional rating requirements, consult factory.

LifeElectronics
Живое партнерство

ООО «ЛайфЭлектроникс» **“LifeElectronics” LLC**

ИНН 7805602321 КПП 780501001 Р/С 40702810122510004610 ФАКБ "АБСОЛЮТ БАНК" (ЗАО) в г.Санкт-Петербурге К/С 30101810900000000703 БИК 044030703

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- *Конкурентоспособные цены и скидки постоянным клиентам.*
- *Специальные условия для постоянных клиентов.*
- *Подбор аналогов.*
- *Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.*

- *Приемлемые сроки поставки, возможна ускоренная поставка.*
- *Доставку товара в любую точку России и стран СНГ.*
- *Комплексную поставку.*
- *Работу по проектам и поставку образцов.*
- *Формирование склада под заказчика.*

- *Сертификаты соответствия на поставляемую продукцию (по желанию клиента).*
- *Тестирование поставляемой продукции.*
- *Поставку компонентов, требующих военную и космическую приемку.*
- *Входной контроль качества.*
- *Наличие сертификата ISO.*

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- *Регистрацию проекта у производителя компонентов.*
- *Техническую поддержку проекта.*
- *Защиту от снятия компонента с производства.*
- *Оценку стоимости проекта по компонентам.*
- *Изготовление тестовой платы монтаж и пусконаладочные работы.*

Тел: +7 (812) 336 43 04 (многоканальный)
Email: org@lifeelectronics.ru

www.lifeelectronics.ru