



# CURRENT REGULATOR DIODES

Qualified per MIL-PRF-19500/463

Qualified Levels:  
JAN, JANTX, JANTXV  
and JANS

## DESCRIPTION

The popular 1N5283UR-1 thru 1N5314UR-1 series of 0.5 watt current regulators provides a selection from 0.22 mA to 4.7 mA in standard 10% tolerances. These devices regulate current over a broad voltage range as a counter part offering to Zeners (that regulate voltage over a broad current range). The DO-213AB package offers a double plug internal bond connection with a large die element for its unique function as a current limiter. Microsemi also offers numerous other Zener products to meet higher and lower power voltage regulation applications.

**Important:** For the latest information, visit our website <http://www.microsemi.com>.

## FEATURES


- JEDEC registered surface mount equivalent of 1N5283 thru 1N5314 series.
- High source impedance.
- Internal metallurgical bond.
- JAN, JANTX, JANTXV, and JANS qualifications are available per MIL-PRF-19500/463.
- Chips also available as JANHC and JANKC.
- RoHS compliant versions available (commercial grade only).



**DO-213AB  
(MELF, LL41)  
Package**

Also available in:

**DO-7 Package**  
(axial-leaded)

 [1N5283-1 to 1N5314-1](#)

## APPLICATIONS / BENEFITS

- Double-plug construction.
- Regulates current over a broad operating voltage and temperature range.
- Extensive selection from 0.22 mA to 4.7 mA.
- Standard current tolerances are plus/minus 10%.
- Non-sensitive to ESD.
- Inherently radiation hard as described in Microsemi "[MicroNote 050](#)".

## MAXIMUM RATINGS

| Parameters/Test Conditions   | Symbol                              | Value       | Unit |
|--|-------------------------------------|-------------|------|
| Junction and Storage Temperature   | T <sub>J</sub> and T <sub>STG</sub> | -65 to +175 | °C   |
| Thermal Resistance Junction-to-End Cap @ L = 0 in                          | R <sub>θJEC</sub>                   | 100         | °C/W |
| Thermal Impedance  | Z <sub>θJX</sub>                    | 25          | °C/W |
| Steady-State Power Dissipation @ T <sub>EC</sub> = +125 °C, <sup>(1)</sup> | P <sub>D</sub>                      | 500         | mW   |
| Working Peak Voltage   | V <sub>WM</sub>                     | 100         | V    |
| Solder Pad Temperature @ 10 s max.   | T <sub>SP</sub>                     | 260         | °C   |

**Notes:** 1. Derate at 10 mW/°C above +125 °C.

### MSC – Lawrence

6 Lake Street,  
Lawrence, MA 01841  
Tel: 1-800-446-1158 or  
(978) 620-2600  
Fax: (978) 689-0803

### MSC – Ireland

Gort Road Business Park,  
Ennis, Co. Clare, Ireland  
Tel: +353 (0) 65 6840044  
Fax: +353 (0) 65 6822298

**Website:**

[www.microsemi.com](http://www.microsemi.com)

**MECHANICAL and PACKAGING**

- CASE: Hermetically sealed glass case.
- TERMINALS: Tin/lead finished copper clad steel or RoHS compliant matte-tin finish available (commercial grade only).
- MARKING: Cathode band.
- POLARITY: Diode to be operated with the banded (cathode) end negative.
- MOUNTING SURFACE SELECTION: The Axial Coefficient of Expansion (COE) of this device is approximately +6PPM/°C. The COE of the Mounting Surface System should be selected to provide a suitable match with this device.
- WEIGHT: 0.2 grams.
- See [Package Dimensions](#) on last page.

**PART NOMENCLATURE**

**SYMBOLS & DEFINITIONS**

| Symbol          | Definition  |
|-----------------|---|
| $I_L$           | Limiting Current: A specified current below the lower knee of the current-regulating characteristic.                            |
| $I_S$           | Regulator current: A current within the regulating range of a current-regulator diode.  |
| $P_D$           | Power Dissipation: The power dissipation, dc.   |
| $R_{\theta JL}$ | Thermal Resistance Junction-to-Lead: The thermal resistance from the virtual junction(s) of a semiconductor device to the lead. |
| $T_L$           | Lead Temperature: The temperature of a lead terminal.   |
| $T_{SP}$        | Temperature Solder Pad: The maximum solder temperature that can be safely applied to the terminal.                              |
| $V_K$           | Knee Voltage: A specified regulator voltage near the lower knee of the current-regulating characteristic.                       |
| $V_L$           | Limiting Voltage: The voltage at point $I_L$ on the current-voltage characteristic.   |
| $V_S$           | Regulator Voltage: A voltage within the regulating range of a current-regulating diode.   |
| $Z_K$           | Knee Impedance: The small-signal impedance at operating point $V_K$ on the current-voltage characteristic.                      |
| $Z_S$           | Regulator Impedance: The small-signal impedance within the regulating range of a current-regulator diode.                       |
| $Z_{\theta JX}$ | Thermal Impedance: The thermal impedance junction to reference point.   |

**ELECTRICAL CHARACTERISTICS** ( $T_A = 25^\circ\text{C}$ , unless otherwise specified)

| TYPE NUMBER | REGULATOR CURRENT<br>$I_S$ (mA) @ $V_S = 25\text{ V}$ |       |       | MINIMUM DYNAMIC IMPEDANCE<br>@ $V_S = 25\text{ V}$<br>$z_s$ (M $\Omega$ )<br>(Note 1) | MINIMUM KNEE IMPEDANCE<br>@ $V_K = 6.0\text{ V}$<br>$z_k$ (M $\Omega$ )<br>(Note 2) | MAXIMUM LIMITING VOLTAGE<br>@ $I_L = 0.8 I_S$<br>(min)<br>$V_L$ (Volts) |
|-------------|---|-------|-------|---|---|---|
|             | NOM   | MIN   | MAX   |   |   |   |
| 1N5283UR    | 0.22  | 0.198 | 0.242 | 25.00   | 2.750   | 1.00  |
| 1N5284UR    | 0.24  | 0.216 | 0.264 | 19.00   | 2.350   | 1.00  |
| 1N5285UR    | 0.27  | 0.243 | 0.297 | 14.00   | 1.950   | 1.00  |
| 1N5286UR    | 0.30  | 0.270 | 0.330 | 9.000   | 1.600   | 1.00  |
| 1N5287UR    | 0.33  | 0.297 | 0.363 | 6.600   | 1.350   | 1.00  |
| 1N5288UR    | 0.39  | 0.351 | 0.429 | 4.100   | 1.000   | 1.05  |
| 1N5289UR    | 0.43  | 0.387 | 0.473 | 3.300   | 0.870   | 1.05  |
| 1N5290UR    | 0.47  | 0.423 | 0.517 | 2.700   | 0.750   | 1.05  |
| 1N5291UR    | 0.56  | 0.504 | 0.616 | 1.900   | 0.560   | 1.10  |
| 1N5292UR    | 0.62  | 0.558 | 0.682 | 1.550   | 0.470   | 1.13  |
| 1N5293UR    | 0.68  | 0.612 | 0.748 | 1.350   | 0.400   | 1.15  |
| 1N5294UR    | 0.75  | 0.675 | 0.825 | 1.150   | 0.335   | 1.20  |
| 1N5295UR    | 0.82  | 0.738 | 0.902 | 1.000   | 0.290   | 1.25  |
| 1N5296UR    | 0.91  | 0.819 | 1.001 | 0.880   | 0.240   | 1.29  |
| 1N5297UR    | 1.00  | 0.900 | 1.100 | 0.800   | 0.205   | 1.35  |
| 1N5298UR    | 1.10  | 0.990 | 1.210 | 0.700   | 0.180   | 1.40  |
| 1N5299UR    | 1.20  | 1.080 | 1.320 | 0.640   | 0.155   | 1.45  |
| 1N5300UR    | 1.30  | 1.170 | 1.430 | 0.580   | 0.135   | 1.50  |
| 1N5301UR    | 1.40  | 1.260 | 1.540 | 0.540   | 0.115   | 1.55  |
| 1N5302UR    | 1.50  | 1.350 | 1.650 | 0.510   | 0.105   | 1.60  |
| 1N5303UR    | 1.60  | 1.440 | 1.760 | 0.475   | 0.092   | 1.65  |
| 1N5304UR    | 1.80  | 1.620 | 1.980 | 0.420   | 0.074   | 1.75  |
| 1N5305UR    | 2.00  | 1.800 | 2.200 | 0.395   | 0.061   | 1.85  |
| 1N5306UR    | 2.20  | 1.980 | 2.420 | 0.370   | 0.052   | 1.95  |
| 1N5307UR    | 2.40  | 2.160 | 2.640 | 0.345   | 0.044   | 2.00  |
| 1N5308UR    | 2.70  | 2.430 | 2.970 | 0.320   | 0.035   | 2.15  |
| 1N5309UR    | 3.00  | 2.700 | 3.300 | 0.300   | 0.029   | 2.25  |
| 1N5310UR    | 3.30  | 2.970 | 3.630 | 0.280   | 0.024   | 2.35  |
| 1N5311UR    | 3.60  | 3.240 | 3.960 | 0.265   | 0.020   | 2.50  |
| 1N5312UR    | 3.90  | 3.510 | 4.290 | 0.255   | 0.017   | 2.60  |
| 1N5313UR    | 4.30  | 3.870 | 4.730 | 0.245   | 0.014   | 2.75  |
| 1N5314UR    | 4.70  | 4.230 | 5.170 | 0.235   | 0.012   | 2.90  |

**NOTE 1:**  $z_s$  is derived by superimposing a 90 Hz RMS signal equal to 10% of  $V_S$  on  $V_S$ .

**NOTE 2:**  $z_k$  is derived by superimposing a 90 Hz RMS signal equal to 10% of  $V_K$  on  $V_K$ .

GRAPHS



FIGURE 1 – CURRENT-REGULATOR CHARACTERISTICS



FIGURE 2 – TEMPERATURE COEFFICIENT

GRAPHS (continued)



FIGURE 3 – TEMPERATURE COEFFICIENT



FIGURE 4 – CURRENT REGULATION FACTOR

**PACKAGE DIMENSIONS**


| Symbol     | Dimensions |      |             |      |
|------------|------------|------|-------------|------|
|            | Inch       |      | Millimeters |      |
|            | Min        | Max  | Min         | Max  |
| <b>BD</b>  | 0.94       | .105 | 2.39        | 2.67 |
| <b>BL</b>  | .189       | .205 | 4.80        | 5.21 |
| <b>ECT</b> | .016       | .022 | 0.41        | 0.55 |
| <b>S</b>   | .001 min   |      | 0.03 min    |      |

**NOTES:**

1. Dimensions are in inches.
2. Millimeters are given for general information only.
3. In accordance with ASME Y14.5M, diameters are equivalent to  $\Phi$ x symbology.

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Microchip:

[JANS1N5288UR-1](#) [JAN1N5314UR-1](#) [JANTX1N5302UR-1](#) [JANTXV1N5288UR-1](#) [JAN1N5302UR-1](#) [JAN1N5304UR-1](#) [JANTX1N5291UR-1](#) [1N5301UR-1](#) [JANTXV1N5287UR-1](#) [1N5304UR-1](#) [JANS1N5305UR-1](#) [JANTXV1N5304UR-1](#) [JAN1N5291UR-1](#) [JAN1N5296UR-1](#) [JANTXV1N5290UR-1](#) [JANTX1N5310UR-1](#) [JANTXV1N5312UR-1](#) [JANTXV1N5283UR-1](#) [JAN1N5285UR-1](#) [JANTX1N5306UR-1](#) [1N5310UR-1](#) [JAN1N5301UR-1](#) [JANTXV1N5306UR-1](#) [JANS1N5290UR-1](#) [JANS1N5296UR-1](#) [JANS1N5295UR-1](#) [JAN1N5308UR-1](#) [JANTXV1N5285UR-1](#) [JANTX1N5285UR-1](#) [JANTXV1N5310UR-1](#) [JANTXV1N5286UR-1](#) [JANTXV1N5300UR-1](#) [JANS1N5284UR-1](#) [JANS1N5291UR-1](#) [JANTX1N5298UR-1](#) [JAN1N5313UR-1](#) [JANS1N5300UR-1](#) [JAN1N5283UR-1](#) [JANS1N5289UR-1](#) [JANS1N5283UR-1](#) [1N5308UR-1](#) [JANS1N5309UR-1](#) [JAN1N5297UR-1](#) [JAN1N5306UR-1](#) [1N5292UR-1](#) [JAN1N5298UR-1](#) [JANS1N5308UR-1](#) [JANTXV1N5289UR-1](#) [JAN1N5284UR-1](#) [JANTX1N5311UR-1](#) [JANTXV1N5292UR-1](#) [JANTX1N5292UR-1](#) [JANTX1N5312UR-1](#) [1N5300UR-1](#) [JAN1N5289UR-1](#) [JAN1N5286UR-1](#) [1N5285UR-1](#) [JANS1N5292UR-1](#) [1N5291UR-1](#) [JANTX1N5284UR-1](#) [JANS1N5306UR-1](#) [1N5293UR-1](#) [1N5299UR-1](#) [1N5287UR-1](#) [JANS1N5301UR-1](#) [JAN1N5303UR-1](#) [JANTX1N5304UR-1](#) [1N5283UR-1](#) [JAN1N5309UR-1](#) [JANTX1N5313UR-1](#) [JANTX1N5308UR-1](#) [JANTX1N5288UR-1](#) [1N5284UR-1](#) [1N5303UR-1](#) [JAN1N5288UR-1](#) [JANS1N5310UR-1](#) [JANS1N5311UR-1](#) [JAN1N5310UR-1](#) [JANTX1N5289UR-1](#) [JANTX1N5301UR-1](#) [1N5297UR-1](#) [1N5296UR-1](#) [1N5295UR-1](#) [JANS1N5297UR-1](#) [JANS1N5294UR-1](#) [JAN1N5292UR-1](#) [JANTXV1N5293UR-1](#) [JANS1N5314UR-1](#) [JANS1N5304UR-1](#) [JANTX1N5305UR-1](#) [JANTX1N5314UR-1](#) [1N5289UR-1](#) [JAN1N5293UR-1](#) [JANS1N5302UR-1](#) [JANTXV1N5295UR-1](#) [1N5305UR-1](#) [JANTXV1N5307UR-1](#) [JANS1N5287UR-1](#) [JANTX1N5296UR-1](#) [1N5313UR-1](#)

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: [org@lifeelectronics.ru](mailto:org@lifeelectronics.ru)