

Class CC/CD and Midget Fuse Blocks

600 Volt



Space saving 600 volt, 30 amp molded case fuse blocks with side barriers for isolation. Class CC blocks and Midget blocks are identical except Class CC blocks incorporate a rejection feature to assure proper fusing.

Safety

- Rejection feature — Class CC fuse blocks have a rejection feature which prevents the insertion of fuses with lower interrupting rating or voltage ratings. Class CC fuses are rated 600 volts and have an

interrupting rating of 200,000 amperes. Midget fuse voltage ratings vary and their interrupting rating may be as low as 10,000 amperes. *Note that Class CC fuses may be used in Midget fuse blocks, but Midget fuses cannot be used in Class CC blocks.*

Long life

- High-strength materials — Class CC and Midget fuse blocks are molded of high-strength, high-temperature material to minimize block breakage during handling and installation, as well as damage caused by overheating.
- Reduced resistance, less heat — High conductivity, one-piece copper alloy fuse clips have lower resistance than traditional two-piece brass or phosphor bronze fuse clips, which minimizes heat rise and watts loss within the fuse block.

Reduced inventory

- Gangable — Interlocking fuse blocks allow ganging to produce a fuse block with any number of poles.
- Flexible terminal arrangements — 30A Class CC and Midget fuse blocks are available with type C box lug, type SQ screw, or type PQ pressure plate terminals. Type SQ terminals have binding-head screws, while type PQ terminals have captive pressure plates. Both terminal types can accommodate side or top mounted quick-connect terminals. This flexibility allows the accommodation of most needs and reduces part inventory requirements.
- 60A CD fuse blocks are available with type C box lug terminals.
- DIN rail mountable — FBDIN1 adapters permit snap-mounting Littelfuse Class CC and Midget 30 amp fuse blocks directly to standard or low profile 35mm symmetrical “hat” and 32mm asymmetrical DIN rails. Patented DIN rail adapters snap securely to Littelfuse fuse blocks and to DIN rails without tools. They can be readily removed from rails by lifting the disconnect tab.
- L60060C 60A fuse blocks have patented integral DIN rail adapters which allow direct mounting to 35mm “hat” type DIN rails.

Specifications

| | |
|--|--|
| Voltage Rating: | 600 Volts AC/600 Volts DC |
| Ampere ratings: | L60030C: 30 amps L60030M: 30 amps L60060C: 60 amps |
| Dielectric strength: | 1200 volts minimum |
| Clip/terminals: | Tin-plated copper alloy |
| Box lug: | Copper |
| Screw and captive pressure plate: | Zinc-plated steel |
| Base: | Thermoplastic. UL 94V0 flammability rating. |
| Approvals: | Class CC: UL Listed (File No. E14721) Midget: UL Recognized (File No. E14721) Class CC/Midget: CSA Certified (File No. LR7316) |

Recommended Fuses

Class CC Blocks:

CCMR | KLDR | KLKR

Midget Blocks:

BLF | BLS | FLM | FLU | KLKD | LA60Q-2
BLN | FLA | FLQ | KLK | KLO

Class CD Blocks:

CCMR

Note: L60030M can be used up to 40A.

Class CC/CD and Midget Fuse Blocks

600 Volt

Class CC 30A Fuse Blocks

| Amp Rating | No. of Poles | Catalog Number | Connector Type (Add Suffix Shown) | Maximum Wire Size |
|------------|--------------|----------------|-----------------------------------|-------------------|
| 30 | 1 | L60030C-1C | Box Lug | #6 CU |
| | 2 | L60030C-2C | | |
| | 3 | L60030C-3C | | |
| 30 | 1 | L60030C-1PQ | Pressure Plate/ Q. C. Terminal | #10 CU |
| | 2 | L60030C-2PQ | | |
| | 3 | L60030C-3PQ | | |
| 30 | 1 | L60030C-1SQ | Screw/ Q. C. Terminal | #10 CU |
| | 2 | L60030C-2SQ | | |
| | 3 | L60030C-3SQ | | |

Class CD 60A Fuse Blocks

| Amp Rating | No. of Poles | Catalog Number | Connector Type (Add Suffix Shown) | Maximum Wire Size |
|------------|--------------|----------------|-----------------------------------|-------------------|
| 60 | 1 | L60060C-1C | Box Lug | #6 CU |
| | 2 | L60060C-2C | | |
| | 3 | L60060C-3C | | |
| 60 | Adder Block | L60060C-AC | Box Lug | #6 CU |

Note: Quick Connect Terminals are rated at 20 amperes.

Midget Fuse Blocks

| Amp Rating | No. of Poles | Catalog Number | Connector Type (Add Suffix Shown) | Maximum Wire Size |
|------------|--------------|----------------|-----------------------------------|-------------------|
| 30 | 1 | L60030M-1C | Box Lug | #6 CU |
| | 2 | L60030M-2C | | |
| | 3 | L60030M-3C | | |
| 30 | 1 | L60030M-1PQ | Pressure Plate/ Q. C. Terminal | #10 CU |
| | 2 | L60030M-2PQ | | |
| | 3 | L60030M-3PQ | | |
| 30 | 1 | L60030M-1SQ | Screw/ Q. C. Terminal | #10 CU |
| | 2 | L60030M-2SQ | | |
| | 3 | L60030M-3SQ | | |

Note: Quick Connect Terminals are rated at 20 amperes.



Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: org@lifeelectronics.ru