

CAT5261

Dual Digitally Programmable Potentiometers (DPP[™]) with 256 Taps and SPI Interface



FEATURES

- Two linear-taper digitally programmable potentiometers
- 256 resistor taps per potentiometer
- End to end resistance 50 kΩ or 100 kΩ
- Potentiometer control and memory access via SPI interface
- Low wiper resistance, typically 100 Ω
- Nonvolatile memory storage for up to four wiper settings for each potentiometer
- Automatic recall of saved wiper settings at power up
- 2.5 to 6.0 volt operation
- Standby current less than 1µA
- 1,000,000 nonvolatile WRITE cycles
- 100 year nonvolatile memory data retention
- 24-lead SOIC and 24-lead TSSOP
- Industrial temperature range
- Industrial temperature range

For Ordering Information details, see page 14.

PIN CONFIGURATION

SOIC/TSSOP (W, Y)

SO	1		24	HOLD
A0	2		23	SCK
NC	3		22	NC
NC	4		21	NC
NC	5	•• •	20	NC
NC	6	CAI 5261	19	NC
V_{CC}	7		18	GND
R_{L0}	8		17	R _{W1}
R_{H0}	9		16	R_{H1}
R _{w0}	10		15	R_{L1}
CS	11		14	A1
WP	12		13	SI

DESCRIPTION

The CAT5261 is two Digitally Programmable Potentiometers (DPPs[™]) integrated with control logic and 8 bytes of NVRAM memory. Each DPP consists of a series of resistive elements connected between two externally accessible end points. The tap points between each resistive element are connected to the wiper outputs with CMOS switches. A separate 8-bit control register (WCR) independently controls the wiper tap switches for each DPP. Associated with each wiper control register are four 8-bit non-volatile memory data registers (DR) used for storing up to four wiper settings. Writing to the wiper control register or any of the nonvolatile data registers is via a SPI serial bus. On powerup, the contents of the first data register (DR0) for each of the potentiometers is automatically loaded into its respective wiper control register.

The CAT5261 can be used as a potentiometer or as a two terminal, variable resistor. It is intended for circuit level or system level adjustments in a wide variety of applications. It is available in the -40°C to 85°C industrial operating temperature range and offered in a 24-lead SOIC and TSSOP package.

FUNCTIONAL DIAGRAM



PIN DESCRIPTIONS

SI: Serial Input

SI is the serial data input pin. This pin is used to input all opcodes, byte addresses and data to be written to the CAT5261. Input data is latched on the rising edge of the serial clock.

SO: Serial Output

SO is the serial data output pin. This pin is used to transfer data out of the CAT5261. During a read cycle, data is shifted out on the falling edge of the serial clock.

SCK: Serial Clock

SCK is the serial clock pin. This pin is used to synchronize the communication between the microcontroller and the CAT5261. Opcodes, byte addresses or data present on the SI pin are latched on the rising edge of the SCK. Data on the SO pin is updated on the falling edge of the SCK.

A0, A1: Device Address Inputs

These inputs set the device address when addressing multiple devices. A total of four devices can be addressed on a single bus. A match in the slave address must be made with the address input in order to initiate communication with the CAT5261.

R_H, R_L: Resistor End Points

The $R_{\rm H}$ and $R_{\rm L}$ pins are equivalent to the terminal connections on a mechanical potentiometer.

R_w: Wiper

The RW pins are equivalent to the wiper terminal of a mechanical potentiometer.

CS: Chip Select

CS is the Chip select pin. CS low enables the CAT5261 and CS high disables the

$(10 \text{ OAT}_{2} \text{OT})$ and (00 High) disables the
CAT5261. CS high takes the SO output pin to high impedance and forces the devices into a Standby mode
(unless an internal write operation is underway). The CAT5261 draws ZERO current in the Standby mode. A high
to low transition on CS is required prior to any sequence being initiated. A low to high transition on CS after a
valid write sequence is what initiates an internal write cycle.

WP: Write Protect

WP is the Write Protect pin. The Write Protect pin will allow normal read/write operations when held high. When WP is tied low, all non-volatile write operations to the Data registers are inhibited (change of wiper control register is allowed). WP going low while CS is still low will interrupt a write to the registers. If the internal write cycle has already been initiated, WP going low will have no effect on any write operation.

HOLD: Hold

The $\overline{\text{HOLD}}$ pin is used to pause transmission to the CAT5261 <u>while</u> in the middle of a serial sequence without having to retransmit entire sequence at a later time. To pause, HOLD must be brought low while SCK is low. The SO pin is in a high impedance state <u>during</u> the time the part is paused, and tr<u>ansitions</u> on the SI pins will be ignored. To resume communication, <u>HOLD</u> is brought high, while SCK is low. (HOLD should be held high any time this function is not being used.) HOLD may be tied high directly to V_{CC} or tied to V_{CC} through a resistor.

WP: Write Protect Input

The $\overline{\text{WP}}$ pin when tied low prevents non-volatile writes to the device (change of wiper control register is allowed) and when tied high or left floating normal read/write operations are allowed. See Write Protection on page 6 for more details.

Pin #	Name	Function
1	SO	Serial Data Output
2	A0	Device Address, LSB
3	NC	No Connect
4	NC	No Connect
5	NC	No Connect
6	NC	No Connect
7	V_{CC}	Supply Voltage
8	R_{L0}	Low Reference Terminal for Potentiometer 0
9	R _{H0}	High Reference Terminal for Potentiometer 0
10	R_{W0}	Wiper Terminal for Potentiometer 0
11	CS	Chip Select
12	WP	Write Protection
13	SI	Serial Input
14	A1	Device Address
15	R_{L1}	Low Reference Terminal for Potentiometer 1
16	R _{H1}	High Reference Terminal for Potentiometer 1
17	R_{W1}	Wiper Terminal for Potentiometer 1
18	GND	Ground
19	NC	No Connect
20	NC	No Connect
21	NC	No Connect
22	NC	No Connect
23	SCK	Bus Serial Clock
24	HOLD	Hold

SERIAL BUS PROTOCOL

The CAT5261 supports the SPI bus data transmission protocol. The synchronous Serial Peripheral Interface (SPI) helps the CAT5261 to interface directly with many of today's popular microcontrollers. The

DEVICE OPERATION

The CAT5261 is two resistor arrays integrated with an SPI serial interface logic, two 8-bit wiper control registers and eight 8-bit, non-volatile memory data registers. Each resistor array contains 255 separate resistive elements connected in series. The physical ends of each array are equivalent to the fixed terminals of a mechanical potentiometer (R_H and R_L). RH and RL are symmetrical and may be interchanged. The tap positions between and at the ends of the series resistors are connected to the output wiper terminals (R_W) by a After the device is selected with \overline{CS} going low the first byte will be received. The part is accessed via the SI pin, with data being clocked in on the rising edge of SCK. The first byte contains one

CAT5261 contains an 8-bit instruction register .The instruction set and the operation codes are detailed in the instruction set table 3 on page 9.

of the six op-codes that define the operation to be performed.

CMOS transistor switch. Only one tap point for each potentiometer is connected to its wiper terminal at a time and is determined by the value of the wiper control register. Data can be read or written to the wiper control registers or the non-volatile memory data registers via the SPI bus. Additional instructions allows data to be transferred between the wiper control registers and each respective potentiometer's non-volatile data registers. Also, the device can be instructed to operate in an "increment/decrement" mode.

ABSOLUTE MAXIMUM RATINGS⁽¹⁾

Parameters	Ratings	Units
Temperature Under Bias	-55 to +125	°C
Storage Temperature	-65 to +150	°C
Voltage on Any Pin with Respect to Ground ^{(1) (2)}	-2.0 to +V _{CC} + 2.0	V
V _{CC} with Respect to Ground	-0.2 to +7.0	V
Package Power Dissipation Capability ($T_A = 25^{\circ}C$)	1.0	W
Lead Soldering Temperature (10 s)	300	°C
Wiper Current	±6	mA

RECOMMENDED OPERATING CONDITIONS

Parameters	Ratings	Units
V _{CC}	+2.5 to +6.0	V
Industrial Temperature	-40 to +85	°C

POTENTIOMETER CHARACTERISTICS

(Over recommended operating conditions unless otherwise stated.)

		Limits				
Symbol	Parameter	Test Conditions	Min	Тур.	Max	Units
R _{POT}	Potentiometer Resistance (-00)			100		kΩ
R _{POT}	Potentiometer Resistance (-50)			50		kΩ
	Potentiometer Resistance				±20	%
	R _{POT} Matching				1	%
	Power Rating	25°C, each pot			50	mW
I _W	Wiper Current				±3	mA
Rw	Wiper Resistance	I _w = ±3 mA @ V _{CC} = 3 V		200	300	Ω
Rw	Wiper Resistance	I _w = ±3 mA @ V _{CC} = 5 V		100	150	Ω
V _{TERM}	Voltage on any R_H or R_L Pin		0		V_{CC}	V
VN	Noise	(4)				nV√Hz
	Resolution			0.4		%
	Absolute Linearity (5)	Rw(n)(actual)-R(n)(expected) ⁽⁸⁾			±1	LSB ⁽⁷⁾
	Relative Linearity ⁽⁶⁾	Rw(n+1)-[Rw(n)+LSB] ⁽⁸⁾			±0.2	LSB ⁽⁷⁾
TC _{RPOT}	Temperature Coefficient of R _{POT}	(4)		±300		ppm/⁰C
TC _{RATIO}	Ratiometric Temp. Coefficient	(4)			20	ppm/ºC
$C_H/C_L/C_W$	Potentiometer Capacitances	(4)		10/10/25		pF
fc	Frequency Response	$R_{POT} = 50 \ k\Omega^{(4)}$		0.4		MHz

Notes:

(1) Stresses above those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions outside of those listed in the operational sections of this specification is not implied. Exposure to any absolute maximum rating for extended periods may affect device performance and reliability.

(2) The minimum DC input voltage is -0.5 V. During transitions, inputs may undershoot to -2.0 V for periods of less than 20 ns. Maximum DC voltage on output pins is V_{CC} +0.5 V, which may overshoot to V_{CC} +2.0 V for periods of less than 20 ns.

(3) Latch-up protection is provided for stresses up to 100 mA on address and data pins from -1 V to V_{cc} +1 V.

(4) This parameter is tested initially and after a design or process change that affects the parameter.

(5) Absolute linearity is utilized to determine actual wiper voltage versus expected voltage as determined by wiper position when used as a potentiometer.

(6) Relative linearity is utilized to determine the actual change in voltage between two successive tap positions when used as a potentiometer. It is a measure of the error in step size.

(7) LSB = R_{TOT} / 255 or ($R_{H} - R_{L}$) / 255, single pot

(8) n = 0, 1, 2, ..., 255

D.C. OPERATING CHARACTERISTICS

 V_{CC} = +2.5 V to +6.0 V, unless otherwise specified.

Symbol	Parameter	Test Conditions	Min	Max	Units
I _{CC1}	Power Supply Current	f_{SCL} = 400 kHz, SDA = Open V _{CC} = 6 V, Inputs = GNDs		1	mA
	Power Supply Current	f _{SCK} = 400 kHz, SDA Open		5	mA
ICC2	Non-volatile WRITE	V _{CC} = 6 V, Input = GND			
I _{SB}	Standby Current (V_{CC} = 5 V)	V_{IN} = GND or V_{CC} , SDA = Open		1	μA
ILI	Input Leakage Current	V_{IN} = GND to V_{CC}		10	μA
I _{LO}	Output Leakage Current	V_{OUT} = GND to V_{CC}		10	μA
V _{IL}	Input Low Voltage		-1	V _{CC} x 0.3	V
V _{IH}	Input High Voltage		V _{CC} x 0.7	V _{CC} + 1.0	V
V _{OL1}	Output Low Voltage (V _{CC} = 3 V)	I _{OL} = 3 mA		0.4	V
V _{OH1}	Output High Voltage	I _{OH} = -1.6 mA	$V_{CC} - 0.8$		V

PIN CAPACITANCE⁽¹⁾

 T_A = 25°C, f = 1.0 MHz, V_{CC} = 5 V, unless otherwise specified.

Symbol	Test	Conditions	Max	Units
C _{OUT} ⁽¹⁾	Output Capacitance (SO)	V _{OUT} = 0 V	8	pF
C _{IN} ⁽¹⁾	Input Capacitance (CS, SCK, SI, WP, HOLD, A0, A1)	V _{IN} = 0 V	6	pF

A.C. CHARACTERISTICS

Symbol	Parameter	Test Conditions	Min	Max	Units
t _{s∪}	Data Setup Time		50		ns
t _H	Data Hold Time		50		ns
t _{wH}	SCK High Time		125		ns
t _{WL}	SCK Low Time		125		ns
f _{SCK}	Clock Frequency		DC	3	MHz
t _{LZ}	HOLD to Output Low Z			50	ns
$t_{RI}^{(1)}$	Input Rise Time			2	μs
$t_{FI}^{(1)}$	Input Fall Time			2	μs
t _{HD}	HOLD Setup Time	C _L = 50 pF	100		ns
t _{CD}	HOLD Hold Time		100		ns
t _v	Output Valid from Clock Low			200	ns
t _{HO}	Output Hold Time		0		ns
t _{DIS}	Output Disable Time			250	ns
t _{HZ}	HOLD to Output High Z			100	ns
t _{cs}	CS High Time		2		ns
t _{CSS}	CS Setup Time		250		ns
t _{CSH}	CS Hold Time		250		ns

Note:

(1) This parameter is tested initially and after a design or process change that affects the parameter.

CAT5261

POWER UP TIMING ⁽¹⁾⁽²⁾

Symbol	Parameter	Max	Units
t _{PUR}	Power-up to Read Operation	1	ms
t _{PUW}	Power-up to Write Operation	1	ms

WIPER TIMING

Symbol	Parameter	Min	Max	Units
t _{WRPO}	Wiper Response Time After Power Supply Stable	5	10	μs
t _{WRL}	Wiper Response Time After Instruction Issued	5	10	μs

WRITE CYCLE LIMITS

Symbol	Parameter	Max	Units
t _{WR}	Write Cycle Time	5	ms

RELIABILITY CHARACTERISTICS

Symbol	Parameter	Reference Test Method	Min	Max	Units
N _{END} ⁽³⁾	Endurance	MIL-STD-883, Test Method 1033	1,000,000		Cycles/Byte
$T_{DR}^{(3)}$	Data Retention	MIL-STD-883, Test Method 1008	100		Years
V _{ZAP} ⁽³⁾	ESD Susceptibility	MIL-STD-883, Test Method 3015	2000		V
I _{LTH} ⁽³⁾	Latch-Up	JEDEC Standard 17	100		mA

Notes:

(1) This parameter is tested initially and after a design or process change that affects the parameter.

(2) t_{PUR} and t_{PUW} are delays required from the time V_{CC} is stable until the specified operation can be initiated.

(3) This parameter is tested initially and after a design or process change that affects the parameter.



Figure 1. Synchronous Data Timing

Note: Dashed Line = mode (1, 1)

Figure 2. HOLD Timing



INSTRUCTION AND REGISTER DESCRIPTION

DEVICE TYPE / ADDRESS BYTE

The first byte sent to the CAT5261 from the master/ processor is called the Device Address Byte. The most significant four bits of the Device Type address are a device type identifier. These bits for the CAT5261 are fixed at 0101[B] (refer to Table 1).

The two least significant bits in the slave address byte, A1 - A0, are the internal slave address and must match the physical device address which is defined by the state of the A1 - A0 input pins for the CAT5261 to successfully continue the command sequence. Only the device which slave address matches the incoming device address sent by the master executes the instruction. The A1 - A0 inputs can be actively driven by CMOS input signals or tied to V_{CC} or $V_{\text{SS}}.$ The remaining two bits in the device address byte must be set to 0.

INSTRUCTION BYTE

The next byte sent to the CAT5261 contains the instruction and register pointer information. The four most significant bits used provide the instruction opcode I3 - I0. The R1 and R0 bits point to one of the four data registers of each associated potentiometer. The least two significant bits point to one of two Wiper Control Registers. The format is shown in Table 2.

Data Register Selection

Data Register Selected	R1	R0
DR0	0	0
DR1	0	1



Table 2. Instruction Byte Format



WIPER CONTROL AND DATA REGISTERS

Wiper Control Register (WCR)

The CAT5261 contains two 8-bit Wiper Control Registers, one for each potentiometer. The Wiper Control Register output is decoded to select one of 256 switches along its resistor array. The contents of the WCR can be altered in four ways: it may be written by the host via Write Wiper Control Register instruction; it may be written by transferring the contents of one of four associated Data Registers via the XFR Data Register instruction; it can be modified one step at a time by the Increment/decrement instruction (see Instruction section for more details). Finally, it is loaded with the content of its data register zero (DR0) upon power-up.

The Wiper Control Register is a volatile register that loses its contents when the CAT5261 is powereddown. Although the register is automatically loaded with the value in DR0 upon power-up, this may be different from the value present at power-down.

Data Registers (DR)

Each potentiometer has four 8-bit non-volatile Data Registers. These can be read or written directly by the host. Data can also be transferred between any of the four Data Registers and the associated Wiper Control Register. Any data changes in one of the Data Registers is a non-volatile operation and will take a maximum of 5ms. If the application does not require storage of multiple settings for the potentiometer, the Data Registers can be used as standard memory locations for system parameters or user preference data.

Write in Process

The contents of the Data Registers are saved to nonvolatile memory when the CS input goes HIGH after a write sequence is received. The status of the internal write cycle can be monitored by issuing a Read Status command to read the Write in Process (WIP) bit.

INSTRUCTIONS

Five of the ten instructions are three bytes in length. These instructions are:

- Read Wiper Control Register read the current wiper position of the selected potentiometer in the WCR
- Write Wiper Control Register change current wiper position in the WCR of the selected potentiometer
- Read Data Register read the contents of the selected Data Register
- Write Data Register write a new value to the selected Data Register
- Read Status Read the status of the WIP bit which when set to "1" signifies a write cycle is in progress.

Note: 1/0 = data is one or zero

	Inst	ructior	n Set						
Instruction	13	12	1	10	R1	R0	WCR1/P1	WCR0/ P0	Operation
Read Wiper Control Register	1	0	0	1	0	0	1/0	1/0	Read the contents of the Wiper Control Register pointed to by P1-P0
Write Wiper Control Register	1	0	1	0	0	0	1/0	1/0	Write new value to the Wiper Control Register pointed to by P1-P0
Read Data Register	1	0	1	1	1/0	1/0	1/0	1/0	Read the contents of the Data Register pointed to by P1-P0 and R1-R0
Write Data Register	1	1	0	0	1/0	1/0	1/0	1/0	Write new value to the Data Register pointed to by P1-P0 and R1-R0
XFR Data Register to Wiper Control Register	1	1	0	1	1/0	1/0	1/0	1/0	Transfer the contents of the Data Register pointed to by P1-P0 and R1- R0 to its associated Wiper Control Register
XFR Wiper Control Register to Data Register	1	1	1	0	1/0	1/0	1/0	1/0	Transfer the contents of the Wiper Control Register pointed to by P1-P0 to the Data Register pointed to by R1-R0
Global XFR Data Registers to Wiper Control Registers	0	0	0	1	1/0	1/0	0	0	Transfer the contents of the Data Registers pointed to by R1-R0 of all four pots to their respective Wiper Control Registers
Global XFR Wiper Control Registers to Data Register	1	0	0	0	1/0	1/0	0	0	Transfer the contents of both Wiper Control Registers to their respective data Registers pointed to by R1-R0 of all four pots
Increment/Decrement Wiper Control Register	0	0	1	0	0	0	1/0	1/0	Enable Increment/decrement of the Control Latch pointed to by P1-P0
Read Status (WIP bit)	0	1	0	1	0	0	0	1	Read WIP bit to check internal write cycle status

Table 3. Instruction Set

The basic sequence of the three byte instructions is illustrated in Figure 8. These three-byte instructions exchange data between the WCR and one of the Data Registers. The WCR controls the position of the wiper. The response of the wiper to this action will be delayed by t_{WRL} . A transfer from the WCR (current wiper position), to a Data Register is a write to non-volatile memory and takes a minimum of t_{WR} to complete. The transfer can occur between one of the potentiometers and one of its associated registers; or the transfer can occur between both potentiometers and one associated register.

Four instructions require a two-byte sequence to complete, as illustrated in Figure 7. These instructions transfer data between the host/processor and the CAT5261; either between the host and one of the data registers or directly between the host and the Wiper Control Register. These instructions are:

- XFR Data Register to Wiper Control Register
 This transfers the contents of one specified Data
 Register to the associated Wiper Control Register.
- XFR Wiper Control Register to Data Register This transfers the contents of the specified Wiper Control Register to the specified associated Data Register.

 Global XFR Data Register to Wiper Control Register
 This transfers the contents of all specified Data

Registers to the associated Wiper Control Registers.

 Global XFR Wiper Counter Register to Data Register

This transfers the contents of all Wiper Control Registers to the specified associated Data Registers.

INCREMENT/DECREMENT COMMAND

The final command is Increment/Decrement (Figure 9 and 10). The Increment/Decrement command is different from the other commands. Once the command is issued the master can clock the selected wiper up and/ or down in one segment steps; thereby providing a fine tuning capability to the host. For each SCK clock pulse (t_{HIGH}) while SI is HIGH, the selected wiper will move one resistor segment towards the R_H terminal. Similarly, for each SCK clock pulse while SI is LOW, the selected wiper will move one resistor segment towards the R_L terminal.

See Instructions format for more detail.







INSTRUCTION FORMAT

Read Wiper Control Register (WCR)

	l	DE\	/ICI	ΕA	DDF	RES	SES	S			INS	TR	υст	101	1					DA	TA				
CS	0	1	0	1	0	0	A 1	A 0	1	0	0	1	0	0	P 1	P 0	7	6	5	4	3	2	1	0	CS

Write Wiper Control Register (WCR)

		DE	VIC	ΕA		RE	SSE	S			INS	TRI	JCT	ION						DA	ΤА				
CS	0	1	0	1	0	0	A 1	A 0	1	0	1	0	0	0	P 1	P 0	7	6	5	4	3	2	1	0	CS

Read Data Register (DR)

		D	EVI	CE	AD	DRE	SSE	S			IN	ST	RUC	TIO	Ν					DA	ΔTA	1			
CS	0	1	0	1	0	0	A 1	A 0	1	0	1	1	R 1	R 0	P 1	P 0	7	6	5	4	3	2	1	0	CS

Write Data Register (DR)

	D	θEV	ICE		DDF	RES	SE	S		I	NS	TRI	JCI	IOI	N					DA	TA					
CS	0	1	0	1	0	0	A 1	A 0	1	1	0	0	R 1	R 0	P 1	P 0	7	6	5	4	3	2	1	0	CS	High Voltage Write Cycle

Read Status (WIP)

		DE	VIC	E/	٩DE	DRE	SSE	ES			INS	TRI	JCT	ION						DA	TA	FA 3 2 1 W 0 0 0 I							
CS	0	1	0	1	0	0	A 1	A 0	0	1	0	1	0	0	0	1	7 0	6 0	5 0	4 0	3 0	2 0	1 0	W I B	CS				

Global Transfer Data Register (DR) to Wiper Control Register (WCR)

		DE	VIC	Ε	٩DD	RE	SSE	S			INS	TR	UC.	TIO	Ν		
CS	0	1	0	1	0	0	A 1	A 0	0	0	0	1	R 1	R 0	0	0	CS

Global Transfer Wiper Control Register (WCR) to Data Register (DR)

ſ		D	E\	/IC	ΕA	DD	RE	SSE	S		I	NS	TR	UC.	TIO	Ν			
	CS	0	1	0	1	0	0	A 1	A 0	1	0	0	0	R 1	R O	0	0	CS	High Voltage Write Cycle

Transfer Wiper Control Register (WCR) to Data Register (DR)

	D	E\	/IC	E A	٩DD	RE	SSE	ES		I	NS	TR	UC	τιο	N			
cs	0	1	0	1	0	0	A 1	A 0	1	1	1	0	R 1	R 0	P 1	P 0	CS	High Voltage Write Cycle

Transfer Data Register (DR) to Wiper Control Register (WCR)

		DE	VIC	ΕA	٩DD	RES	SSE	S			INS	TR	UC.	TIO	Ν		
cs	0	1	0	1	0	0	A 1	A 0	1	1	0	1	R 1	R 0	P 1	P 0	cs

Increment (I)/Decrement (D) Wiper Control Register (WCR)

	DEVICE ADDRESSES						INSTRUCTION					DATA										
CS	0	1	0	1	0	0	A 1	A 0	0	0	1	0	0	0	P 1	P 0	I/D	I/D		I/D	I/D	CS

Notes:

(1) Any write or transfer to the Non-volatile Data Registers is followed by a high voltage cycle after a STOP has been issued.

PACKAGE OUTLINE DRAWINGS

SOIC 24-Lead 300 mils (W)



SYMBOL	MIN	NOM	МАХ
А	2.35		2.65
A1	0.10		0.30
A2	2.05		2.55
b	0.31		0.51
С	0.20		0.33
D	15.20		15.40
Е	10.11		10.51
E1	7.34		7.60
е		1.27 BSC	
h	0.25		0.75
L	0.40		1.27
θ	0°		8°
θ1	5°		15°

TOP VIEW



SIDE VIEW



END VIEW

Notes:

- (1) All dimensions in millimeters. Angles in degrees.
- (2) Complies with JEDEC specification MS-013.

TSSOP 24-Lead 4.4 mm (Y)



SYMBOL	MIN	NOM	MAX			
Α			1.20			
A1	0.05		0.15			
A2	0.80		1.05			
b	0.19		0.30			
С	0.09		0.20			
D	7.70	7.80	7.90			
E	6.25	6.40	6.55			
E1	4.30	4.40	4.50			
е	0.65 BSC					
L	1.00 REF					
L1	0.50	0.60	0.70			
θ1	0°		8°			



SIDE VIEW

TOP VIEW



Notes:

- (1) All dimensions in millimeters. Angles in degrees.
- (2) Complies with JEDEC specification MO-153.

EXAMPLE OF ORDERING INFORMATION



ORDERING INFORMATION

Orderable Part Number	Resistance (kΩ)	Package	Lead Finish	
CAT5261WI-50-T1	50	SOIC		
CAT5261WI-00-T1	100	3010		
CAT5261YI-50-T2	50	TEEOD		
CAT5261YI-00-T2	100	13305	Matta Tin	
CAT5261WI50	50	SOIC	Malle-TIT	
CAT5261WI00	100	3010		
CAT5261YI50	50	TSSOD		
CAT5261YI00	100	1330F		

Notes:

(1) All packages are RoHS-compliant (Lead-free, Halogen-free).

(2) The device used in the above example is a CAT526159WI-00-T1 (SOIC, Industrial Temperature, 100 k Ω , Tape & Reel).

REVISION HISTORY

Date	Rev.	Description
18-Nov-03	Α	Initial Issue
04-Apr-04	В	Updated wiper resistance from 50Ω to 100Ω Updated Functional Diagram Updated WP Pin Description Updated notes in Absolute Max Ratings Eliminated Commercial temp range in all areas Updated Potentiometer Characteristics table Updated DC Characteristics table Updated Pin Capacitance table Updated AC Characteristics table Added Wiper Timing Table on page 6 Corrected Synchronous Data Timing (Figure 1) drawing
21-Sep-04	С	Updated Figure 8 (Three Byte Instruction Sequence)
31-Jul-07	D	Updated Example of Ordering Information Update Package Outline Drawings Added MD- to document number
07-Feb-08	E	Update Instruction Format – Read Data Register (DR) and Write Data Register (DR)
24-Nov-08	F	Change logo and fine print to ON Semiconductor
05-Aug-09	G	Update Ordering Information table

ON Semiconductor and are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications proves or use SCILLC products for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer or use SCILL products like for any other application application application purpose, cube jointended or used thering application where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application. Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized to subscription and the soft of the part. SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION LITERATURE FULFILL

LITERATURE FULFILLMENT:				
Literature Distribution Center for ON Semiconductor P.O. Box 5163, Denver, Colorado 80217 USA	N. American Technical Support: 800-282-9855 Toll Free USA/Canada	ON Semiconductor Website: www.onsemi.com		
Phone: 303-675-2175 or 800-344-3860 Toll Free USA/Canada	Europe, Middle East and Africa Technical Support: Phone: 421 33 790 2910	Order Literature: http://www.onsemi.com/orderlit		
Email: orderlit@onsemi.com	Japan Customer Focus Center: Phone: 81-3-5773-3850	For additional information, please contact your local Sales Representative		



ООО "ЛайфЭлектроникс"

ИНН 7805602321 КПП 780501001 Р/С 40702810122510004610 ФАКБ "АБСОЛЮТ БАНК" (ЗАО) в г.Санкт-Петербурге К/С 3010181090000000703 БИК 044030703

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный) Email: org@lifeelectronics.ru

www.lifeelectronics.ru