

Datamate Connectors

Female Crimp

- ❖ Part numbers are for housings and the equivalent number of contacts.
- ❖ Contacts are rear insertable.
- ❖ For British Standard versions see pages 14 to 15.
- ❖ Hoods & cable assembly service available – contact datamate@harwin.com.
- ❖ Spare contacts are available – see page 16.



SINGLE ROW		CALCULATION		DOUBLE ROW		CALCULATION																			
		A	$B + 5.15$			A	$B + 5.15$																		
		B	$(\text{Total No. of contacts} - 1) \times 2$			B	$\text{Total No. of contacts} - 2$																		
TOOLS				WIRE STRIPPING DETAILS																					
<p>Recommended Crimp Tool – M22520/2-01 Positioner – T5747 Contact Insertion/Removal Tool – Z80-280 See pages 77 to 79 ❖ Instruction sheets available at www.harwin.com/downloads/instructions</p>																									
HOW TO ORDER																									
SERIES CODE		M80 - XXX XX XX		FINISH																					
TYPE				<table border="1"> <tr> <td>01</td> <td>Gold + Tin</td> <td></td> </tr> <tr> <td>05</td> <td>Gold</td> <td></td> </tr> </table>				01	Gold + Tin		05	Gold													
01	Gold + Tin																								
05	Gold																								
<table border="1"> <tr> <td>788</td> <td>Extra Small Bore, Double Row</td> <td>889</td> <td>Large Bore, Double Row</td> </tr> <tr> <td>798</td> <td>Extra Small Bore, Single Row</td> <td>898</td> <td>Small Bore, Single Row</td> </tr> <tr> <td>888</td> <td>Small Bore, Double Row</td> <td>899</td> <td>Large Bore, Single Row</td> </tr> </table>		788	Extra Small Bore, Double Row	889	Large Bore, Double Row	798	Extra Small Bore, Single Row	898	Small Bore, Single Row	888	Small Bore, Double Row	899	Large Bore, Single Row			<table border="1"> <tr> <th colspan="2">TOTAL NO. OF CONTACTS</th> </tr> <tr> <td>Single Row</td> <td>02 to 07, 17</td> </tr> <tr> <td>Double Row</td> <td>04, 06, 08, 10, 12, 14, 16, 18, 20, 26, 34</td> </tr> </table>				TOTAL NO. OF CONTACTS		Single Row	02 to 07, 17	Double Row	04, 06, 08, 10, 12, 14, 16, 18, 20, 26, 34
788	Extra Small Bore, Double Row	889	Large Bore, Double Row																						
798	Extra Small Bore, Single Row	898	Small Bore, Single Row																						
888	Small Bore, Double Row	899	Large Bore, Single Row																						
TOTAL NO. OF CONTACTS																									
Single Row	02 to 07, 17																								
Double Row	04, 06, 08, 10, 12, 14, 16, 18, 20, 26, 34																								

All dimensions in mm.

www.harwin.com



Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)
Email: org@lifeelectronics.ru