FS6S1565RB

Fairchild Power Switch(FPS)

Features

- Wide operating frequency range up to 150Khz
- Internal Burst mode Controller for Stand-by mode
- Pulse by pulse over current limiting
- Over current protection(Auto restart mode)
- Over voltage protection (Auto restart mode)
- Over load protection(Auto restart mode)
- Internal thermal shutdown function(Auto restart mode)
- Under voltage lockout
- Internal high voltage sense FET
- Eternal sync terminal/Soft start

Description


The Fairchild Power Switch(FPS) product family is specially designed for an off-line SMPS with minimal external components. The Fairchild Power Switch(FPS) consist of high voltage power SenseFET and current mode PWM IC. Included PWM controller features integrated fixed oscillator, under voltage lock out, optimized gate turn-on/turn-off driver, thermal shut down protection, over voltage protection, and temperature compensated precision current sources for loop compensation and fault protection circuitry. compared to discrete MOSFET and controller or R_{CC} switching converter solution, a Fairchild Power Switch(FPS) can reduce total component count, design size, and weight and at the same time increase efficiency, productivity, and system reliability. It has a basic platform well suited for cost effective monitor power supply.

TO-3P-5L



1

Internal Block Diagram



Rev.1.0.1

©2001 Fairchild Semiconductor Corporation

Absolute Maximum Ratings

(Ta=25°C, unless otherwise specified)

Parameter	Symbol	Value	Unit
Drain-source(GND) voltage (1)	V_{DSS}	650	V
Drain-Gate Voltage (R_{GS}=1MΩ)	V_{DGR}	650	V
Gate-source (GND) Voltage	V_{GS}	±30	V
Drain current pulsed (2)	I_{DM}	60	A_{DC}
Single pulsed avalanche energy (3)	E_{AS}	1040	mJ
Single Pulsed Avalanche current (4)	I_{AS}	37	A
Continuous drain current (Tc = 25°C)	I_D	15	A_{DC}
Continuous drain current (T_C=100°C)	I_D	9.5	A_{DC}
Supply voltage	V_{CC}	35	V
Input Voltage Range	V_{FB}	–0.3 to V_{CC}	V
	V_{S_S}	–0.3 to 10	V
Total Power Dissipation	P_D(Watt H/S)	270	W
	Derating	2.17	W/°C
Operating junction temperature	T_j	+160	°C
Operating Ambient Temperature	T_A	–25 to +85	°C
Storage Temperature range	T_{STG}	–55 to +150	°C

Notes:

1. Tj=25°C to 150°C
2. Repetitive rating: Pulse width limited by maximum junction temperature
3. L=8.5mH, starting Tj=25°C
4. L=13uH, starting Tj=25°C

Electrical Characteristics (SFET part)

(Ta=25°C unless otherwise specified)

Parameter	Symbol	Condition	Min.	Typ.	Max.	Unit
Drain-source breakdown voltage	BV_{DSS}	V_{GS} = 0V, I_D = 250μA	650	-	-	V
Zero gate voltage drain current	I_{DSS}	V_{DS} = 650V, V_{GS} = 0V	-	-	200	μA
		V_{DS} = 520V V_{GS} = 0V, T_C = 125°C	-	-	300	μA
Static drain-source on resistance (note)	$R_{DS(ON)}$	V_{GS} = 10V, I_D = 7.5A	-	0.5	0.65	Ω
Forward transconductance (note)	gfs	V_{DS} = 50V, I_D = 7.5A	-	-	-	S
Input capacitance	Ciss	V_{GS} = 0V, V_{DS} = 25V, f = 1MHz	-	2580	-	pF
Output capacitance	Coss		-	270	-	
Reverse transfer capacitance	Crss		-	50	-	
Turn on delay time	$t_{d(on)}$	V_{DD} = 325V, I_D = 15A (MOSFET switching time are essentially independent of operating temperature)	-	50	-	nS
Rise time	tr		-	155	-	
Turn off delay time	$t_{d(off)}$		-	270	-	
Fall time	tf		-	125	-	
Total gate charge (gate-source+gate-drain)	Qg	V_{GS} = 10V, I_D = 15A, V_{DS} = 520V (MOSFET Switching time are Essentially independent of Operating temperature)	-	90	-	nC
Gate source charge	Qgs		-	15	-	
Gate drain (Miller) charge	Qgd		-	45	-	
Single Pulsed Avalanche current (1)	I_{AS}	V_{CC} = V_{FB} = V_{SS} = GND	-	37	-	A

Note:

Pulse test : Pulse width ≤ 300μS, duty 2%

$S = \frac{1}{R}$

1. L=13uH, starting Tj=25°C

Electrical Characteristics

(Ta=25°C unless otherwise specified)

Parameter	Symbol	Condition	Min.	Typ.	Max.	Unit
UVLO SECTION						
Start threshold voltage	V_{START}	V_{FB} = GND	14	15	16	V
Stop threshold voltage	V_{STOP}	V_{FB} = GND	8	9	10	V
SENSEFET SECTION						
Drain to PKG Breakdown voltage	BVpkg	60HZ AC, Ta = 25°C	3500	-	-	V
Drain to Source Breakdown voltage	BVdss	Vdrain = 650V, Ta = 25°C	650	-	-	V
Drain to Source Leakage current	Idss	Vdrain = 650V, Ta = 25°C	-	-	300	uA
OSCILLATOR SECTION						
Initial Frequency	F_{OSC}	-	22	25	28	kHz
Voltage Stability	F_{STABLE}	12V ≤ Vcc ≤ 23V	0	1	3	%
Temperature Stability (note4)	ΔF_{OSC}	-25°C ≤ Ta ≤ 85°C	0	±5	±10	%
Maximum duty cycle	D_{MAX}	-	92	95	98	%
Minimum Duty Cycle	D_{MIN}	-	-	-	0	%
FEEDBACK SECTION						
Feedback source current	I_{FB}	V_{FB} = GND	0.7	0.9	1.1	mA
Shutdown Feedback voltage	V_{SD}	Vfb ≥ 6.9V	6.9	7.5	8.1	V
Shutdown delay current	Idelay	V_{FB} = 5V	1.6	2.0	2.4	µA
PROTECTION SECTION						
Over Voltage Protection	V_{OVP}	Vsync ≥ 11V	27	30	33	V
Over Current Latch Voltage (Note2)	V_{OCL}	-	0.9	1.0	1.1	V
Thermal Shutdown Temp.(Note4)	T_{SD}	-	140	160	-	°C

Electrical Characteristics (Continued)

(Ta=25°C unless otherwise specified)

Parameter	Symbol	Condition	Min.	Typ.	Max.	Unit
Sync & SOFTSTART SECTION						
Softstart Vortage	V_{SS}	Vfb = 2	4.7	5.0	5.3	V
Softstart Current	I_{SS}	Vss = V	0.8	1.0	1.2	mA
Sync High Threshold Voltage	V_{SYNCH}	Vcc = 16V, Vfb = 5V	-	7.2	-	V
Sync Low Threshold Voltage	V_{SYNCL}	Vcc = 16V, Vfb = 5V	-	5.8	-	V
BURST MODE SECTION						
Burst mode Low Threshold Voltage	V_{BURL}	Vfb = 0V	10.4	11.0	11.6	V
Burst mode High Threshold Voltage	V_{BURH}	Vfb = 0V	11.4	12.0	12.6	V
Burst mode Enable Feedback Voltage (Note4)	V_{BEN}	Vcc = 10.5V	0.7	1.0	1.3	V
Burst mode Peak Current Limit (Note3)	I_{BU_PK}	Vcc = 10.5V	0.6	0.85	1.1	V
Burst mode Frequency	F_{BUR}	Vcc = 10.5V, Vfb = 0V	40	50	60	KHz
CURRENT LIMIT(SELF-PROTECTION)SECTION						
Peak Current Limit (Note3)	I_{OVER}	-	8.5	9.7	10.9	A
TOTAL DEVICE SECTION						
Start Up current	I_{START}	Vfb = GND, V_{CC} = 14V	-	0.1	0.17	mA
Operating supply current (Note1)	I_{OP}	Vfb = GND, V_{CC} = 16V	-	10	15	mA
	$I_{OP(MIN)}$	Vfb = GND, V_{CC} = 10V				
	$I_{OP(MAX)}$	Vfb = GND, V_{CC} = 28V				

Notes:

(1) These parameters is the current flowing in the Control IC.

(2) These parameters, although guaranteed, are tested in EDS(wafer test) process.

(3) These parameters indicate Inductor Current.

(4) These parameters, although guranteed at the design, are not tested in massing production.

Typical Performance Characteristics




Figure 1. Start Up Current vs. Temp




Figure 2. Operating Current vs. Temp




Figure 3. Start Threshold Voltage vs. Temp




Figure 4. Stop Threshold Voltage vs. Temp




Figure 5. Initial Freqency vs. Temp




Figure 6. Maximum Duty vs. Temp

Typical Performance Characteristics (Continued)




Figure 7. Feedback Offset Voltage vs. Temp




Figure 8. Feedback Source Current vs. Temp




Figure 9. ShutDown Delay Current vs. Temp




Figure 10. ShutDown Feedback Voltage vs. Temp




Figure 11. Softstart Voltage vs. Temp




Figure 12. OverVoltage Protection vs. Temp

Typical Performance Characteristics (Continued)




Figure 13. Burst Mode Low Voltage vs. Temp




Figure 14. Burst Mode High Voltage vs. Temp




Figure 15. Burst Mode Freqency vs. Temp




Figure 16. Burst ModeEnable Voltage vs. Temp




Figure 17. Softstart Voltage vs. Temp




Figure 18. OverVoltage Protection vs. Temp

Typical Performance Characteristics (Continued)




Figure 19. Burst Mode Low Voltage vs. Temp




Figure 20. Burst Mode High Voltage vs. Temp




Figure 21. Burst Mode Freqency vs. Temp




Figure 22. Burst ModeEnable Voltage vs. Temp




Figure 23. Burst Mode Peak Current vs. Temp





Figure 24. Over Current Limit vs. Temp


Package Dimensions

TO-3P-5L



Package Dimensions

TO-3P-5L (Forming)



Ordering Information

Product Number	Package	Marking Code	BVdss	Rds(on)
FS6S1565RB-TU	TO-3P-5L	6S1565RB	650V	0.5
FS6S1565RB-YDTU	TO-3P-5L(Forming)			

TU : Non Forming Type
YDTU : Forming Type

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
2. A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

© 2001 Fairchild Semiconductor Corporation

LifeElectronics
Живое партнерство

ООО «ЛайфЭлектроникс» **“LifeElectronics” LLC**

ИНН 7805602321 КПП 780501001 Р/С 40702810122510004610 ФАКБ "АБСОЛЮТ БАНК" (ЗАО) в г.Санкт-Петербурге К/С 30101810900000000703 БИК 044030703

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- *Конкурентоспособные цены и скидки постоянным клиентам.*
- *Специальные условия для постоянных клиентов.*
- *Подбор аналогов.*
- *Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.*

- *Приемлемые сроки поставки, возможна ускоренная поставка.*
- *Доставку товара в любую точку России и стран СНГ.*
- *Комплексную поставку.*
- *Работу по проектам и поставку образцов.*
- *Формирование склада под заказчика.*

- *Сертификаты соответствия на поставляемую продукцию (по желанию клиента).*
- *Тестирование поставляемой продукции.*
- *Поставку компонентов, требующих военную и космическую приемку.*
- *Входной контроль качества.*
- *Наличие сертификата ISO.*

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- *Регистрацию проекта у производителя компонентов.*
- *Техническую поддержку проекта.*
- *Защиту от снятия компонента с производства.*
- *Оценку стоимости проекта по компонентам.*
- *Изготовление тестовой платы монтаж и пусконаладочные работы.*

Тел: +7 (812) 336 43 04 (многоканальный)
Email: org@lifeelectronics.ru

www.lifeelectronics.ru