

# 958

## Low-Solids No-Clean Liquid Flux

### Product Description

Kester 958 is a no-clean, non-corrosive, liquid flux that is specifically designed for the wave soldering of conventional and surface mount circuit board assemblies. Kester 958 was developed to give excellent soldering performance on bare copper printed circuit boards treated with OSP coatings. Essentially, no residue remains after soldering. Boards are dry and cosmetically clean as they exit the wave solder machine, thus posing no interference with electrical testing. Kester 958 has excellent compatibility with most conformal coating products on the market today. This comprehensive formulation possesses improved wetting characteristics and also exhibits superior corrosion inhibiting properties and provides a non-tacky residue. A major advantage of this flux is the reduced odor associated with the soldering process.

#### Performance Characteristics:

- Excellent for bare copper circuit board technology
- Compatible with conformal coat processes
- Improves soldering performance
- Reduced odor associated with soldering process
- Eliminates the need and expense of cleaning
- Non-corrosive tack-free residues
- Classified as ORL0 per J-STD-004
- Compliant to Bellcore GR-78

### Physical Properties

**Specific Gravity:**  $0.806 \pm 0.005$

Antoine Paar DMA 35 @ 25°C

**Percent Solids (typical):** 2.7

Tested to J-STD-004, IPC-TM-650, Method 2.3.34

**Acid Number:**  $23.2 \pm 1.0$  mg KOH/g of flux

Tested to J-STD-004, IPC-TM-650, Method 2.3.13

**pH (10% solution):** 3.1

Hanna Instruments 8314 @ 25°C

**Flash Point:** 18°C (64°F)

### Reliability Properties

**Copper Mirror Corrosion:** Low

Tested to J-STD-004, IPC-TM-650, Method 2.3.32

**Corrosion Test:** Low

Tested to J-STD-004, IPC-TM-650, Method 2.6.15

**Silver Chromate:** Pass

Tested to J-STD-004, IPC-TM-650, Method 2.3.33

**Chloride and Bromides:** None Detected

Tested to J-STD-004, IPC-TM-650, Method 2.3.35

**Fluorides by Spot Test:** Pass

Tested to J-STD-004, IPC-TM-650, Method 2.3.35.1

**SIR, IPC (typical):** Pass

Tested to J-STD-004, IPC-TM-650, Method 2.6.3.3

	<b>Blank</b>	<b>958 PD</b>	<b>958 PU</b>
Day 1	$5.0 \times 10^9 \Omega$	$3.1 \times 10^9 \Omega$	$5.2 \times 10^9 \Omega$
Day 4	$5.8 \times 10^9 \Omega$	$4.9 \times 10^9 \Omega$	$6.8 \times 10^9 \Omega$
Day 7	$6.3 \times 10^9 \Omega$	$5.5 \times 10^9 \Omega$	$7.2 \times 10^9 \Omega$

## Application Notes

### Flux Application:

Kester 958 can be applied to circuit boards by a spray, foam or dip process. Flux deposition should be 120-240  $\mu\text{g}$  of solids/ $\text{cm}^2$  (750-1500  $\mu\text{g}$  of solids/ $\text{in}^2$ ). An air knife after the flux tank is recommended to remove excess flux from the circuit board and prevent dripping on the preheater surface.

### Process Considerations:

The optimum preheat temperature for most circuit assemblies is 90-105°C (194-221°F) as measured on the top or component side of the printed circuit board. Dwell time in the wave is typically 2-4 seconds. The wave soldering speed should be adjusted to accomplish proper preheating and evaporate excess solvent, which could cause spattering. For best results, speeds of 1.1-1.8 m/min (3½-6 ft/min) are used. The surface tension has been adjusted to help the flux form a thin film on the board surface allowing rapid solvent evaporation.

### Flux Control:

Acid number is normally the most reliable method to control the flux concentration of low solids, no clean fluxes. To check concentration, a simple acid-base titration should be used. PS-20 Test Kit and procedure are available from Kester. Control of the flux in the foam flux tank during use is necessary for assurance of consistent flux distribution on the circuit boards. The complex nature of the solvent system for the flux makes it imperative that Kester 4662 Thinner be used to replace evaporative losses. When excessive debris from circuit boards, such as board fibers and from the air line build up in the flux tank, these particulates will redeposit on the circuit boards which may create a build up of residues on probe test pins. It is, therefore, necessary to clean the tank and then replenish it with fresh flux when excessive debris accumulates in the flux tank.

### Cleaning:

Kester 958 flux residues are non-conductive, non-corrosive and do not require removal in most applications.

### Storage and Shelf Life:

Kester 958 is flammable. Store away from sources of ignition. Shelf life is 3 years from date of manufacture when handled properly and held at 10-25°C (50-77°F).

### Health & Safety:

This product, during handling or use, may be hazardous to health or the environment. Read the Material Safety Data Sheet and warning label before using this product.

---

**World Headquarters:** 800 West Thorndale Avenue, Itasca, Illinois, 60143 USA  
**Phone:** (+1) 630-616-4000 • **Email:** customerservice@kester.com • **Website:** www.kester.com

**Asia Pacific Headquarters**  
 500 Chai Chee Lane  
 Singapore 469024  
 (+65) 6449-1133  
 customerservice@kester.com.sg

**European Headquarters**  
 Zum Plom 5  
 08541 Neuensalz  
 Germany  
 (+49) 3741 4233-0  
 customerservice@kester-eu.com

**Japanese Headquarters**  
 20-11 Yokokawau 2-Chome  
 Sumida-Ku  
 Tokyo 130-0003 Japan  
 (+81) 3-3624-5351  
 jpsales@kester.com.sg

---

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: [org@lifeelectronics.ru](mailto:org@lifeelectronics.ru)

[www.lifeelectronics.ru](http://www.lifeelectronics.ru)