

Fluke 789 ProcessMeter™

Technical Data

Double your power.

The Fluke 787 ProcessMeter was the first tool to combine a loop calibrator with a DMM to give process technicians double the power in one tool. Now it's even better – the ultimate loop calibration multimeter – the Fluke 789 ProcessMeter.

The 789 has a display that's not only twice as large, but also twice as bright with two levels of backlighting. And with its built-in, selectable 250 ohm HART® resistor, it eliminates the need to carry a separate resistor with you.

Now process technicians can do a lot more while carrying a lot less.



Key new features of the Fluke 789

- 24 V Loop power supply
- HART mode setting with loop power (adds 250 ohm resistor)
- 100 % larger dual display
- 1200 ohm drive capability on mA source
- Enhanced backlight with two brightness settings
- 0-100 % mA *Span Check* buttons to toggle between 4 and 20 mA
- Infrared I/O serial port compatible with FlukeView® Forms Software Version 2.1 (available Feb. 2003)
- Externally accessible fuses for easy replacement

These 787 features are also included in the 789

- DMM designed to meet 1000 volt IEC 1010 CAT III standards
- Precision 1000 V, 440 mA True-rms digital multimeter
- Frequency measurement to 20 kHz
- Min/Max/Average/Hold/Relative modes
- Diode Test and Continuity Beeper
- Simultaneous mA and % of scale readout
- 20 mA dc current source / loop calibrator / simulator
- Manual Step (100 %, 25 %, Coarse, Fine) plus Auto Step and Auto Ramp
- Externally accessible battery for easy battery changes



Measurement Function	Range and Resolution	Best Accuracy (% of reading + LSD)
V dc	400.0 mV, 4.000 V, 40.00 V, 400.0 V, 1000 V	0.1 % + 1
V ac (true-rms)	400.0 mV, 4.000 V, 40.00 V, 400.0 V, 1000 V	0.7 % + 2
mA dc	30.000 mA	.05 % + 2
A dc	1.000 A (0.440 A continuous)	0.2 % + 2
A ac	1.000 A (0.440 A continuous)	1 % + 2
Resistance	400.0 Ohms, 4.000 k, 40.00 k, 400.0 k, 4.0 M, 40 M	0.2 % + 1
Frequency (0.5 Hz to 20 kHz)	199.99 Hz, 1999.9 Hz, 19.999 kHz	.005 % + 1
Diode Test	2.000 V (shows diode voltage drop)	2 % + 1
Continuity	Beeps for resistance < approx. 100 ohms	

Output Function	Range and Resolution	Drive Capability	Accuracy (% of span)
DC Current Output (Internal battery operation)	0.000 to 20.000 mA or 4.000 to 20.000 mA (selectable at power-up) Over-range to 24.000 mA	24 V compliance, or, 1,200 Ohms, @ 20 mA	.05 %
DC Current Simulate (Ext. 24 Volt loop supply)	0.000 to 20.000 mA or 4.000 to 20.000 mA, (selectable at power-up) Over-range to 24.000 mA	1000 Ohms, @ 20 mA	.05 %
24 V Loop Supply	Minimum 24 V	250 Ohms @ 20 mA	> 24 V
Current Adjustment Modes	Manual: Coarse, Fine, 25 % and 100 % step Automatic: Slow Ramp, Fast Ramp, 25 % step		

Temperature range of 18 °C to 28 °C, for one year after calibration

General specifications

Maximum voltage applied between any jack and earth ground: 1000 V RMS

Storage temperature: -40 °C to 60 °C

Operating temperature: -20 °C to 55 °C

Temperature coefficient: 0.05 x (specified accuracy) per °C (for temperatures < 18 °C or > 28 °C)

Relative humidity: 95 % up to 30 °C; 75 % up to 40 °C; 45 % up to 50 °C; 35 % up to 55 °C

Vibration: Random, 2 g, 5-500 Hz

Shock: 1 meter drop test

Safety: Designed in accordance with ENG1010, ANSI/ISA S82.01-1994 and CAN/CSA C22.2 No. 1010.1-92 Over-voltage Category III

Size: 50 mm H x 100 mm W x 203 mm L (1.97 in H x 3.94 in W x 8.00 in L)

Weight: 600 g (1.3 lbs)

Battery: Four AA alkaline batteries

Battery life: 140 hours typical (measurement), 10 hours typical (sourcing 12 mA)

Warranty: 3 years

Optional accessories

80T-IR Infrared Temperature Probe

80TK Thermocouple Module

80T-150U Universal Temperature Probe

TL20 / TL22 / TL24 / TL26 / TL28 /

TL40A Test Lead Sets

AC20 / AC80 Clips

TP20 Industrial Test Probes

80i-400 AC Current Clamp*

i-410 AC/DC Current Clamp**

i-1010 AC/DC Current Clamp**

C25 / C100 Cases

80K-6 and 80K-40 High Voltage Probes

85RF High Frequency Probes

PV350 Pressure Vacuum Module

Fiber Optic Meter FOM

LPAK80-4 LockPak

TPAK ToolPak Meter Hanging Kit

*Above 50 A ac

**Above 1 A dc or 20 A ac

Ordering information

Model

Fluke-789 ProcessMeter Including:
TL71 Premium Test Lead Set plus AC72 Alligator Clips, Four AA alkaline batteries (installed), Users Manual and Quick Reference Guide

Fluke. Keeping your world up and running.

Fluke Corporation

PO Box 9090, Everett, WA USA 98206

Fluke Europe B.V.
PO Box 1186, 5602 BD Eindhoven, The Netherlands

For more information call:
In the U.S.A. (800) 443-5853 or Fax (425) 446-5116
In Europe/M-East/Africa (31 40) 2 675 200 or Fax (31 40) 2 675 222
In Canada (800) 36-FLUKE or Fax (905) 890-6866
From other countries +1 (425) 446-5500 or Fax +1 (425) 446-5116
Web access: <http://www.fluke.com/>

©2002 Fluke Corporation. All rights reserved. All copyrights are the property of their respective owners. Printed in U.S.A. 10/2002 1999242 D-ENG-N Rev C

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)
Email: org@lifeelectronics.ru