

A DIVISION OF MINNEAPOLIS-HONEYWELL REGULATOR COMPANY
FREEPORT, ILLINOIS
FED. MFR. CODE 91929

BRACKET -
SHEET METAL

CATALOG LISTING
17 MA1 - B

17MA1-B

 Σ DRAWING
NUMBER

2	3
---	---

ENSS

REPLACES

SR 10124

RELEASE NO.

F

111

1

CHECK

1

6

✓

6.3

1

76

工

CHECK

CH

12

3. A

7

10.



1

4

1

5

i

1

1

1

1

L

Technical drawing of a mechanical part, likely a valve or actuator, showing dimensions and a section line A-A. The drawing includes the following dimensions and features:

- Overall length: $2.625 \pm .030$
- Section line A-A: Indicated by a horizontal line with arrows at both ends, labeled 'A'.
- Internal feature: A circular feature with a diameter dimension of $.142 \begin{smallmatrix} +.005 \\ -.003 \end{smallmatrix}$.
- Other dimensions: $.34$, $.69$, and $.75$.
- Internal structure: A dashed line indicates a hidden internal feature, possibly a valve stem or actuator mechanism.

Technical drawing of a basic switch assembly. The drawing shows a side view of the assembly with various dimensions and material specifications.

- Dimensions:**
 - Top thickness: $.455 \pm .045$
 - Operating position height: OPERATING POSITION
 - Bottom thickness: $.050$
- Material:** CADIUM PLATED COLD ROLLED STEEL
- Assembly:** DOTTED LINES INDICATE BASIC SWITCH IN PLACE

NOTE —

- 1 - GIVEN CHARACTERISTICS ARE FOR BZ-2R-A2 BASIC SWITCH
- 2 - THE BRACKET IS FOR USE WITH MICRO SWITCH TYPE "A" OR TYPE "Z" BASIC SWITCHES
- 3 - THE BRACKET MAY BE MOUNTED BY TWO NO. 6 SCREWS ON A SURFACE WITH TWO HOLES,
CENTERLINES AT $2.375 \pm .016$ DISTANCE
- 4 - IN ASSEMBLING THE BASIC SWITCH ON THE BRACKET, PLACE THE BRACKET ON A FLAT SURFACE
AND PRESS THE BASIC SWITCH ONTO THE PRONGS OF THE BRACKET
- 5 - "A" DIMENSION IS $.900 \pm .050$ FOR TYPE Z BASIC AND, $1.060 \pm .050$ FOR TYPE A BASIC
- 6 - BASIC SWITCH MAY BE MOUNTED FROM EITHER SIDE

THIS DRAWING COVERS A PROPRIETARY ITEM AND IS THE PROPERTY OF MICRO SWITCH, A DIVISION OF MINNEAPOLIS-HONEYWELL REGULATOR CO. THIS DRAWING IS NOT TO BE COPIED OR USED WITHOUT THE APPROVAL OF MICRO SWITCH.

CHARACTERISTICS		ELECTRICAL DATA		SCALE FULL
		CONTACT ARRANGEMENT	BREAK DISTANCE	DO NOT SCALE PRINT
				UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES TOLERANCES ARE:
				ONE PLACE (.0) ±.030 TWO PLACE (.00) ±.015 THREE PLACE (.000) ±.001 ANGLES ±
				WEIGHT

FO-50378-003

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: org@lifeelectronics.ru

www.lifeelectronics.ru