

PXI/DAQ/DAQe-2200 Series

64-CH 12/16-Bit Up to 3 MS/s Multi-Function DAQ Cards



Introduction

ADLINK's PXI/DAQ/DAQe-2200 series are high-density and high-performance multi-function DAQ cards. These devices can sample up to 64 AI channels with different gain settings and scan sequences, making them ideal for dealing with high-density analog signals with various input ranges and sampling speeds. These devices also offer differential mode for 32 AI channels in order to achieve maximum noise elimination.

The PXI/DAQ/DAQe-2200 series also feature analog and digital triggering, 2-CH 12-bit analog outputs with waveform generation capability, 24-CH programmable digital I/O lines, and 2-CH 16-bit general-purpose timer/counter. Like all the other members in the PXI/DAQ/DAQe-2200 family, the PXI/DAQ/DAQe-2200 is able to perform the analog input and output functions at full speed simultaneously and multiple cards can be synchronized through the SSI (System Synchronization Interface) bus. The auto-calibration functions adjust the gain and offset to within specified accuracies such that you do not have to adjust trimpots to calibrate the cards.

Features

- Supports a 32-bit 3.3 V or 5 V PCI bus (DAQ-2200 series)
- x1 lane PCI Express® Interface (DAQe-2200 series)
- PXI specification Rev 2.2 compliant (PXI-2200 series)
- 64-CH single-ended or 32-CH differential analog inputs
- Onboard 1 k-sample A/D FIFO
- Bipolar or unipolar analog input ranges
- Programmable gains:
 - x1, x2, x4, x5, x8, x10, x20, x40, x50, x200 (DAQ/DAQe-2204)
 - x1, x2, x4, x8 (DAQ/DAQe-2205 & DAQ/DAQe-2206)
- 512-configuration channel gain queue
- Scatter-gather DMA for both analog inputs and outputs
- 2-CH 12-bit multiplying analog outputs with waveform generation
- Onboard 1 k-sample D/A FIFO
- 24-CH TTL digital input/output
- 2-CH 16-bit general-purpose timer/counter
- Analog and digital triggering
- Fully auto calibration
- Multiple cards synchronization through SSI (System Synchronization Interface) bus or PXI trigger bus
- Operating Systems
 - Windows 7/Vista/XP/2000/2003 Server
 - Linux

Recommended Software

- AD-Logger
- VB.NET/VC.NET/VB/VC++/BCB/Delphi
- DAQBench

Driver Support

- DAQPilot for LabVIEW™
- DAQ-MTLB for MATLAB®
- D2K-DASK for Windows
- D2K-DASK/X for Linux

Terminal Boards & Cables

DIN-68S-01

Terminal Board with One 68-pin SCSI-II Connector and DIN-Rail Mounting (Cables are not included.)

ACL-10568-I

68-pin SCSI-VHDCI cable (mating with AMP-787082-7), 1 M

* For more information on mating cables, please refer to P2-61/62.

SSI Bus Cables (for multiple cards synchronization)

- ACL-SSI-2
SSI Bus cable for 2 devices
- ACL-SSI-3
SSI Bus cable for 3 devices
- ACL-SSI-4
SSI Bus cable for 4 devices



SSI bus cable for multiple card synchronization for DAQ/DAQe-2000 series



Terminal board DIN-68S-01 & 68-Pin SCSI-VHDCI cable ACL-10568-I

Pin Assignment Connector CN1 Pin Assignment

AI0 (AIH0)	1	35	(AIL0) AI32
AI1 (AIH1)	2	36	(AIL1) AI33
AI2 (AIH2)	3	37	(AIL2) AI34
AI3 (AIH3)	4	38	(AIL3) AI35
AI4 (AIH4)	5	39	(AIL4) AI36
AI5 (AIH5)	6	40	(AIL5) AI37
AI6 (AIH6)	7	41	(AIL6) AI38
AI7 (AIH7)	8	42	(AIL7) AI39
AI8 (AIH8)	9	43	(AIL8) AI40
AI9 (AIH9)	10	44	(AIL9) AI41
AI10 (AIH10)	11	45	(AIL10) AI42
AI11 (AIH11)	12	46	(AIL11) AI43
AI12 (AIH12)	13	47	(AIL12) AI44
AI13 (AIH13)	14	48	(AIL13) AI45
AI14 (AIH14)	15	49	(AIL14) AI46
AI15 (AIH15)	16	50	(AIL15) AI47
AI16 (AIH16)	17	51	AI48
AI17 (AIH17)	18	52	(AIL16) AI48
AI18 (AIH18)	19	53	(AIL17) AI49
AI19 (AIH19)	20	54	(AIL18) AI50
AI20 (AIH20)	21	55	(AIL19) AI51
AI21 (AIH21)	22	56	(AIL20) AI52
AI22 (AIH22)	23	57	(AIL21) AI53
AI23 (AIH23)	24	58	(AIL22) AI54
AI24 (AIH24)	25	59	(AIL23) AI55
AI25 (AIH25)	26	60	(AIL24) AI56
AI26 (AIH26)	27	61	(AIL25) AI57
AI27 (AIH27)	28	62	(AIL26) AI58
AI28 (AIH28)	29	63	(AIL27) AI59
AI29 (AIH29)	30	64	(AIL28) AI60
AI30 (AIH30)	31	65	(AIL29) AI61
AI31 (AIH31)	32	66	(AIL30) AI62
EXTATRIG	33	67	(AIL31) AI63
	34	68	AI64

Pin Assignment Connector CN2 Pin Assignment

DA0OUT	1	35	AOGND
DA1OUT	2	36	AOGND
AOEXTREF	3	37	AOGND
N/C	4	38	N/C
DGND	5	39	DGND
EXTWTRIG	6	40	DGND
EXTDTRIG	7	41	DGND
SSHOUT	8	42	SDI0 / DGND*
RESERVED	9	43	SDI1 / DGND*
RESERVED	10	44	SDI2 / DGND*
AF1	11	45	SDI3 / DGND*
AF10	12	46	DGND
GPTC0_SRC	13	47	DGND
GPTC0_GATE	14	48	DGND
GPTC0_UPDOWN	15	49	DGND
GPTC0_OUT	16	50	DGND
GPTC1_SRC	17	51	DGND
GPTC1_GATE	18	52	DGND
GPTC1_UPDOWN	19	53	DGND
GPTC1_OUT	20	54	DGND
EXTTIMEBASE	21	55	DGND
PB7	22	56	PB6
PB5	23	57	PB4
PB3	24	58	PB2
PB1	25	59	PB0
PC7	26	60	PC6
PC5	27	61	PC4
DGND	28	62	DGND
PC3	29	63	PC2
PC1	30	64	PC0
PA7	31	65	PA6
PA5	32	66	PA4
PA3	33	67	PA2
PA1	34	68	PA0

*Pin 42-45 are SDI<0..3> for 2204; DGND for 2205 and 2206

Ordering Information / Quick Selection Guide

Model Name	Analog Input				Analog Output			DIO	Timer/Counter
	No. of channels	Resolution	Sampling rate	Input range	No. of channels	Resolution	Update rate	No. of channels	No. of channels
PXI/DAQ/DAQe-2204	32 DI/64 SE	12 bits	3 MS/s	± 0.05 V to ± 10 V	2	12 bits	1 MS/s	24-CH 8255 PIO	2-CH, 16-bit
PXI/DAQ/DAQe-2205	32 DI/64 SE	16 bits	500 kS/s	± 1.25 V to ± 10 V	2	12 bits	1 MS/s	24-CH 8255 PIO	2-CH, 16-bit
PXI/DAQ/DAQe-2206	32 DI/64 SE	16 bits	250 kS/s	± 1.25 V to ± 10 V	2	12 bits	1 MS/s	24-CH 8255 PIO	2-CH, 16-bit

Specifications

Model Name	PXI/DAQ/DAQe-2204		PXI/DAQ/DAQe-2205	PXI/DAQ/DAQe-2206
Analog Input				
Resolution	12 bits, no missing codes		16 bits, no missing codes	16 bits, no missing codes
Number of channels	64 single-ended or 32 differential (software selectable per channel)			
Channel gain queue size	512			
Maximum sampling rate	3 MS/s	500 kS/s	250 kS/s	
Programmable gain	1, 2, 4, 5, 8, 10, 20, 40, 50, 200	1, 2, 4, 8	1, 2, 4, 8	
Bipolar input ranges	Max. : ±10 V, Min. : ±0.05 V±10 V, ±5 V, ±2.5 V, ±1.25 V±10 V, ±5 V, ±2.5 V, ±1.25 V			
Unipolar input ranges	Max. : 0-10 V, Min. : 0-0.1 V0-10 V, 0-5 V, 0-2.5 V, 0-1.25 V0-10 V, 0-5 V, 0-2.5 V, 0-1.25 V			
Offset error	±2 mV	±1 mV	±2 mV	
Gain error	±0.06% of FSR	±0.08% of FSR	±0.06% of FSR	
Input coupling	DC			
Overvoltage protection	Power on: Continuous ±30 V, Power off: Continuous ±15 V			
Input impedance	1 GΩ/100 pF			
CMRR (gain = 1)	90 dB	83 dB	83 dB	
Settling time	1 μs to 0.1% error *	2 μs to 0.1% error	4 μs to 0.01% error	
-3 dB small signal bandwidth (@Bipolar +/-10V Gain=1)	2 MHz	850kHz	600 kHz	
Trigger sources	Software, external digital/analog trigger, SSI bus			
Trigger modes	Pre-trigger, post-trigger, middle-trigger, delay-trigger, and repeated trigger			
FIFO buffer size	1 k samples			
Data transfers	Polling, scatter-gather DMA			
Analog Output				
Number of channels	2 voltage outputs			
Resolution	12 bits			
Output ranges	0-10 V, ±10 V, 0-AOEXTREF, ±AOEXTREF			
Maximum update rate	1 μs			
Slew rate	20 V/μs			
Settling time	3 μs to ±0.5 LSB accuracy			
Offset error	±1 mV	±2 mV	±1 mV	
Gain error	±0.02% of max. output	±0.04% of max. output	±0.02% of max. output	
Driving capacity	±5 mA			
Stability	Any passive load, up to 1500 pF			
Trigger sources	Software, external digital/analog trigger, SSI bus			
Trigger modes	Post-trigger, delay-trigger, and repeated trigger			
FIFO buffer size	1 k samples			
Data transfers	Programmed I/O, scatter-gather DMA			
Digital I/O				
Number of channels	24-CH 8255 programmable input/output			
Compatibility	5 V/TTL			
Data transfers	Programmed I/O			
General-Purpose Timer/Counter				
Number of channels	2			
Resolution	16-bit			
Base clock available	40 MHz, external clock up to 10 MHz			
Auto Calibration				
Onboard reference	+5 V			
Temperature drift	±2 ppm/°C			
Stability	±6 ppm/1000 Hrs			
General Specifications				
Dimensions	160 mm x 100 mm (not including connectors) (PXI-2200 series) 175 mm x 107 mm (not including connectors) (DAQ-2200 series) 168 mm x 107 mm (not including connectors) (DAQe-2200 series)			
Connector	68-pin VHDCI female x 2			
Operating temperature	0 to 55°C			
Storage temperature	-20 to 70°C			
Humidity	5 to 95%, non-condensing			
Power requirements	+5 V 1.3 A typical (PXI/DAQ-2204) +3.3 V 0.9 A, +12 V 0.564 A typical (DAQe-2204)	+5 V 1.2 A typical (PXI/DAQ-2205) +3.3 V 0.81 A, +12 V 0.568 A typical (DAQe-2205)	+5 V 1.2 A typical (PXI/DAQ-2206) +3.3 V 0.756 A, +12 V 0.584 A typical (DAQe-2206)	

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: org@lifeelectronics.ru

www.lifeelectronics.ru