

1.5V Drive Nch+Pch MOSFET

US6M11

●Structure

Silicon N-channel MOSFET /
Silicon P-channel MOSFET

●Features

- 1) Nch MOSFET and Pch MOSFET are put in TUMT6 package.
- 2) Low on-resistance.
- 3) Low voltage drive (1.5V drive).
- 4) Built-in G-S Protection Diode.


●Applications

Switching


●Packaging specifications

| Type | Package | Taping |
|--------|------------------------------|--------|
| | Code | TR |
| | Basic ordering unit (pieces) | 3000 |
| US6M11 | | ○ |

●Dimensions (Unit : mm)



●Inner circuit



●Absolute maximum ratings (Ta=25°C)

| Parameter | Symbol | Limits | | Unit | |
|------------------------------|-------------------|--------------------|----------------|-------------|---|
| | | Tr1 : Nchannel | Tr2 : Pchannel | | |
| Drain-source voltage | V _{DSS} | 20 | -12 | V | |
| Gate-source voltage | V _{GSS} | ±10 | ±10 | V | |
| Drain current | Continuous | I _D | ±1.5 | ±1.3 | A |
| | Pulsed | I _{DP} *1 | ±6 | ±5.2 | A |
| Source current (Body diode) | Continuous | I _S | 0.5 | -0.5 | A |
| | Pulsed | I _{SP} *1 | 6 | -5.2 | A |
| Power dissipation | P _D *2 | 1.0 | | W / TOTAL | |
| | | 0.7 | | W / ELEMENT | |
| Channel temperature | T _{ch} | 150 | | °C | |
| Range of storage temperature | T _{stg} | -55 to +150 | | °C | |

*1 P_w≤10μs, Duty cycle≤1%

*2 Mounted on a ceramic board.

●Thermal resistance

| Parameter | Symbol | Limits | Unit |
|--------------------|--------------------------------------|--------|----------------|
| Channel to ambient | R _{th(ch-a)} * ² | 125 | °C/W / TOTAL |
| | | 179 | °C/W / ELEMENT |

* Mounted on a ceramic board

<N-ch>

●Electrical characteristics (Ta=25°C)

| Parameter | Symbol | Min. | Typ. | Max. | Unit | Conditions |
|---|----------------------|------|------|------|------|---|
| Gate-source leakage | I _{GSS} | – | – | ±10 | μA | V _{GS} = ±10V, V _{DS} =0V |
| Drain-source breakdown voltage | V _{(BR)DSS} | 20 | – | – | V | I _D = 1mA, V _{GS} =0V |
| Zero gate voltage drain current | I _{DSS} | – | – | 1 | μA | V _{DS} = 20V, V _{GS} =0V |
| Gate threshold voltage | V _{GS(th)} | 0.3 | – | 1.0 | V | V _{DS} = 10V, I _D = 1mA |
| Static drain-source on-state resistance | R _{DS(on)*} | – | 130 | 180 | mΩ | I _D = 1.5A, V _{GS} = 4.5V |
| | | – | 170 | 240 | mΩ | I _D = 1.5A, V _{GS} = 2.5V |
| | | – | 220 | 310 | mΩ | I _D = 0.8A, V _{GS} = 1.8V |
| | | – | 300 | 600 | mΩ | I _D = 0.3A, V _{GS} = 1.5V |
| Forward transfer admittance | Y _{fs} * | 1.6 | – | – | S | V _{DS} = 10V, I _D = 1.5A |
| Input capacitance | C _{iss} | – | 110 | – | pF | V _{DS} = 10V |
| Output capacitance | C _{oss} | – | 18 | – | pF | V _{GS} =0V |
| Reverse transfer capacitance | C _{rss} | – | 15 | – | pF | f=1MHz |
| Turn-on delay time | t _{d(on)*} | – | 5 | – | ns | V _{DD} ≐ 10V |
| Rise time | t _r * | – | 5 | – | ns | I _D = 1A |
| Turn-off delay time | t _{d(off)*} | – | 20 | – | ns | V _{GS} = 4.5V |
| Fall time | t _f * | – | 3 | – | ns | R _L ≐ 10Ω |
| Total gate charge | Q _g * | – | 1.8 | – | nC | V _{DD} ≐ 10V, V _{GS} = 4.5V |
| Gate-source charge | Q _{gs} * | – | 0.3 | – | nC | I _D = 1.5A |
| Gate-drain charge | Q _{gd} * | – | 0.3 | – | nC | R _L ≐ 6.7Ω, R _G = 10Ω |

*Pulsed

●Body diode characteristics (Source-drain) (Ta=25°C)

| Parameter | Symbol | Min. | Typ. | Max. | Unit | Conditions |
|-----------------|-------------------|------|------|------|------|--|
| Forward voltage | V _{SD} * | – | – | 1.2 | V | I _S = 1.5A, V _{GS} =0V |

*Pulsed

<P-ch>

●Electrical characteristics (Ta=25°C)

| Parameter | Symbol | Min. | Typ. | Max. | Unit | Conditions |
|---|----------------------|------|------|------|------|---|
| Gate-source leakage | I _{GSS} | – | – | ±10 | μA | V _{GS} = ±10V, V _{DS} =0V |
| Drain-source breakdown voltage | V _{(BR)DSS} | –12 | – | – | V | I _D = –1mA, V _{GS} =0V |
| Zero gate voltage drain current | I _{DSS} | – | – | –1 | μA | V _{DS} = –12V, V _{GS} =0V |
| Gate threshold voltage | V _{GS(th)} | –0.3 | – | –1.0 | V | V _{DS} = –6V, I _D = –1mA |
| Static drain-source on-state resistance | R _{DS(on)*} | – | 190 | 260 | mΩ | I _D = –1.3A, V _{GS} = –4.5V |
| | | – | 280 | 390 | mΩ | I _D = –0.6A, V _{GS} = –2.5V |
| | | – | 400 | 600 | mΩ | I _D = –0.6A, V _{GS} = –1.8V |
| | | – | 530 | 1060 | mΩ | I _D = –0.2A, V _{GS} = –1.5V |
| Forward transfer admittance | Y _{fs} * | 1.4 | – | – | S | V _{DS} = –6V, I _D = –1.3A |
| Input capacitance | C _{iss} | – | 290 | – | pF | V _{DS} = –6V |
| Output capacitance | C _{oss} | – | 28 | – | pF | V _{GS} = 0V |
| Reverse transfer capacitance | C _{rss} | – | 21 | – | pF | f=1MHz |
| Turn-on delay time | t _{d(on)*} | – | 8 | – | ns | V _{DD} ≐ –6V |
| Rise time | t _r * | – | 10 | – | ns | I _D = –0.6A |
| Turn-off delay time | t _{d(off)*} | – | 30 | – | ns | V _{GS} = –4.5V |
| Fall time | t _f * | – | 9 | – | ns | R _L ≐ 10Ω |
| Total gate charge | Q _g * | – | 2.4 | – | nC | V _{DD} ≐ –6V, V _{GS} = –4.5V |
| Gate-source charge | Q _{gs} * | – | 0.6 | – | nC | I _D = –1.3A |
| Gate-drain charge | Q _{gd} * | – | 0.4 | – | nC | R _L ≐ 4.6Ω, R _G = 10Ω |

*Pulsed

●Body diode characteristics (Source-drain) (Ta=25°C)

| Parameter | Symbol | Min. | Typ. | Max. | Unit | Conditions |
|-----------------|-------------------|------|------|------|------|---|
| Forward voltage | V _{SD} * | – | – | –1.2 | V | I _S = –1.3A, V _{GS} =0V |

*Pulsed

●Electrical characteristic curves

<Nch>




Fig.1 Typical Output Characteristics(I)




Fig.2 Typical Output Characteristics(II)




Fig.3 Typical Transfer Characteristics




Fig.4 Static Drain-Source On-State Resistance vs. Drain Current(I)




Fig.5 Static Drain-Source On-State Resistance vs. Drain Current(II)




Fig.6 Static Drain-Source On-State Resistance vs. Drain Current(III)




Fig.7 Static Drain-Source On-State Resistance vs. Drain Current(IV)




Fig.8 Static Drain-Source On-State Resistance vs. Drain Current(V)




Fig.9 Forward Transfer Admittance vs. Drain Current




Fig.10 Reverse Drain Current vs. Source-Drain Voltage




Fig.11 Static Drain-Source On-State Resistance vs. Gate Source Voltage




Fig.12 Switching Characteristics




Fig.13 Dynamic Input Characteristics




Fig.14 Typical Capacitance vs. Drain-Source Voltage

<Pch>




Fig.1 Typical output characteristics (I)




Fig.2 Typical output characteristics (II)




Fig.3 Typical Transfer Characteristics




Fig.4 Static Drain-Source On-State Resistance vs. Drain Current (I)




Fig.5 Static Drain-Source On-State Resistance vs. Drain Current (II)




Fig.6 Static Drain-Source On-State Resistance vs. Drain Current (III)




Fig.7 Static Drain-Source On-State Resistance vs. Drain Current (IV)




Fig.8 Static Drain-Source On-State Resistance vs. Drain Current (IV)






Fig.9 Forward Transfer Admittance vs. Drain Current




SOURCE-DRAIN VOLTAGE : $-V_{DS}$ [V]

Fig.10 Reverse Drain Current vs. Source-Drain Voltage



GATE-SOURCE VOLTAGE : $-V_{GS}$ [V]

Fig.11 Static Drain-Source On-State Resistance vs. Gate Source Voltage



DRAIN-CURRENT : $-I_D$ [A]

Fig.12 Switching Characteristics




Fig.13 Dynamic Input Characteristics




Fig.14 Typical Capacitance vs. Drain-Source Voltage

●Measurement circuit

<Nch>




Fig.1-1 Switching Time Measurement Circuit




Fig.1-2 Switching Waveforms




Fig.2-1 Gate Charge Measurement Circuit




Fig.2-2 Gate Charge Waveform

<Pch>




Fig.3-1 Switching Time Measurement Circuit




Fig.3-2 Switching Waveforms




Fig.4-1 Gate Charge Measurement Circuit




Fig.4-2 Gate Charge Waveform

●Notice

This product might cause chip aging and breakdown under the large electrified environment. Please consider to design ESD protection circuit.

Notes

No copying or reproduction of this document, in part or in whole, is permitted without the consent of ROHM Co.,Ltd.

The content specified herein is subject to change for improvement without notice.

The content specified herein is for the purpose of introducing ROHM's products (hereinafter "Products"). If you wish to use any such Product, please be sure to refer to the specifications, which can be obtained from ROHM upon request.

Examples of application circuits, circuit constants and any other information contained herein illustrate the standard usage and operations of the Products. The peripheral conditions must be taken into account when designing circuits for mass production.

Great care was taken in ensuring the accuracy of the information specified in this document. However, should you incur any damage arising from any inaccuracy or misprint of such information, ROHM shall bear no responsibility for such damage.

The technical information specified herein is intended only to show the typical functions of and examples of application circuits for the Products. ROHM does not grant you, explicitly or implicitly, any license to use or exercise intellectual property or other rights held by ROHM and other parties. ROHM shall bear no responsibility whatsoever for any dispute arising from the use of such technical information.

The Products specified in this document are intended to be used with general-use electronic equipment or devices (such as audio visual equipment, office-automation equipment, communication devices, electronic appliances and amusement devices).

The Products specified in this document are not designed to be radiation tolerant.

While ROHM always makes efforts to enhance the quality and reliability of its Products, a Product may fail or malfunction for a variety of reasons.

Please be sure to implement in your equipment using the Products safety measures to guard against the possibility of physical injury, fire or any other damage caused in the event of the failure of any Product, such as derating, redundancy, fire control and fail-safe designs. ROHM shall bear no responsibility whatsoever for your use of any Product outside of the prescribed scope or not in accordance with the instruction manual.

The Products are not designed or manufactured to be used with any equipment, device or system which requires an extremely high level of reliability the failure or malfunction of which may result in a direct threat to human life or create a risk of human injury (such as a medical instrument, transportation equipment, aerospace machinery, nuclear-reactor controller, fuel-controller or other safety device). ROHM shall bear no responsibility in any way for use of any of the Products for the above special purposes. If a Product is intended to be used for any such special purpose, please contact a ROHM sales representative before purchasing.

If you intend to export or ship overseas any Product or technology specified herein that may be controlled under the Foreign Exchange and the Foreign Trade Law, you will be required to obtain a license or permit under the Law.



Thank you for your accessing to ROHM product informations.
More detail product informations and catalogs are available, please contact us.

ROHM Customer Support System

<http://www.rohm.com/contact/>

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[ROHM Semiconductor:](#)

[US6M11TR](#)

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)
Email: org@lifeelectronics.ru