

LTM4601AHV

5V_{IN} to 28V_{IN}, 12A Step-Down μModule Regulator

DESCRIPTION

Demonstration circuit 1414B-B features the LTM[®]4601AHVEV, the high efficiency, high density switch mode step-down power module. The input voltage range is 5V to 28V with a jumper selectable output voltage from 0.6V to 5V. The rated load current is 12A, although derating is necessary for certain V_{IN}, V_{OUT} and thermal conditions. The PLLIN pin supports synchronizing the μModule[®] regulator to an external clock. The TRACK/SS pin allows the user to program output ramp-up and ramp-down rates which may coincidentally or ratiometrically

track with another voltage rail. Output voltage margining of ±5% from the nominal value is available via the margin control pins MARG0 and MARG1. The LTM4601AHV data sheet must be read in conjunction with this demo manual prior to working on or modifying demo circuit DC1414B-B.


Design files for this circuit board are available at <http://www.linear.com/demo>

LT, LTC, LTM, μModule, Linear Technology and the Linear logo are registered trademarks of Linear Technology Corporation. All other trademarks are the property of their respective owners.

PERFORMANCE SUMMARY (T_A = 25°C)

PARAMETER	CONDITION	VALUE
Input Voltage Range		5V to 28V
Output Voltage V _{OUT}	Jumper Selectable (Open for 0.6V)	1.2V, 1.5V, 1.8V, 2.5V, 3.3V, 5V
Maximum Continuous Output Current	Derating is Necessary for Certain V _{IN} , V _{OUT} and Thermal Conditions	12A DC
Default Operating Frequency		850kHz
External Synchronous Clock Frequency Range	Please Refer to Data Sheet for Minimum t _{ON} and t _{OFF} Requirement.	600kHz to 1000kHz
Efficiency	V _{IN} = 12V, V _{OUT} = 3.3V, I _{OUT} = 12A	89.5%, See Figure 2

BOARD PHOTO



dc1414b-bf

QUICK START PROCEDURE

Demonstration circuit 1414B-B is easy to set up to evaluate the performance of the LTM4601AHVEV. Please refer to Figure 1 for proper measurement equipment setup and follow the procedure below:

1. Place jumpers in the following positions for a typical $1.5V_{OUT}$ application:

MARG0	MARG1	RUN	V_{OUT} SELECT
LO	LO	ON	1.5V

2. With power off, connect the input power supply, load and meters as shown in Figure 1. Preset the load to 0A and V_{IN} supply to be less than 20V.
3. Turn on the power at the input. The output voltage should be $1.5V \pm 1\%$.
4. Once the proper output voltage is established, adjust the load within the operating range and observe the output voltage regulation, ripple voltage, efficiency and other parameters. Output ripple should be measured at J4 with a BNC cable.

5. For optional load transient test, apply adjustable pulse signal between IOSTEP CLK and GND pins. Pulse amplitude sets the current step. The pulse signal should have very small duty cycle (<15%) to limit the thermal stress on the transient load circuit. The output transient current can be monitored at BNC connector J3 (10mV/A).
6. For Margining function test, place jumper MARG0 and MARG1 in the configurations shown in the following table, measure the output voltage at J4.

MARG1	MARG0	ΔV_{OUT}
LO	LO	0
LO	HI	+5%
HI	LO	-5%
HI	HI	0

QUICK START PROCEDURE




Figure 1. Test Setup of DC1414B-B





Figure 2. Measured Supply Efficiency with Different V_{OUT} ($V_{IN} = 12V$)



$V_{IN} = 12V$
 $V_{OUT} = 1.2V$
2A TO 10A LOAD STEP
 $C_{OUT} = 2 \times 100\mu F, 3.6V, X5R, 1812$ CERAMIC +
 $1 \times 22\mu F, 10V, X5R, 1206$ CERAMIC


Figure 3. Measured Load Transient Response

DEMO MANUAL DC1414B-B

PARTS LIST

ITEM	QTY	REFERENCE	PART DESCRIPTION	MANUFACTURER/PART NUMBER
Required Circuit Components				
1	1	CIN1	Cap., Alum 150µF 35V 20%	SANYO 35ME150WXV+TS (now SUNCON 35ME150WXV)
2	2	CIN2, CIN3	Cap., X7R 10µF 35V 20%	Taiyo Yuden GMK316BJ106ML-T
3	2	COUT1, COUT2	Cap., X5R 100µF 6.3V 20%, 1210/1812	TDK C4532X5R0J107M
4	1	COUT4	Cap., X5R 10µF 10V 10%	Taiyo Yuden LMK316BJ106KL-T
5	1	CSS	Cap., X7R 0.1µF 16V 20%	AVX 0603YC104MAT2A
6	1	D1	Zener Diode, 5.1V	On Semi. MMBZ5231B
7	1	R17	Res., Chip 10k 0.1W 5%	Vishay CRCW060310K0JNEA
8	1	R3	Res., Chip 51k 0.1W 5%	Vishay CRCW060351K0JNEA
9	1	R4	Res., Chip 392k 0.1W 1%	Vishay CRCW0603392KFKEA
10	1	R14	Res., Chip 49.9k 0.1W 1%	Vishay CRCW060349K9FKEA
11	1	R16	Res., Chip 40.2k 0.1W 1%	Vishay CRCW060340K2FKEA
12	1	U1	I.C., Volt. Reg.	Linear Tech. LTM4601AHVEV
Additional Demo Board Circuit Components				
1	0	CIN4, CIN5 (Opt)	Cap., 1206 TBD	
2	0	COUT3 (Opt)	Cap., 1210 TBD	
3	2	C1,C2	Cap., X5R 1µF 10V 10%	Taiyo Yuden LMK107BJ105KA
4	0	C3, C4, C5, C6, C7 (Opt)	Cap., 0603 TBD	
5	1	Q1	MOSFET, N-Channel 30V	Vishay SUD50N03-09P-E3
6	1	R1	Res., Chip 10k 0.1W 5%	Vishay CRCW060310K0JNEA
7	1	R2	Res., LRF, 0.010Ω, 2W, 1%, 2512	IRC LRF2512LF-01-R010-F
8	2	R8, R5	Res., Chip 10Ω 0.1W 5%	Vishay CRCW060310R0JNEA
9	0	R6, R9, R11, R12, R18 (Opt)	Res., 0603 TBD	
10	3	R7, R10, R23	Res/Jumper, Chip 0Ω 1/16W 1 AMP	Vishay CRCW06030000Z0EA
11	1	R15	Res., Chip 60.4k 0.1W 1%	Vishay CRCW060360K4FKEA
12	1	R19	Res., Chip 30.1k 0.1W 1%	Vishay CRCW060330K1FKEA
13	1	R20	Res., Chip 19.1k 0.1W 1%	Vishay CRCW060319K1FKEA
14	1	R21	Res., Chip 13.3k 0.1W 1%	Vishay CRCW060313K3FKEA
15	1	R22	Res., Chip 8.25k 0.1W 1%	Vishay CRCW06038K25FKEA
Hardware-For Demo Board Only				
1	13	E1-E4, E6-E14	Turret, Testpoint	Mill Max 2308-02-00-80-00-00-07-0
2	6	JP1, JP2, JP3, JP4, JP5, JP6	2-Pin 0.079 Single Row Header	SAMTEC TMM102-02-L-S
3	3	JP7, JP8, JP9	3-Pin 0.079 Single Row Header	SAMTEC TMM103-02-L-S
4	4	XJP2, XJP7, XJP8, XJP9	Shunt, 0.079" Center	SAMTEC 2SN-BK-G
5	4	J1, J2, J5, J6	Connector, Banana Jack	Keystone 575-4
6	2	J3, J4	BNC Connector	Connex 112404
7	4		Stand-Off, Nylon, 0.5" Tall	Keystone 8833 (SNAP ON)

SCHEMATIC DIAGRAM



DEMO MANUAL DC1414B-B

DEMONSTRATION BOARD IMPORTANT NOTICE

Linear Technology Corporation (LTC) provides the enclosed product(s) under the following **AS IS** conditions:

This demonstration board (DEMO BOARD) kit being sold or provided by Linear Technology is intended for use for **ENGINEERING DEVELOPMENT OR EVALUATION PURPOSES ONLY** and is not provided by LTC for commercial use. As such, the DEMO BOARD herein may not be complete in terms of required design-, marketing-, and/or manufacturing-related protective considerations, including but not limited to product safety measures typically found in finished commercial goods. As a prototype, this product does not fall within the scope of the European Union directive on electromagnetic compatibility and therefore may or may not meet the technical requirements of the directive, or other regulations.

If this evaluation kit does not meet the specifications recited in the DEMO BOARD manual the kit may be returned within 30 days from the date of delivery for a full refund. **THE FOREGOING WARRANTY IS THE EXCLUSIVE WARRANTY MADE BY THE SELLER TO BUYER AND IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED, IMPLIED, OR STATUTORY, INCLUDING ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR ANY PARTICULAR PURPOSE. EXCEPT TO THE EXTENT OF THIS INDEMNITY, NEITHER PARTY SHALL BE LIABLE TO THE OTHER FOR ANY INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES.**

The user assumes all responsibility and liability for proper and safe handling of the goods. Further, the user releases LTC from all claims arising from the handling or use of the goods. Due to the open construction of the product, it is the user's responsibility to take any and all appropriate precautions with regard to electrostatic discharge. Also be aware that the products herein may not be regulatory compliant or agency certified (FCC, UL, CE, etc.).

No License is granted under any patent right or other intellectual property whatsoever. **LTC assumes no liability for applications assistance, customer product design, software performance, or infringement of patents or any other intellectual property rights of any kind.**

LTC currently services a variety of customers for products around the world, and therefore this transaction **is not exclusive**.

Please read the DEMO BOARD manual prior to handling the product. Persons handling this product must have electronics training and observe good laboratory practice standards. **Common sense is encouraged.**

This notice contains important safety information about temperatures and voltages. For further safety concerns, please contact a LTC application engineer.

Mailing Address:

Linear Technology
1630 McCarthy Blvd.
Milpitas, CA 95035

Copyright © 2004, Linear Technology Corporation

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкуренеспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: org@lifeelectronics.ru