







SCHEMATIC
THREE PHASE WYE
FUSE RECOMMENDED BUT
NOT SUPPLIED.

SCHEMATIC
SINGLE PHASE PARALLEL
FUSE RECOMMENDED BUT
NOT SUPPLIED.

++ LINE TO LINE VOLTAGE.
** REQUIRES THREE 51LAC PARALLELING CHOKES (NOT SUPPLIED).
π IF GANGED UNITS ARE USED IN A SYSTEM THAT ORDINARILY HAS A COMMON NEUTRAL OR GROUND BETWEEN SOURCE AND LOAD, THE NEUTRAL OR GROUND MUST BE CONNECTED TO THE COMMON TERMINALS OF THE VARIABLE TRANSFORMER ASSEMBLY. IF THE SYSTEM HAS NO NEUTRAL, THE LOAD MUST BE BALANCED OR THE TRANSFORMER WILL BE DAMAGED.
■ JUMPER PROVIDED IN STANDARD COMMON POSITION AND SHOULD BE REMOVED OR REMOVED AS REQUIRED.

SPECIFICATIONS												
WIRING	INPUT		OUTPUT				SHAFT ROTATION TO INCREASE VOLTAGE	TERMINAL CONNECTIONS				
	VOLTS	HERTZ	VOLTS	CONSTANT CURRENT LOAD		CONSTANT IMPEDANCE LOAD		FOR INCREASING VOLTAGE AS VIEWED FROM BASE END ■				
				MAX. AMPS	MAX. KVA	MAX. AMPS		MAX. KVA	INPUT	JUMPER	OUTPUT	
SINGLE PHASE PARALLEL **	120	50/60	0-120	75	9.00	90	10.8	CW	2-2-2, 4-4-4	4-D		
			0-140	75	10.50	—	—	CCW	2-2-2, 4-4-4	2-D		
								CW	1-1-1, 4-4-4	4-D		
								CCW	5-5-5, 2-2-2	2-D		
THREE PHASE WYE π	240 ++	50/60	0-240	25	10.40	30	12.5	CW	2-2-2	4-4-4 3-3-3		
		60	0-280	25	12.10	—	—	CCW	4-4-4	2-2-2 3-3-3		
								CW	1-1-1	4-4-4 3-3-3		
								CCW	5-5-5	2-2-2 3-3-3		
UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ±				UNITS		TITLE: SPEC. CONTROL DRAWING VARIABLE TRANSFORMER MODEL: 2510-3						
DECIMALS		Holes		ANGLES							DRAFT	
XX .0005		.01		1°							1-1/2°	
MATERIAL:				ALL DIMENSIONS APPLY AFTER PLATING								
The information and design disclosed herein was originated by and is the property of STACO ENERGY PRODUCTS CO., which reserves all patent, proprietary, design, manufacturing, reproduction, use and sale rights thereto, and to any article disclosed therein except to the extent rights are expressly granted to others. The foregoing does not apply to vendor proprietary parts.						DRAWN BY		DATE	FIRST USED ON	DO NOT SCALE DWG.	CUSTOMER APPROVAL	DATE
						S.A. SMITH		12/28/00				
						CHECKER		DATE	WEIGHT APPROX. 68 LBS	CODE IDENT. NO. 83008	DWG. SIZE	DWG. NO.
						ENGINEER		DATE	SCALE 1/2	SHEET 1 OF 1	D	031-4325

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: org@lifeelectronics.ru

www.lifeelectronics.ru