

Small Signal Transistors

TO-39 Case (Continued)



TYPE NO.	DESCRIPTION	V _{CBO}	V _{CEO}	V _{EBO}	I _{CBO}	@ V _{CB}	h _{FE}		@ I _C	@ V _{CE}	V _{CE(SAT)}	@ I _C	f _T	C _{ob}	t _{on}	t _{off}	NF
		(V)	(V) *V _{CER}	(V)	(μA) *I _{CEO} **I _{CES} ***I _{CEV} ****I _{CER}	(V)	MIN	MAX	(mA)	(V)	(V)	(mA)	(MHz) *TYP	(pF) *TYP	(ns) *TYP	(ns) *TYP	(dB) *TYP
2N2854	NPN AMPL/SWITCH	60	40	5.0	0.10	40	100	300	1,000	1.0	0.40	1,000	--	--	--	--	--
2N2855	NPN AMPL/SWITCH	60	40	5.0	0.10	40	40	120	1,000	1.0	0.40	1,000	--	--	--	--	--
2N2890	NPN AMPL/SWITCH	100	80	5.0	0.50	60	30	90	1,000	2.0	0.50	1,000	30	70	--	--	--
2N2891	NPN AMPL/SWITCH	100	80	5.0	0.50	60	50	150	1,000	2.0	0.50	1,000	30	70	--	--	--
2N2904A	PNP AMPL/SWITCH	60	60	5.0	0.10	50	40	120	150	10	0.40	150	200	8.0	--	--	--
2N2905A	PNP AMPL/SWITCH	60	60	5.0	0.10	50	100	300	150	10	0.40	150	200	8.0	--	--	--
2N2927	PNP AMPL/SWITCH	30	25	4.0	--	--	30	130	50	5.0	0.25	50	100	20	--	--	--
2N2951	NPN AMPL/SWITCH	60	20	5.0	0.10	50	20	150	10	10	0.50	150	200	8.0	--	--	--
2N2958	NPN AMPL/SWITCH	60	20	5.0	0.025	50	40	120	150	10	0.50	150	250	8.0	--	--	--
2N2959	NPN AMPL/SWITCH	60	20	5.0	0.025	50	100	300	150	10	0.50	150	250	8.0	--	--	--
2N2960	NPN AMPL/SWITCH	60	30	5.0	--	--	100	300	150	10	0.50	150	250	8.0	--	--	--
2N2961	NPN AMPL/SWITCH	60	30	5.0	--	--	100	300	150	10	2.00	500	250	8.0	--	--	--
2N3015	NPN CORE DRIVER	60	30	5.0	0.20	30	30	120	150	10	0.40	150	250	8.0	--	60	--
2N3019	NPN AMPL/SWITCH	140	80	7.0	0.10	90	100	300	150	10	0.20	150	100	12	--	--	--
2N3020	NPN AMPL/SWITCH	140	80	7.0	0.10	90	40	120	150	10	0.20	150	100	12	--	--	--
2N3053	NPN AMPL/SWITCH	60	40	5.0	0.25	30	50	250	150	10	1.40	150	100	15	--	--	--
2N3072	PNP AMPL/SWITCH	60	60	4.0	0.01**	30	30	130	50	1.0	1.00	300	130	10	--	--	--
2N3107	NPN AMPL/SWITCH	100	60	7.0	0.01**	60	100	300	150	10	1.00	1,000	70	20	--	--	--
2N3108	NPN AMPL/SWITCH	100	60	7.0	0.01*	60	40	120	150	10	1.00	1,000	60	20	--	--	--
2N3109	NPN AMPL/SWITCH	80	40	7.0	0.01*	60	100	300	150	10	0.25	150	70	25	--	--	--
2N3110	NPN AMPL/SWITCH	80	40	7.0	0.01*	60	40	120	150	10	0.25	150	60	25	--	--	--
2N3114	NPN HIGH VOLTAGE	150	150	5.0	0.01	100	30	120	30	10	1.00	50	40	9.0	--	--	--
2N3119	NPN AMPL/SWITCH	100	80	4.0	50	60	50	200	100	10	0.50	100	250	6.0	40	700	--
2N3120	PNP AMPL/SWITCH	45	45	4.0	0.01*	30	30	130	150	1.0	0.50	300	130	10	--	--	--
2N3122	NPN AMPL/SWITCH	50	30	5.0	--	--	25	100	300	10	1.50	300	60	25	--	--	--
2N3133	PNP AMPL/SWITCH	50	35	4.0	0.50	30	40	120	150	10	0.60	150	200	10	--	--	--
2N3134	PNP AMPL/SWITCH	50	35	4.0	0.50	30	100	300	150	10	0.60	150	200	10	--	--	--
2N3137	NPN VHF/UHF OSC	40	20	4.0	0.50	20	20	120	50	5.0	0.30	50	500	3.5	--	--	--
2N3244	PNP CORE DRIVER	40	40	5.0	0.50	30	50	150	500	1.0	1.00	1,000	175	25	50	185	--
2N3245	PNP CORE DRIVER	50	50	5.0	0.50	30	30	90	500	1.0	1.20	1,000	150	25	55	165	--
2N3252	NPN CORE DRIVER	60	30	5.0	0.50	40	30	90	500	1.0	1.00	1,000	200	12	45	70	--
2N3253	NPN CORE DRIVER	75	40	5.0	0.50	60	25	75	500	1.0	1.20	1,000	175	12	50	70	--
2N3299	NPN AMPL/SWITCH	60	30	5.0	0.01**	50	40	120	150	10	0.60	500	250	8.0	60	150	--
2N3300	NPN AMPL/SWITCH	60	30	5.0	0.01**	50	100	300	150	10	0.60	500	250	8.0	60	150	--
2N3326	NPN AMPL/SWITCH	60	40	5.0	0.10	50	40	120	150	10	0.40	150	250	8.0	--	--	--
2N3388	NPN AMPL/SWITCH	125	100	6.0	--	--	60	--	2.5	5.0	1.00	2.5	36	35	--	--	--
2N3420	NPN AMPL/SWITCH	85	60	6.0	0.50***	80	40	160	1,000	2.0	0.50	2,000	40	150	--	--	--
2N3421	NPN AMPL/SWITCH	125	80	8.0	0.50***	120	40	160	1,000	2.0	0.50	2,000	40	150	--	--	--
2N3439	NPN HIGH VOLTAGE	450	350	7.0	20	360	40	160	20	10	0.50	50	15	10	--	--	--
2N3440	NPN HIGH VOLTAGE	300	250	7.0	20	250	40	160	20	10	0.50	50	15	10	--	--	--

(04-April 2014)

OUTSTANDING SUPPORT AND SUPERIOR SERVICES



PRODUCT SUPPORT

Central's operations team provides the highest level of support to insure product is delivered on-time.

- Supply management (Customer portals)
- Inventory bonding
- Consolidated shipping options
- Custom bar coding for shipments
- Custom product packing

DESIGNER SUPPORT/SERVICES

Central's applications engineering team is ready to discuss your design challenges. Just ask.

- Free quick ship samples (2nd day air)
- Online technical data and parametric search
- SPICE models
- Custom electrical curves
- Environmental regulation compliance
- Customer specific screening
- Up-screening capabilities
- Special wafer diffusions
- PbSn plating options
- Package details
- Application notes
- Application and design sample kits
- Custom product and package development

REQUESTING PRODUCT PLATING

1. If requesting Tin/Lead plated devices, add the suffix " TIN/LEAD" to the part number when ordering (example: 2N2222A TIN/LEAD).
2. If requesting Lead (Pb) Free plated devices, add the suffix " PBFREE" to the part number when ordering (example: 2N2222A PBFREE).

CONTACT US

Corporate Headquarters & Customer Support Team

Central Semiconductor Corp.
145 Adams Avenue
Hauppauge, NY 11788 USA
Main Tel: (631) 435-1110
Main Fax: (631) 435-1824
Support Team Fax: (631) 435-3388
www.centrasemi.com

Worldwide Field Representatives:
www.centrasemi.com/wwreps

Worldwide Distributors:
www.centrasemi.com/wwdistributors

For the latest version of Central Semiconductor's **LIMITATIONS AND DAMAGES DISCLAIMER**, which is part of Central's Standard Terms and Conditions of sale, visit: www.centrasemi.com/terms

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкуренспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: org@lifeelectronics.ru