



Main

|                              |                                                                                                      |
|------------------------------|------------------------------------------------------------------------------------------------------|
| Range of product             | Integral 32                                                                                          |
| Device short name            | LX1                                                                                                  |
| Product or component type    | Coil                                                                                                 |
| [Uc] control circuit voltage | 24 V AC 50 Hz                                                                                        |
| Power consumption in VA      | 10...16 VA AC network 50 Hz sealed (cos φ 0.28)<br>150...200 VA AC network 50 Hz inrush (cos φ 0.55) |
| Value of inductance          | 0.142 mH closed circuit                                                                              |
| Average resistance           | 1.78 Ohm at 68 °F (20 °C) +/- 10 %                                                                   |

Complementary

|                |                       |
|----------------|-----------------------|
| Product weight | 0.26 lb(US) (0.12 kg) |
|----------------|-----------------------|

Environment

Offer Sustainability

|                                                                                                |                                                                                                |
|------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------|
| Not Green Premium product                                                                      | Not Green Premium product                                                                      |
| Compliant - since 0702 - Schneider Electric declaration of conformity                          | Compliant - since 0702 - Schneider Electric declaration of conformity                          |
| Available                                                                                      | Available                                                                                      |
| Available                                                                                      | Available                                                                                      |
| WARNING: This product can expose you to chemicals including:                                   | WARNING: This product can expose you to chemicals including:                                   |
| Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer. | Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer. |
| For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>  | For more information go to <a href="http://www.p65warnings.ca.gov">www.p65warnings.ca.gov</a>  |

Contractual warranty

|                 |           |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

The information provided in this documentation contains general descriptions and/or technical characteristics of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: [org@lifeelectronics.ru](mailto:org@lifeelectronics.ru)

[www.lifeelectronics.ru](http://www.lifeelectronics.ru)