



RS-1007 PRO CAT IV Analog Clamp

This CAT IV 600V safety rated analog clamp is a great tool for tough electrical applications. The RS-1007 PRO works well in extreme temperatures of 32°F to 5°F, while digital clamp LCD screens tend to freeze this analog clamp measures up to the test. The RS-1007 PRO does not require batteries for measuring Amps and Volts.

- Measures AC Current up to 1000A
- Voltage up to 600 VAC
- Resistance and Continuity
- Pointer Lock - Data hold
- Easy to use Rotary Scale
- Measures Volts and Amps, no batteries required
- Works in temperatures from 5°F to 122°F
- Operates on 50 and 60 Hz frequency
- CAT IV, 600 V Safety Rated
- Includes test leads, battery (installed, for resistance measurement only), Users Manual, Carrying Case

No hassle warranty

No waiting.

*No shipping
charges.*



Our commitment to high-quality products and customer service is demonstrated by our industry exclusive "No Hassle" warranty. In the unlikely event that an Amprobe Test Tool requires warranty service, any of our local dealers are authorized to replace it, on the spot.

(note: \$500 MSLP limit)





RS-1007 PRO CAT IV Analog Clamp

Data Sheet

Specifications

General

Display	Analog scales with clamping needle
Dimension	261 x 102 x 41 mm (10.3 x 4.0 x 1.6 in.)
Weight	0.474 kg (1.05 lb.)
Jaw opening / Conductor diameter	47mm (1.88") max

Power Supply

Volt/ amp	powered by circuit under test
Ohm	1.5 V AAA battery (ANSI/NEDA-24A, IEC LR03)
Low Battery	Below approx. 1.2 V
Environmental	Indoor operation; below 2000m (6,562ft)
Operating Temperature	-15°C to 50°C (5°F to 122°F) ; < 80%
Storage Temperature	-20°C to 60°C (-4°F to 140°F), < 80% R.H. (with battery removed)
Temperature Coefficient	nominal 0.15 x (specified accuracy)/°C @ 0°C - 18°C or 28°C - 40°C (32°F - 64°F or 82°F - 104°F)

Safety LVD

Category IV – 600 Volts ac
Meets EN60101-1:2001; EN61010-2-032(2002; pollution degree : II; class 2

CE EMC

EN 61326-1:2006

Electrical [23°C ± 5°C (73°C ± 9°C)]

AC Voltage (50/60 Hz)

Ranges	150 / 300 / 600 Vrms
Accuracy	± 3 % of Full Scale.
Input Impedance	1.5 MΩ
OL Protection	600 V ac rms

AC Amp (50/60 Hz)

Ranges	6 / 15 / 40 / 100 / 600 Arms
Accuracy	± 3 % of Full Scale

Ohms

Range	1000 ohms; 25 Ohms mid-scale
Accuracy	± 3 degrees of Arc
Open Circuit voltage	1.5v
Short circuit Current	xx mA
OL Protection	(F 0.5 A / 1000 V, size 6 x 32 mm IR fast blow ceramic)

Optional Accessories

TL-1500	Test leads with set of alligator clips
CC-RS	Deluxe Carrying Case

Amprobe® Test Tools

website: www.Amprobe.com
email: info@amprobe.com
Everett, WA 98203
Tel: 877-AMPROBE

Amprobe® Test Tools Europe

Amprobe Test Tools Europe
Beha-Amprobe GmbH
In den Engematten 14
79286 Glottertal, Germany
Tel.: +49 (0) 7684 8009 - 0

©2009 Amprobe Test Tools. All rights reserved.
03/2009 3465207 Rev A

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: org@lifeelectronics.ru

www.lifeelectronics.ru