



90-T40F1



90-T40S3



90-T75C3

90-T40S1 THRU 90-T75C3 24 VOLT SECONDARY CLASS 2 TRANSFORMERS ENERGY LIMITING

For Industrial, Heating and Air Conditioning Controls Applications

FEATURES

- Color coded primary leads.
- Multi-mount styles available.

SPECIFICATIONS

Agency U.L. file number **cULus** E33334

MULTI-MOUNT (CLOSED CONSTRUCTION) UNIVERSAL MOUNTING WITH PLATE

Model Number	Mars Part No.	Jard Part No.	VA	Hz	Primary	Connections	Sec.	Connections
90-T40M1	50302	4011M	40	60	120V	Leads	24V	Leads
90-T40M2	50303	4021M	40	50/60	208/240V	Leads	24V	Leads
90-T40M3	50304	4031M	40	60	120/208/240V	Leads	24V	Leads
90-T50M3	50314	5031M	50	60	120/208/240V	Leads	24V	Leads

FOOT-MOUNT (OPEN CONSTRUCTION)

Model Number	Mars Part No.	Jard Part No.	VA	Hz	Primary	Connections	Sec.	Connections
90-T40F1	50352	4011F	40	60	120V	Leads	24V	Leads
90-T40F2	50353	4021F	40	50/60	208/240V	Leads	24V	Leads
90-T40F3	50354	4031F	40	60	120/208/240V	Leads	24V	Leads
T40-24	—	—	40	50/60	120/208/240V	Leads	24V	Leads
90-T50F3	—	5031F	50	60	120/208/240V	Leads	24V	Leads

FOOT-MOUNT (MANUAL RESET, OPEN CONSTRUCTION)

Model Number	Mars Part No.	Jard Part No.	VA	Hz	Primary	Connections	Sec.	Connections
90-T50C3	50327	5041C	50	50/60	120/208/240V	Leads	24V	Leads
90-T60C3	50327	6041C	60	50/60	120/208/240V	Leads	24V	Leads
90-T75C3	50321	7541C	75	50/60	120/208/240V	Leads	24V	Leads
90-T100C1	—	—	100	60	120V	Leads	25V	Leads
90-T100C2	—	—	100	50/60	208/240V	Leads	25V	Leads

TRANSFORMER LEAD COLOR CODING

Primary Side			Secondary Side	
Common	120V	208V	Common	24V
* Black	White	Red	Blue	Yellow

* Black is common with respect to the transformer winding, not the external circuit.



5401A-1

WALL PLUG-IN

Isolation Step Down Transformer

FEATURES

- Sealed tamper and impact resistant case.
- Output termination is screw terminals.
- Non-polarized 120V plug-in blades.
- Trouble free maintenance.
- Isolated from power source.

SPECIFICATIONS

Dimensions, **5401A-1** 3"H x 2 1/2"W x 1 3/4"D
 Dimensions, **5402A-1** 3"H x 2 3/4"W x 2 1/4"D
 Output terminals #6-32 screws
 Agency ratings C.S.A. and U.L. class 2

Model Number	Primary	Secondary
5401A-1	120VAC, 60 Hz, 0.14A	24VAC, 10VA
5402A-1	120VAC, 60 Hz, 0.31A	24VAC, 25VA

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: org@lifeelectronics.ru

www.lifeelectronics.ru