






Possible references:

USB3 FTV 7 A N F312 Nickel plating
USB3 FTV 7 A G F312 Olive drab cadmium plating
USB3 FTV 7 A ZN F312 Black zinc nickel plating

! For PC to peripheral application
use a "CROS" USB3 crossed cord set

! For PC to PC application
use a "STR" USB3 straight cord set



Panel drilling

Pin assignments:

USB 3.0 Standard A front coupling side connector to USB 3.0 Standard A back side connector					
Pin number	Signal name	Description	Sequence	Pin number	Signal name
1	VBUS	Power	Second	1	VBUS
2	D-	USB 2.0 differential pair	Third	2	D-
3	D+			3	D+
4	GND	Ground for power return	Second	4	GND
5	StdA_SSRX-	Superspeed receiver differential pair	Last	8	StdB_SSTX-
6	StdA_SSRX+			9	StdB_SSTX+
7	GND_DRAIN	Ground for signal return		7	GND_DRAIN
8	StdA_SSTX-	Superspeed transmitter differential pair	First	5	StdB_SSRX-
9	StdA_SSTX+			6	StdB_SSRX+
Shell	Shield	Connector metal shell	First	Shell	Shield

Always crossed

USB3 FTV 7 A X F312

Reduced Flange

USB3.0 Standard A Receptacle

Customer Approval _____

MODIFICATIONS

A	Plan original	ECHELLE
		2,5

Amphenol Socapex

BP 29 - 74311 THYEZ CEDEX


DESSIN: M.Peters LE: 11/01/17

TECHNIQUE: L.Guyomar LE: 11/01/17

A

191-PLC-742-00 1/2

DANS LE BUT CONSTANT D'AMELIORER SES PRODUITS, Amphenol Socapex SE RESERVE LE DROIT D'EN MODIFIER TOUTE COTE OU CARACTERISTIQUE.
IMP 036 A




Possible references:

USB3 FTV 7 B N F312 Nickel plating
USB3 FTV 7 B G F312 Olive drab cadmium plating
USB3 FTV 7 B ZN F312 Black zinc nickel plating

⚠ For PC to peripheral application
use a "CROS" USB3 crossed cord set

⚠ For PC to PC application
use a "STR" USB3 straight cord set




Panel o-ring is delivered with the receptacle

Pin assignments:

USB 3.0 Standard A front coupling side connector to USB 3.0 Standard A back side connector					
Pin number	Signal name	Description	Sequence	Pin number	Signal name
1	VBUS	Power	Second	1	VBUS
2	D-	USB 2.0 differential pair	Third	2	D-
3	D+			3	D+
4	GND	Ground for power return	Second	4	GND
5	StdA_SSRX-	Superspeed receiver differential pair	Last	8	StdB_SSTX-
6	StdA_SSRX+			9	StdB_SSTX+
7	GND_DRAIN	Ground for signal return		7	GND_DRAIN
8	StdA_SSTX-	Superspeed transmitter differential pair		5	StdB_SSRX-
9	StdA_SSTX+			6	StdB_SSRX+
Shell	Shield	Connector metal shell	First	Shell	Shield

Always crossed



Panel drilling

USB3 FTV 7 B X F312

Reduced Flange

USB3.0 Standard A Receptacle

Customer Approval _____

MODIFICATIONS

A	Plan original	ECHELLE
		2,5

Amphenol Socapex

BP 29 - 74311 THYEZ CEDEX

DESSIN: M.Peters LE: 11/01/17

TECHNIQUE: L.Guyomar LE: 11/01/17

A

--	--	--	--	--	--	--	--	--	--

191-PLC-742-00 2/2

Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: org@lifeelectronics.ru

www.lifeelectronics.ru