

# MIL-F-19207 military qualified panel-mount fuse holders

| * Bussmann™ series     |                        |                       |                    |                          |                          |                 |                      |             |          |
|------------------------|------------------------|-----------------------|--------------------|--------------------------|--------------------------|-----------------|----------------------|-------------|----------|
| Military specification | Government designation | commercial equivalent | Electrical ratings | Fuse family accommodated | Knob Type                | Number of poles | Max. panel thickness |             |          |
| MIL-F-19207/1          | FHL10U                 | HGA-C                 | 30 A, 90-250 V     | F02, F03                 | Clear, neon, F-S         | 2               | 1/8"                 |             |          |
| MIL-F-19207/1          | FHL10G                 | —                     |                    |                          |                          |                 |                      |             |          |
| MIL-F-19207/2          | FHL11U                 | HGB-C                 |                    | F60, F07, F09            | Clear, neon, Oct.        |                 |                      |             |          |
| MIL-F-19207/2          | FHL11G                 | —                     |                    |                          |                          |                 |                      |             |          |
| MIL-F-19207/3          | FHL12U                 | HGC Series            |                    |                          |                          |                 |                      |             |          |
| MIL-F-19207/3          | FHL12G                 | —                     |                    |                          |                          |                 |                      |             |          |
| MIL-F-19207/8          | FHL17G1                | HKL                   | 20 A, 90-250 V     | F02, F03                 | Amber, incandescent, F-S | 1               | 1/16"                |             |          |
| MIL-F-19207/9          | FHL18G1-1              |                       | 20 A, 12-22 V      |                          |                          |                 |                      |             |          |
| MIL-F-19207/9          | FHL18G1-2              | HKX                   | 20 A, 23-33 V      |                          |                          |                 |                      |             |          |
| MIL-F-19207/9          | FHL18G1-3              |                       | 20 A, 34-45 V      |                          |                          |                 |                      |             |          |
| MIL-F-19207/9          | FHL18G1-4              |                       | 20 A, 46-60 V      |                          |                          |                 |                      |             |          |
| MIL-F-19207/9          | FHL18G1-5              |                       | 20 A, 61-80 V      |                          |                          |                 |                      |             |          |
| MIL-F-19207/9          | FHL18G1-6              |                       | 20 A, 81-90 V      |                          |                          |                 |                      |             |          |
| MIL-F-19207/9          | FHL18G1-7              |                       | 20 A, 2.5-4 V      |                          |                          |                 |                      |             |          |
| MIL-F-19207/9          | FHL18G1-8              |                       | 20 A, 5-7 V        |                          |                          |                 |                      |             |          |
| MIL-F-19207/9          | FHL18G1-9              |                       | 20 A, 8-12 V       |                          |                          |                 |                      |             |          |
| MIL-F-19207/10         | FHN19G†                |                       | HCM                |                          |                          |                 |                      | 15 A, 250 V | F05, F06 |
| MIL-F-19207/11         | FHN20G                 | HTA                   | 20 A, 250 V        | F02, F03                 |                          |                 |                      |             |          |
| MIL-F-19207/12         | FHL22W†                | HPF-C                 | 15 A, 250 V        | F10                      | Clear                    |                 |                      |             |          |
| MIL-F-19207/13         | FHN23W†                | HPC-D                 | 30 A, 500 V        | F60, F09                 | Screw                    |                 |                      |             |          |
| MIL-F-19207/16         | FHN26G1                | HKP                   | 30 A, 250 V        |                          | Bayonet                  | 2               |                      |             |          |
| MIL-F-19207/18         | FHL29G-1               | HGN-CI                | 30 A, 12-22 V      | F02, F03                 | Amber, incandescent, F-S |                 |                      |             |          |
| MIL-F-19207/18         | FHL29G-2               |                       | 30 A, 23-33 V      |                          |                          |                 |                      |             |          |
| MIL-F-19207/18         | FHL29G-3               |                       | 30 A, 34-45 V      |                          |                          |                 |                      |             |          |
| MIL-F-19207/18         | FHL29G-4               |                       | 30 A, 46-60 V      |                          |                          |                 |                      |             |          |
| MIL-F-19207/18         | FHL29G-5               |                       | 30 A, 61-80 V      |                          |                          |                 |                      |             |          |
| MIL-F-19207/18         | FHL29G-6               |                       | 30 A, 81-90 V      |                          |                          |                 |                      |             |          |
| MIL-F-19207/19         | FHL30G-1               | HGF-C                 | 30 A, 12-22 V      |                          | 1                        | 1/8"            |                      |             |          |
| MIL-F-19207/19         | FHL30G-2               |                       | 30 A, 23-33 V      |                          |                          |                 |                      |             |          |
| MIL-F-19207/19         | FHL30G-3               |                       | 30 A, 34-45 V      |                          |                          |                 |                      |             |          |
| MIL-F-19207/19         | FHL30G-4               |                       | 30 A, 46-60 V      |                          |                          |                 |                      |             |          |
| MIL-F-19207/19         | FHL30G-5               |                       | 30 A, 61-80 V      |                          |                          |                 |                      |             |          |
| MIL-F-19207/19         | FHL30G-6               |                       | 30 A, 81-90 V      |                          |                          |                 |                      |             |          |
| MIL-F-19207/20         | FHN31G1†               | HJM                   | 5 A, 250 V         | F01                      | Bayonet                  |                 | 1/16"                |             |          |
| MIL-F-19207/26         | FHN42W                 | HWA-AF                | 5 A, 125 V         | FM01                     | —                        |                 |                      |             |          |
| MIL-F-19207/36         | FHN55W                 | HKP/RFI               | 30 A, 250 V        | F02, F03                 | RFI Shield               |                 | 1/8"                 |             |          |
| MIL-F-19207/38         | FHL57G                 | —                     | 15 A, 125 V        | F77A                     | Clear, neon, F-S         | 2               |                      |             |          |

## Designation/description

FHL = Indicating holder  
FHN = Non-indicating holder  
F-S = Flat-sided knob  
G = Drip proof  
Oct. = Octagonal knob  
U = Unsealed  
W = Waterproof

\* Commercial equivalent part number is for basic design reference only, NOT intended to be used as a substitute for the military part number.

† These government designations are obsolete. Their appearance in this table is for historical reference only.



Powering Business Worldwide

The only controlled copy of this data sheet is the electronic read-only version located on the Eaton network drive. All other copies of this document are by definition uncontrolled. This bulletin is intended to clearly present comprehensive product data and provide technical information that will help the end user with design applications. Eaton reserves the right, without notice, to change design or construction of any products and to discontinue or limit distribution of any products. Eaton also reserves the right to change or update, without notice, any technical information contained in this bulletin. Once a product has been selected, it should be tested by the user in all possible applications.

**Eaton**  
1000 Eaton Boulevard  
Cleveland, OH 44122  
Eaton.com

Bussmann Division  
114 Old State Road  
Ellisville, MO 63021  
United States  
Eaton.com/bussmannseries

© 2018 Eaton  
All Rights Reserved  
Printed in USA  
Publication No. 1214 — BU-SB08838  
September 2018



Eaton and Bussmann are valuable trademarks of Eaton in the US and other countries. You are not permitted to use the Eaton trademarks without prior written consent of Eaton.

For Eaton's Bussmann series product information, call **1-855-287-7626** or visit: **Eaton.com/bussmannseries**

Follow us on social media to get the latest product and support information.



Компания «Life Electronics» занимается поставками электронных компонентов импортного и отечественного производства от производителей и со складов крупных дистрибьюторов Европы, Америки и Азии.

С конца 2013 года компания активно расширяет линейку поставок компонентов по направлению коаксиальный кабель, кварцевые генераторы и конденсаторы (керамические, пленочные, электролитические), за счёт заключения дистрибьюторских договоров

Мы предлагаем:

- Конкурентоспособные цены и скидки постоянным клиентам.
- Специальные условия для постоянных клиентов.
- Подбор аналогов.
- Поставку компонентов в любых объемах, удовлетворяющих вашим потребностям.
- Приемлемые сроки поставки, возможна ускоренная поставка.
- Доставку товара в любую точку России и стран СНГ.
- Комплексную поставку.
- Работу по проектам и поставку образцов.
- Формирование склада под заказчика.
- Сертификаты соответствия на поставляемую продукцию (по желанию клиента).
- Тестирование поставляемой продукции.
- Поставку компонентов, требующих военную и космическую приемку.
- Входной контроль качества.
- Наличие сертификата ISO.

В составе нашей компании организован Конструкторский отдел, призванный помогать разработчикам, и инженерам.

Конструкторский отдел помогает осуществить:

- Регистрацию проекта у производителя компонентов.
- Техническую поддержку проекта.
- Защиту от снятия компонента с производства.
- Оценку стоимости проекта по компонентам.
- Изготовление тестовой платы монтаж и пусконаладочные работы.



Тел: +7 (812) 336 43 04 (многоканальный)

Email: [org@lifeelectronics.ru](mailto:org@lifeelectronics.ru)

[www.lifeelectronics.ru](http://www.lifeelectronics.ru)